



Reference Designs

Version 23.8.1, 12 September 2023

Table of Contents

1. RBFS C-BNG for IPoE Subscribers	1
1.1. Overview	1
1.2. Configuration and Settings	4
1.3. Protocol Configurations	19
1.4. IPoE Subscriber Management Configuration	32
1.5. Appendixes	67
2. RBFS C-BNG with Redundancy for IPoE Subscribers	69
2.1. RBFS C-BNG with Redundancy for IPoE Subscribers	69
2.2. RBFS Redundancy Configurations	72

1. RBFS C-BNG for IPoE Subscribers

1.1. Overview

This document provides guidance to validate IPoE implementation using the RBFS Consolidated BNG (C-BNG). The guide contains quick information about general platform configuration, configuration of various access and routing protocols, subscriber management, Quality of Service (QoS) and troubleshooting. The document presents a single use case scenario and provides information specifically on how to validate this particular implementation and for more information on any specific application, refer to <https://documents.rtbrick.com/>.

This guide is not intended to be an exhaustive guide of all RBFS features and does not provide information on features such as Multicast, Lawful Intercept etc.

About the RBFS Consolidated BNG

The RtBrick C-BNG is delivered as a container, running on Open Network Linux (ONL) provided by the hardware ODM manufacturers. Platforms that support C-BNG include Edgecore AGR 400, CSR 320, and UfiSpace S9600. The RtBrick C-BNG software runs on powerful bare-metal switches as an open BNG.

The BNG is designed to dynamically deliver the following services:

1. Discovering and managing subscriber sessions for IPoE subscribers
2. Providing authentication, authorization and accounting (AAA)

The basic C-BNG architecture for IPoE subscribers is shown in Fig. 1.




Fig. 1: Topology setup with **C-BNG** as a DUT (device under test) connected to BNG Blaster.

In this topology:

1. The Service Node is an Ubuntu server on which a new container is spawned with the associated interfaces for running BNG Blaster tests.
2. Rtbrick's home grown BNG Blaster emulates both the routing and access functions and, in effect, tests the DUT.
3. The topology emulates IPoE subscribers and traffic between RBFS switch and the core network.
4. The objective of this topology is to demonstrate complete IPoE subscriber emulating and service along with routing to connect to the network uplink.
5. R-1, R-2 and RR are simulated using BNG Blaster. The **C-BNG** forms an IS-IS L1 adjacency with the BNG blaster to discover R-1, R-2, and RR. The RR is the route

reflector that replays a full internet feed of IPv4 and IPv6 addresses, in total about 1.1 million prefixes. R-2 is the nexthop for all internet routes.

6. Through DCHP, an IPv4 address needs to be assigned to the out-of-band management port.

Deployment

A C-BNG provides BNG functionality on a single bare-metal switch and eliminates the need to have a chassis based system. It provides a low footprint and optimal power consumption based on BRCM chipsets, a compelling value proposition that has complete BNG and routing feature support.

C-BNG runs on small form-factor temperature hardened hardware that allows deployments in street site cabinets.

The rtbrick-toolkit is a meta package that can be used to install all the tools needed to work with RBFS images (container or ONL installer) and the RBFS APIs.

For more information, see [RBFS and Tools Installation, and RBFS Licensing Guide](#).

Using the RBFS CLI

Connect to the [C-BNG](#) node.

```
$ ssh <C-BNG-management-ip> -l supervisor
supervisor@<C-BNG-management-ip>'s password:
```

The password for [C-BNG-management-ip](#) should be entered here.

As a result, the CLI prompt will look like this:

```
supervisor@rtbrick>C-BNG.rtbrick.net:~ $
```

Open the RBFS CLI.

```
supervisor@rtbrick>C-BNG.rtbrick.net:~ $ cli
```

The CLI has three different modes:

- [operation](#) mode is a read-only mode to inspect and analyse the system state

- **config** mode allows modifying the RBFS configuration
- **debug** mode provides advanced tools for trouble-shooting

The **switch-mode** command allows switching between the different modes. The **show** commands allow inspecting the system state. The **set** and **delete** commands, which are only available in the configuration mode, allow modifying or deleting the current configuration. The **commit** command persists the changes. RBFS provides a commit history which allows reviewing changes (**show commit log**) and restoring a previous configuration (**rollback**). There are also commands to **ping** destinations, **capture** network traffic, **save** the configuration to or **load** the configuration from a file.

The CLI supports abbreviating commands, provides suggestions by hitting the **[tab]** key and displays a context help by entering a **?**.

For more information on how to use the RBFS CLI, see the [RBFS CLI User Guide](#).

1.2. Configuration and Settings

Platform Configuration and Settings

This section provides information about the platform and how to set various required configurations for the platform.

Know your Device

The configurations provided in this reference design document (C-BNG IPoE implementation) are generated on the UfiSpace S9600-72XC platform. The UfiSpace S9600-72XC is a multi-function, disaggregated white box aggregation routing platform that is equipped with Broadcom's Qumran2c chipset. It features 64x25GE [1GbE/10GbE/25GbE] and 8x100GE [40GbE/100GbE] high-speed ports with a switching capacity of up to 2.4Tbs.

The RBFS C-BNG software is installed on top of the UfiSpace S9600-72XC.



Although the specific device used here is UfiSpace S9600-72XC, the configuration will stay exactly the same for any other device that supports the C-BNG image.

For more information about the hardware specifications of UfiSpace S9600-72XC,

see [Hardware Specification](#).

Prerequisites

- Access to BNG Blaster, an open-source network testing platform for access and routing protocols. For information on obtaining and building BNG Blaster, see <https://rtbrick.github.io/bngblaster/>.
- Access to FreeRADIUS, a free RADIUS suite. For accessing FreeRADIUS, see <https://freeradius.org/>.
- Access to Syslog server.

Restore Configuration

Depending on the deployment scenario, a running configuration can be applied or restored as needed.

To enable configuration restore, enter the `set system load-last-config true` command as shown below.

```
supervisor@rtbrick>C-BNG.rtbrick.net: cfg> set system load-last-config true  
supervisor@rtbrick>C-BNG.rtbrick.net: cfg> commit
```

For more information, see section "2.3. Running Configuration" of the [RBFS NOC Troubleshooting Guide](#).

General Configuration

To enable testing some basic primitives need to be configured. These general configurations include loopback interface for identifying and accessing the device on network, NTP for setting accurate time across a whole network of devices, TACACS+ for user authentication, user management for user configuration, license for accessing RBFS, Resmon for resource monitoring, and Syslog configurations for exporting the log message to the external log management server.

Configure License

Without any license installed on your system, you can evaluate RBFS for 7 days. You need to get an evaluation license or purchase an actual license within 7 days to use the full functionality of RBFS.

The following steps provide the commands to install an RBFS license key. For more information about license configuration, see [Installing License](#).

Switch to config mode using the switch-mode config command to continue with the RBFS configurations.

```
supervisor@rtbrick>C-BNG.rtbrick.net: op> switch-mode config  
supervisor@rtbrick>C-BNG.rtbrick.net: cfg>
```

Install the license encrypted string (that is received from RtBrick) using the RBFS CLI.

```
supervisor@rtbrick>C-BNG.rtbrick.net: cfg> set system license <license-key>
```

RBFS license configuration is shown below:

```
supervisor@rtbrick>C-BNG.rtbrick.net: op> show config system license  
AAAAWsfg&jdkfs4D34H5@2evf...
```

As shown below, the "show system license" command displays the expiration date for the current license.

```
supervisor@rtbrick>C-BNG.rtbrick.net: op> show system license  
License Validity:  
License index 1:  
Start date : Tue Feb 28 09:44:27 GMT +0000 2023  
End date   : Mon Mar 04 09:44:27 GMT +0000 2024  
supervisor@rtbrick>C-BNG.rtbrick.net: op>
```

Configure Instance

Instance **default** will be available by default without any configurations.

Create the instance **inband_mgmt** by entering the following commands.

```
set instance inband_mgmt  
set instance inband_mgmt address-family ipv4 unicast  
commit
```

The configurations of the instance **inband_mgmt** are shown below.

```
supervisor@rtbrick>C-BNG.rtbrick.net: cfg> show config instance inband_mgmt
```

```
{
  "rtbrick-config:instance": [
    {
      "name": "inband_mgmt",
      "address-family": [
        {
          "afi": "ipv4",
          "safi": "unicast"
        }
      ]
    }
  ]
}
```

Below are the configurations available for the available instances.

```
supervisor@rtbrick>C-BNG.rtbrick.net: cfg> show instance detail
Instance: default
  Instance ID: 0
  State: Active
    AFI      SAFI      State
    ipv4    unicast    Active
    ipv4    multicast   Active
    ipv4    labeled-unicast Active
    ipv6    unicast    Active
    ipv6    multicast   Active
    ipv6    labeled-unicast Active
    mpls   unicast    Active
Instance: inband_mgmt
  Instance ID: 3
  State: Active
    AFI      SAFI      State
    ipv4    unicast    Active
```

Configure Loopback Interface

Loopback Interface configuration is required as it is the best way to identify a network device and is always reachable. Also, protocols use the loopback address to determine protocol-specific properties for the device.

The following steps provide the commands to configure the loopback interface. For more information about Loopback Interface configuration, see [Interfaces User Guide](#).

Configure loopback interface on the device.

```
set interface lo-0/0/1 unit 0 address ipv4 192.0.2.64/32
set interface lo-0/0/1 unit 1 address ipv4 192.0.2.74/32
set interface lo-0/0/1 unit 2 instance inband_mgmt
set interface lo-0/0/1 unit 2 address ipv4 192.0.2.128/32
set interface lo-0/0/1 unit 3 instance inband_mgmt
```

```
set interface lo-0/0/1 unit 3 address ipv4 192.0.2.131/32
commit
```



The configuration commands should be followed by the **commit** command to save the configurations into the device.

```
supervisor@rtbrick>C-BNG.rtbrick.net: cfg> commit
```

Loopback Interface configuration is shown below:

```
supervisor@rtbrick>C-BNG.rtbrick.net: cfg> show config interface lo-0/0/1
{
    "rtbrick-config:interface": [
        {
            "name": "lo-0/0/1",
            "unit": [
                {
                    "unit-id": 0,
                    "address": {
                        "ipv4": [
                            {
                                "prefix4": "192.0.2.64/32"
                            }
                        ]
                    }
                },
                {
                    "unit-id": 1,
                    "address": {
                        "ipv4": [
                            {
                                "prefix4": "192.0.2.74/32"
                            }
                        ]
                    }
                },
                {
                    "unit-id": 2,
                    "instance": "inband_mgmt",
                    "address": {
                        "ipv4": [
                            {
                                "prefix4": "192.0.2.128/32"
                            }
                        ]
                    }
                },
                {
                    "unit-id": 3,
                    "instance": "inband_mgmt",
                    "address": {
                        "ipv4": [
                            {
                                "prefix4": "192.0.2.131/32"
                            }
                        ]
                    }
                }
            ]
        }
    ]
}
```

```

        }
    ]
}
]
```

Configure IP Addresses for Core Interfaces

Enter the following commands to configure IP addresses for the core interfaces.

```

set interface ifp-0/1/31 unit 10
set interface ifp-0/1/31 unit 10 vlan 10
set interface ifp-0/1/31 unit 10 address ipv4 192.0.2.1/27
set interface ifp-0/1/31 unit 10 address ipv6 2001:db8::1/64
set interface ifp-0/1/31 unit 100
set interface ifp-0/1/31 unit 100 vlan 100
set interface ifp-0/1/31 unit 100 address ipv4 192.0.2.33/27
set interface ifp-0/1/31 unit 200
set interface ifp-0/1/31 unit 200 instance inband_mgmt
set interface ifp-0/1/31 unit 200 vlan 200
set interface ifp-0/1/31 unit 200 address ipv4 192.0.2.97/27
commit

```

Below configuration shows the IP address configurations for the core interfaces.

```
{
  "rtbrick-config:interface": [
    {
      "name": "ifp-0/1/31",
      "unit": [
        {
          "unit-id": 10,
          "vlan": 10,
          "address": {
            "ipv4": [
              {
                "prefix4": "192.0.2.1/27"
              }
            ],
            "ipv6": [
              {
                "prefix6": "2001:db8::1/64"
              }
            ]
          }
        },
        {
          "unit-id": 100,
          "vlan": 100,
          "address": {
            "ipv4": [
              {
                "prefix4": "192.0.2.33/27"
              }
            ]
          }
        }
      ]
    }
  ]
}
```

```
        ]
    }
},
{
    "unit-id": 200,
    "instance": "inband_mgmt",
    "vlan": 200,
    "address": {
        "ipv4": [
            {
                "prefix4": "192.0.2.97/27"
            }
        ]
    }
}
]
```

Configure Static Routes to Enable Reachability to the NTP and TACACS Servers

Below are static routes configured to enable reachability to the NTP (192.0.2.129) and TACACS (192.0.2.130) servers. On the Service Node, 192.0.2.98 is the interface address on VLAN 200. It is explained later in this document how to configure IP addresses on Service Node. For details, see [refdesign:cbrngipoe refdesign config settings::config-interface-sn].

```
set instance inband_mgmt static route ipv4 192.0.2.129/32 unicast np1
set instance inband_mgmt static route ipv4 192.0.2.130/32 unicast np1
set instance inband_mgmt static nexthop-profile np1
set instance inband_mgmt static nexthop-profile np1 nexthop 192.0.2.98
set instance inband_mgmt static nexthop-profile np1 lookup-instance inband_mgmt
set instance inband_mgmt static nexthop-profile np1 lookup-afi ipv4
set instance inband_mgmt static nexthop-profile np1 lookup-safi unicast
commit
```

The configuration of the static routes is shown below:

```
supervisor@rtbrick>C-BNG.rtbrick.net: cfg> show config instance inband_mgmt static
{
  "rtbrick-config:static": {
    "route": {
      "ipv4": [
        {
          "prefix4": "192.0.2.129/32",
          "safi": "unicast",
          "nexthop-profile": "npl"
        },
        {
        }
      ]
    }
  }
}
```

```

        "prefix4": "192.0.2.130/32",
        "safi": "unicast",
        "nexthop-profile": "np1"
    }
]
},
"nexthop-profile": [
{
    "name": "np1",
    "nexthop": "192.0.2.98",
    "lookup-instance": "inband_mgmt",
    "lookup-afi": "ipv4",
    "lookup-safi": "unicast"
}
]
}
}

```

Configure NTP

Configuring NTP (Network Time Protocol) provides time synchronization across a whole network of devices. An NTP network consists devices (clients) which are to be synchronized with the NTP server that provides accurate time to the client devices.

The following steps provide the commands to configure Network Time Protocol (NTP) for the device. For more information about NTP configuration, see [NTP User Guide](#).

Enabling NTP Service:

To access the NTP service running in the ONL, this service has to be enabled in inband-management. On configuring this, the hosts reachable in inband instance via the physical interface can access this service.

Configure NTP server and NTP service on the device.

```

set system ntp server ntp1
set system ntp server ntp1 ipv4-address 192.0.2.129
set inband-management instance inband_mgmt
set inband-management instance inband_mgmt ntp true
commit

```

NTP configuration is shown below:

```

supervisor@rtbrick>C-BNG.rtbrick.net: cfg> show config inband-management
{
    "rtbrick-config:inband-management": {

```

```

"instance": [
    {
        "name": "inband_mgmt",
        "ntp": "true"
    }
]
}

```

```

supervisor@rtbrick>C-BNG.rtbrick.net: cfg> show config system ntp
{
    "rtbrick-config:ntp": {
        "server": [
            {
                "server-name": "ntp1",
                "ipv4-address": "192.0.2.129"
            }
        ]
    }
}

```

User Authentication

RBFS supports user authentication through a centralized TACACS+ server and with a local authentication system. The following authentication process typically occurs when a user attempts to access the network.

1. When a user logs in through [SSH](#), the SSH Daemon ([sshd](#)) invokes the Pluggable Authentication Module (PAM) to trigger authentication process.
2. PAM requests TACACS+ authentication (except for the user with the [supervisor](#) privileges).
3. TACACS+ server provides 'grant access' node if the user authentication is successful.
4. If the user is not allowed using the TACACS+ authentication, it is required to undergo an additional authentication phase. PAM looks up local users. Upon successful authentication, PAM generates RTB PAM token; includes user role in 'scope'.

Define Users on TACACS+ Server

Administrator needs to define users and associate them with the predefined roles on the TACACS+ server. Optionally, RBFS CLI commands can be restricted using the [rtb-allow-cmds](#) and [rtb-deny-cmds](#).

The `tac_plus.conf` file contains configuration information for the `tac_plus`(tacacs+) daemon. This file is stored at the following location:

`/etc/tacacs+/tac_plus.conf`

To view the TACACS+ server configuration file, enter the following command.

```
sudo cat /etc/tacacs+/tac_plus.conf
```

For more information about TACACS+ server configuration, see

https://manpages.ubuntu.com/manpages/trusty/man5/tac_plus.conf.5.html

This Reference Design document uses the default local user `supervisor` for the configurations, whereas other users, defined in the TACACS server, can log into RBFS by using their usernames and passwords.

The following TACACS+ configuration shows the details of the TACACS users.

→ Click [here](#) to download the `tac_plus.conf` file.

Configure TACACS+ on RBFS

After defining the users on the TACACS+ server, configure the TACACS+ server on C-BNG. This configuration allows the remote TACACS+ server to communicate with the C-BNG and to validate user access on the network.

The following steps provide the commands to configure TACACS+. For more information about TACACS+ configuration, see [Configure TACACS+ on RBFS](#).

To access the TACACS+ service running in the ONL, this service has to be enabled in inband management. On configuring this, the hosts reachable in inband instance via the physical interface can access this service.

```
set system secure-management-status true
set system authorization tacacs 192.0.2.130 inband secret-plain-text
RtBrick_Little_Secret
set inband-management instance inband_mgmt tacacs true
commit
```

In the above configuration, the command `set inband-management instance inband_mgmt tacacs true` is used to enable TACACS+ under the instance called

inband_mgmt.

TACACS+ configuration is shown below:

```
supervisor@rtbrick>C-BNG.rtbrick.net: cfg> show config system authorization
{
  "rtbrick-config:authorization": {
    "tacacs": [
      {
        "ipv4-address": "192.0.2.130",
        "type": "inband",
        "secret-encrypted-text":
        "$22464b2c7336cf71e596c447be28d598b9b7b37f92faea157fd5058e5fe0d769"
      }
    ]
  }
}
```

Configuration for enabling TACACS+ under the instance **inband_mgmt** is shown below:

```
"rtbrick-config:inband-management": {
  "instance": [
    {
      "name": "inband_mgmt",
      "tacacs": "true"
    }
  ]
},
```

Enabling TACACS+ Service on the Service Node

Enter the following commands to enable the TACACS service on the Service Node.

```
~$ sudo /bin/systemctl enable tacacs_plus.service
~$ sudo /bin/systemctl start tacacs_plus.service
```

Validating TACACS+ authentication

The following scenario shows a successful authentication for the user **bob** with password **bob**.

```
~$ ssh bob@C-BNG.rtbrick.net
bob@C-BNG.rtbrick.net's password:
Last login: Mon Apr 3 16:13:40 2023 from C-BNG.rtbrick.net
bob@rtbrick>C-BNG.rtbrick.net: op>
```

The following scenario shows an unsuccessful password authentication for the user **bob** with password **bob123**.

```
~$ ssh bob@rtbrick>C-BNG.rtbrick.net:  
bob@C-BNG.rtbrick.net's password:  
Permission denied, please try again.  
bob@C-BNG.rtbrick.net's password:
```

The following scenario shows an unsuccessful authentication for an undefined user **frank**.

```
~$ ssh frank@rtbrick>C-BNG.rtbrick.net:  
frank@C-BNG.rtbrick.net's password:  
Permission denied, please try again.  
frank@C-BNG.rtbrick.net's password:  
accounting file = /var/log/tac_plus.acct  
key = RtBrick_Little_Secret
```

Configure User Management

Configuring Local User Management enables administrators to create, manage, and secure the users and groups. It allows creation of privileges that are configurable for user-defined and predefined roles.

The following steps provide the commands to configure user management. For more information about license configuration, see [Local User Management](#).

1. To create a role, configure the RBAC privilege and the command privilege. To configure the RBAC privilege for both table and object:

```
set system user admin role supervisor
set system user admin shell /bin/bash
set system user admin password-hashed-text
$6$XNkmuMRI.5.R/NBJ$XDFZec7gEM3z/31Yn8mDDWimRZ/68xawia.pTMdrGqoYHEE3nWHB08DeaPNQTw
HW6WjBlaX6.xjYjh8CNCy4g1
commit
```

For information about Configuring hashed password, see [Configure Hashed Password](#).

Authentication configuration of a password hashed text and an SSH public key is shown below:

```
{
```

```

"ietf-restconf:data": {
    "rtbrick-config:system": {
        "user": [
            {
                "username": "admin",
                "shell": "/usr/local/bin/cli",
                "password-hashed-text": "$5$L2DaOYYuddhBV$9RA5MX9RQzLC9fIKJzbnoFBb88w9rkSX17GVrVJ9PY7",
                "ssh-pub-key": [
                    "ssh-rsa AAAWsfg&jdkfs4D34H5@2evf....."
                ]
            }
        ]
    }
}

```

Configure Syslog

RBFS supports sending log messages to Syslog, which is a standard for logging events. The Syslog endpoint must be specified in CtrlID (Control Daemon) along with an alias name.

To configure logging for **bgp** by using Syslog, enter the following commands.

```

set log module bgp
set log module bgp level debug
set log module bgp plugin-alias
set log module bgp plugin-alias alias-name syslog
set log module bgp plugin-alias level debug
commit

```



For event logging, CtrlID only supports Graylog and Syslog. Graylog must be disabled in order to enable Syslog. In addition, Graylog attributes must be replaced with Syslog attributes.

Sylog configuration for the module **bgp** is shown below:

```

supervisor@rtbrick>C-BNG.rtbrick.net: cfg> show config log
{
    "rtbrick-config:log": {
        "module": [
            {
                "module-name": "bgp",
                "level": "debug",
                "plugin-alias": {
                    "alias-name": "syslog",
                    "level": "debug"
                }
            }
        ]
    }
}

```

```

    }
}
```

Accessing the ONL to Configure Syslog

The steps described in this section are performed on the ONL (Open Network Linux). For logging into the ONL, use SSH port 1022.

```
ssh supervisor@<C-BNG-management-ip> -p 1022
```

After logging into the ONL, go to the following location of CtrlID and edit the [config.json](#) file.

- [/etc/rtbrick/ctrlid/config.json](#)

Specify the Syslog configurations as shown below in the [config.json](#) file.

```
{
  "rbms_enable": false,
  "graylog_enable": false,
  "syslog_enable": true,
  "syslog_network": "udp",
  "syslog_urls": [
    "198.51.100.49:516"
  ],
  "syslog_severity_level": 7,
  "auth_enabled": false
}
```



- For documentation purposes, the IP address [198.51.100.49](#) has been used as the IP address of the Syslog endpoint. This IP address should be updated with the actual Syslog server's IP address.
- Syslog messages can be transported using UDP or TCP protocol. In this configuration, Syslog messages are transported using [udp](#).

After making configuration changes in the [config.json](#), restart CtrlID service as shown below.

```
supervisor@onl>C-BNG.rtbrick.net:~ $ sudo service rtbrick-ctrlid restart
[sudo] password for supervisor:
[ ok ] Stopping rtbrick ctrlid service:.
[ ok ] Starting rtbrick ctrlid service:.
```

Monitor Resources (Resmon)

Resource monitoring enables administrators to collect and analyze the health information and usage data of various hardware resources such as CPU, memory, processes, disks, sensors, optics, and so on.

Run `show cpu usage`, `show memory usage` and `show disk usage` to see the CPU, memory and disk utilization respectively.

```
supervisor@rtbrick>C-BNG.rtbrick.net: cfg> show cpu usage
Name      Total     User     System     Nice    I/O Wait    Idle
IRQ      Soft IRQ
cpu      11%       9%       1%        0%      0%       88%
0%       0%
cpu0     10%       8%       1%        0%      0%       89%
0%       0%
cpu1     44%       43%      1%        0%      0%       55%
0%       0%
cpu2     34%       32%      2%        0%      0%       66%
0%       0%
cpu3     11%       9%       2%        0%      0%       89%
0%       0%
cpu4     3%        1%       2%        0%      0%       96%
0%       0%
cpu5     4%        3%       1%        0%      0%       96%
0%       0%
cpu6     13%       11%      2%        0%      0%       87%
0%       0%
cpu7     24%       22%      1%        0%      0%       75%
0%       0%
cpu8     4%        2%       2%        0%      0%       95%
0%       0%
cpu9     2%        1%       1%        0%      0%       97%
0%       0%
cpu10    6%        4%       2%        0%      0%       93%
0%       0%
cpu11    3%        2%       1%        0%      0%       96%
0%       0%
cpu12    8%        6%       2%        0%      0%       91%
0%       0%
cpu13    3%        3%       0%        0%      0%       96%
0%       0%
cpu14    6%        4%       2%        0%      0%       93%
0%       0%
cpu15    8%        5%       2%        0%      0%       91%
0%       0%
supervisor@rtbrick>C-BNG.rtbrick.net: cfg> show memory usage
Name      Total     Used      Free      Shared    Buffers
Cached
RAM      31.03 GiB   8.51 GiB  17.04 GiB  1.19 GiB  112.66 MiB
5.37 GiB
SWAP     0 bytes    0 bytes   0 bytes   n/a      n/a
n/a
supervisor@rtbrick>C-BNG.rtbrick.net: cfg> show disk usage
Filesystem          Type      Size      Used      Available
Mountpoint         Usage %

```

none	tmpfs	492 KiB	0 bytes	492 KiB
/dev	0.0			
tmpfs	tmpfs	15.51 GiB	17.23 MiB	15.5 GiB
/run	0.11			
tmpfs	tmpfs	6 GiB	828.75 MiB	5.19 GiB
/shm	13.49			
tmpfs	tmpfs	15.51 GiB	182.96 MiB	15.33 GiB
/dev/shm	1.15			
tmpfs	tmpfs	5 MiB	0 bytes	5 MiB
/run/lock	0.0			
devtmpfs	devtmpfs	1 MiB	0 bytes	1 MiB
/dev/mem	0.0			
/dev/sda10	ext4	15.62 GiB	50.61 MiB	14.76 GiB
/var/log	0.33			
/dev/sda6	ext4	29.4 GiB	4.24 GiB	23.65 GiB
/platform	15.2			
tmpfs	tmpfs	3.1 GiB	0 bytes	3.1 GiB
/run/user/1000	0.0			
tmpfs	tmpfs	3.1 GiB	0 bytes	3.1 GiB
/run/user/1001	0.0			
tmpfs	tmpfs	15.51 GiB	0 bytes	15.51 GiB
/sys/fs/cgroup	0.0			
/dev/sdall	ext4	43.79 GiB	51.89 MiB	41.49 GiB
/var/crash	0.12			
tmpfs	tmpfs	3.1 GiB	1.02 MiB	3.1 GiB
/var/run-ext/onl/r	0.03			
/var/cache/rtbrick/imag	overlay	29.4 GiB	4.24 GiB	23.65 GiB
	15.2			/

The show command can also be used to view other resource details. For information about the resmon configuration and operational commands, see the [RBFS Resource Monitoring Guide](#).

1.3. Protocol Configurations

This validated solution design topology uses IS-IS as the interior gateway protocol to distribute IP routing information among the routers in an Autonomous System (AS). The Label Distribution Protocol (LDP) is used to exchange label mapping information for MPLS traffic. And, iBGP is used for exchanging routing and reachability information within ASs.

One thus needs to configure the following protocols:

- IS-IS : To ensure IP connectivity on the core network.
- LDP : To establish MPLS LSP tunnels for MPLS data transmission on the network.
- iBGP: To exchange routing information within an AS.

Configure IS-IS

The following steps provide the commands to execute various IS-IS protocol functionalities. For more detailed information about IS-IS configuration, see [IS-IS User Guide](#)

1. Configure IS-IS system-id, area, hostname and interfaces.

```
set instance default protocol isis system-id 1920.0000.2064
set instance default protocol isis area 49.0001/24
set instance default protocol isis hostname C-BNG
set instance default protocol isis interface ifl-0/1/31/10
set instance default protocol isis interface ifl-0/1/31/10 type point-to-point
set instance default protocol isis interface ifl-0/1/31/10 level-2 adjacency-
disable true
set instance default protocol isis interface lo-0/0/1/0
set instance default protocol isis interface lo-0/0/1/0 passive true
commit
```

IS-IS instance configuration on interface is shown below:

```
supervisor@rtbrick>C-BNG.rtbrick.net: op> show config instance default protocol
isis
{
    "rtbrick-config:isis": {
        "system-id": "1920.0000.2064",
        "area": [
            "49.0001/24"
        ],
        "hostname": "C-BNG",
        "interface": [
            {
                "name": "ifl-0/1/31/10",
                "type": "point-to-point",
                "level-2": {
                    "adjacency-disable": "true"
                }
            },
            {
                "name": "lo-0/0/1/0",
                "passive": "true"
            }
        ]
    }
}
```

Configure LDP on the Interfaces

The following steps provide the commands to execute various LDP functionalities. For more detailed information about LDP configuration, see [LDP User Guide](#).

1. Configure LDP on the router interface.

```
set instance default protocol ldp router-id 192.0.2.64
set instance default protocol ldp interface ifl-0/1/31/10
set instance default protocol ldp interface lo-0/0/1/0
commit
```

Configuration for LDP on the interface is shown below:

```
supervisor@rtbrick>C-BNG.rtbrick.net: cfg> show config instance default protocol
ldp
{
  "rtbrick-config:ldp": {
    "router-id": "192.0.2.64",
    "interface": [
      {
        "name": "ifl-0/1/31/10"
      },
      {
        "name": "lo-0/0/1/0"
      }
    ]
  }
}
```

Configure BGP

The following steps provide the commands to execute the various BGP functionalities quickly. For more detailed information about BGP configuration, see [BGP User Guide](#).

1. Configure BGP local AS, router-id, and hostname

```
set instance default protocol bgp local-as 4200000001
set instance default protocol bgp router-id 192.0.2.64
set instance default protocol bgp hostname C-BNG
commit
```

BGP local AS, router-id, and hostname configurations are shown below:

```
supervisor@rtbrick>C-BNG.rtbrick.net: cfg> show config instance default protocol
bgp
{
  "rtbrick-config:bgp": {
    "local-as": 4200000001,
    "hostname": "C-BNG",
    "router-id": "192.0.2.64",
```

<....>

2. Enable the IPv4 and IPv6 address families which are to be supported on the specific BGP instance.

```
set instance default protocol bgp address-family ipv4 unicast
set instance default protocol bgp address-family ipv4 unicast resolve-nexthop safi
labeled-unicast
set instance default protocol bgp address-family ipv6 labeled-unicast
set instance default protocol bgp address-family ipv6 unicast
set instance default protocol bgp address-family ipv6 unicast resolve-nexthop safi
labeled-unicast
commit
```

BGP address family configuration is shown below:

```
supervisor@rtbrick>C-BNG.rtbrick.net: cfg> show config instance default protocol
bgp address-family
{
  "rtbrick-config:address-family": [
    {
      "afi": "ipv4",
      "safi": "unicast",
      "resolve-nexthop": {
        "safi": "labeled-unicast"
      }
    },
    {
      "afi": "ipv6",
      "safi": "labeled-unicast"
    },
    {
      "afi": "ipv6",
      "safi": "unicast",
      "resolve-nexthop": {
        "safi": "labeled-unicast"
      }
    }
  ]
}
```

3. Create the peer group with the specific remote AS configurations and the address family that is to be negotiated with the peer which will be attached to the peer group later.

```
set instance default protocol bgp peer-group RR
set instance default protocol bgp peer-group RR remote-as 4200000001
set instance default protocol bgp peer-group RR address-family ipv4 unicast
set instance default protocol bgp peer-group RR address-family ipv6 labeled-
unicast
set instance default protocol bgp peer-group RR address-family ipv6 unicast
```

```
commit
```

BGP peer-group configuration is shown below:

```
supervisor@rtbrick>C-BNG.rtbrick.net: cfg> show config instance default protocol
bgp peer-group
{
  "rtbrick-config:peer-group": [
    {
      "pg-name": "RR",
      "remote-as": 4200000001,
      "address-family": [
        {
          "afi": "ipv4",
          "safi": "unicast"
        },
        {
          "afi": "ipv6",
          "safi": "labeled-unicast"
        },
        {
          "afi": "ipv6",
          "safi": "unicast"
        }
      ]
    }
  ]
}
supervisor@rtbrick>C-BNG.rtbrick.net: cfg>
```

4. Add a BGP peer and associate it with the specific peer group.

```
set instance default protocol bgp peer
set instance default protocol bgp peer ipv4 198.51.100.3 192.0.2.64
set instance default protocol bgp peer ipv4 198.51.100.3 192.0.2.64 peer-group RR
commit
```

Configuration for adding a BGP peer and associating it with a peer group is shown below:

```
supervisor@rtbrick>C-BNG.rtbrick.net: cfg> show config instance default protocol
bgp peer
{
  "rtbrick-config:peer": {
    "ipv4": [
      {
        "peer-address": "198.51.100.3",
        "update-source": "192.0.2.64",
        "peer-group": "RR"
      }
    ]
  }
}
```

```
supervisor@rtbrick>C-BNG.rtbrick.net: cfg>
```

5. Configure the IPv6 unicast address family with **send-label** as true, then address-family IPv6 labeled-unicast gets negotiated with the peer.

```
set instance default protocol bgp peer-group RR address-family ipv6 unicast send-label true
commit
```

The following configuration shows the BGP IPv6 unicast address family with **send-label** as true.

```
supervisor@rtbrick>C-BNG.rtbrick.net: cfg> show config instance default protocol
bgp peer-group RR address-family ipv6 unicast
{
    "rtbrick-config:address-family": [
        {
            "afi": "ipv6",
            "safi": "unicast",
            "send-label": "true"
        }
    ]
}
supervisor@rtbrick>C-BNG.rtbrick.net: cfg>
```

6. Set the resolve-nexthop, if the BGP nexthop attribute of the BGP routes needs to be resolved under ipv4/ipv6 labeled-unicast routing table. It configures only resolve-nexthop safi. Based on the nexthop-type (ipv4 or ipv6), it gets looked up into either IPv4 labeled-unicast or IPv6 labeled-unicast.

```
set instance default protocol bgp address-family ipv4 unicast resolve-nexthop safi
labeled-unicast
commit
```

Resolve nexthop configuration is shown below:

```
supervisor@rtbrick>C-BNG.rtbrick.net: cfg> show config instance default protocol
bgp address-family ipv4 unicast resolve-nexthop
{
    "rtbrick-config:resolve-nexthop": {
        "safi": "labeled-unicast"
    }
}
supervisor@rtbrick>C-BNG.rtbrick.net: cfg>
```

7. To redistribute the routes (belonging to a specific source) into BGP, execute the

following command. The following command redistributes **direct** routes into BGP.

```
set instance default protocol bgp address-family ipv4 unicast redistribute direct
commit
```

```
supervisor@rtbrick>C-BNG.rtbrick.net: cfg> show config instance default protocol
bgp address-family ipv4 unicast redistribute
{
    "rtbrick-config:redistribute": [
        {
            "source": "direct"
        }
    ]
}
supervisor@rtbrick>C-BNG.rtbrick.net: cfg>
```

Configuring the Service Node

Configuring Interfaces on the Service Node for RADIUS Connectivity from C-BNG

To configure interfaces on the Service Node for RADIUS connectivity from C-BNG, enter the following commands:

```
sudo ip link add link SN1-3-C1 name SN1-3-C1.100 type vlan id 100
sudo ifconfig SN1-3-C1.100 192.0.2.34/27
```



SN1-3-C1 is the internal nomenclature that denotes the interface name on Service Node that connects to the C-BNG.

Configuring Interfaces on the Service Node for NTP and TACACS Connectivity from C-BNG

To configure interfaces on the Service Node for NTP and TACACS connectivity from C-BNG, enter the following commands:

```
sudo ip link add link SN1-3-C1 name SN1-3-C1.200 type vlan id 200
sudo ifconfig SN1-3-C1.200 192.0.2.98/27
sudo ifconfig lo:1 192.0.2.129 netmask 255.255.255.255 up
sudo ifconfig lo:2 192.0.2.130 netmask 255.255.255.255 up
```

Configuring Routes on the Service Node

To configure routes on the Service Node that provides reachability to the RADIUS, TACACS and NTP servers, enter the following commands:

```
sudo ip route add 192.0.2.74/32 via 192.0.2.33
sudo ip route add 192.0.2.131/32 via 192.0.2.97
sudo ip route add 192.0.2.128/32 via 192.0.2.97
```

BNG Blaster Configuration for Protocols

BNG Blaster is an open-source network testing platform for access and routing protocols. It can emulate massive PPPoE and IPoE (DHCP) subscribers including IPTV, and L2TP (LNS). There are various routing protocols supported such as IS-IS and BGP. So, one can use this platform for end-to-end BNG and non-BNG router testing.

For more information about BNG Blaster, see <https://github.com/rtbrick/bngblaster>

For information about installing BNG Blaster, see <https://rtbrick.github.io/bngblaster/install.html>

Downloading the Blaster Configuration File

The following is the configuration file that is used in BNG Blaster for validating IPoE, BGP, IS-IS, and LDP.

→ Click [here](#) to download the BNG Blaster configuration file ([blaster.json](#)).

Generating Supporting Files for Protocols

- **Generating BGP Internet Prefixes**

Enter the following commands to generate BGP internet prefixes.

```
bgpupdate -f internet.bgp -a 4200000001 -n 198.51.100.2 -N 1 -p 172.16.0.0/24 -P
1000000
bgpupdate -f internet.bgp -a 4200000001 -n 198.51.100.2 -N 1 -p 2004::/48 -m 10000
-M 5 -P 150000 --append
```

Ensure that the command execution has finished (as shown below) before

continuing.

```
[2023-04-05 10:19:32][INFO] init 1000000 IPv4 prefixes
[2023-04-05 10:19:56][INFO] open file internet.bgp (replace)
[2023-04-05 10:25:31][INFO] finished
```

After the generation of the **internet.bgp** file, the "raw-update-file" attribute of the **blaster.json** file needs to be updated as follows:

```
"raw-update-file": "/home/supervisor/internet.bgp"
```



For more information about downloading the blaster.json file, see section [Downloading the Blaster Configuration File](#).

- **Generating MRT File for IS-IS**

Below is the JSON file ([isis_3node.json](#)) which is used to simulate R-1, R-2, and RR on BNG Blaster.

→ Click [here](#) to download the **isis_3node.json** file.

This JSON file needs to converted to MRT format using the following command:

```
lspgen -r isis_3node.json -m isis.mrt
```

After converting the file to **isis.mrt**, it needs to be updated in the IS-IS section in the **blaster.json** file as shown below.

```
"mrt-file": "/home/supervisor/isis.mrt"
```

- Generate labels for the IS-IS prefixes using "ldpupdate" command as shown below:

```
ldpupdate -l 192.0.2.65 -p 198.51.100.1/32 -P 3 -M 3 -f out.ldp
```

The detail of the generated file needs to be added to the LDP section in the **blaster.json** file as shown below:

```
"raw-update-file": "/home/supervisor/out.ldp"
```

Starting BNG Blaster

In the following command line string, a BNG Blaster instance is started and the **blaster.json** file is used.

```
sudo bngblaster -C blaster.json -I
```

The **-C blaster.json** argument specifies the blaster configuration file. The **-I** flag enables the interactive blaster UI.

```
F1: Select View F7/F8: Start/Stop Traffic F9: Terminate Sessions
F2: Network Interface Left/Right: Access Interface

Feb 26 22:23:24.359062 Loaded BGP RAW update file /home/supervisor/o
ut.bgp (27629.44 KB, 188773 updates)
Feb 26 22:23:25.456524 Resolve network interfaces
Feb 26 22:23:25.456630 All network interfaces resolved

Test Duration: 4s

Sessions      100 (0 PPPoE / 100 IPoE)
Established   0 [
Outstanding   100 [#####
Terminated    0 [
DHCPv4        0/100 [
DHCPv6        0/100 [
Setup Time    0 ms
Setup Rate    0.00 CPS (MIN: 0.00 AVG: 0.00 MAX: 0.00)
Flapped       0

Traffic Flows Verified
Session      0/600 [

Network Interface ( SN-1-BNG )
TX Packets      9 | 3 PPS 5 Kbps
5 RX Packets    3 | 1 PPS 0 Kbps
TX Session Packets IPv4 0 | 0 PPS 0 Loss
RX Session Packets IPv4 0 | 0 PPS 0 Loss
TX Session Packets IPv6 0 | 0 PPS 0 Loss
RX Session Packets IPv6 0 | 0 PPS 0 Loss
TX Session Packets IPv6PD 0 | 0 PPS 0 Loss
RX Session Packets IPv6PD 0 | 0 PPS 0 Loss
TX Multicast Packets 0 | 0 PPS

Access Interface ( SN-2-BNG )
TX Packets      200 | 200 PPS 375 Kbps
RX Packets      0 | 0 PPS 0 Kbps
TX Session Packets IPv4 0 | 0 PPS RX Session Packets IPv4 0

Feb 26 22:23:24.359062 Loaded BGP RAW update file /home/supervisor/o
ut.bgp (27629.44 KB, 188773 updates)
Feb 26 22:23:25.456524 Resolve network interfaces
Feb 26 22:23:25.456630 All network interfaces resolved
```

Validating Protocols on RBFS Consolidated BNG

Validating IS-IS Adjacency, Routes and Reachability

Run the following command to show IS-IS adjacency.

```
supervisor@rtbrick>C-BNG.rtbrick.net: op> show isis neighbor
Instance: default
  Interface      System      Level      State      Type      Up since      Expires
  ifl-0/1/31/10  BNG-Blaster  L1        Up        P2P      Wed Mar 29 05:23:24      in 22s 242106us
```

After configuring IS-IS protocol, check the IPv4 unicast routes, populated by IS-IS using the following command:

```
supervisor@rtbrick>C-BNG.rtbrick.net: op> show route ipv4 unicast source isis instance default
Instance: default, AFI: ipv4, SAFI: unicast
Prefix/Label                               Source      Pref     Next Hop
Interface

192.0.2.2/27                             isis        15       192.0.2.2
ifl-0/1/31/10
192.0.2.65/32                            isis        15       192.0.2.2
ifl-0/1/31/10
198.51.100.1/32                           isis        15       192.0.2.2
ifl-0/1/31/10
198.51.100.2/32                           isis        15       192.0.2.2
ifl-0/1/31/10
198.51.100.3/32                           isis        15       192.0.2.2
ifl-0/1/31/10
198.51.100.101/31                          isis        15       192.0.2.2
ifl-0/1/31/10
198.51.100.103/31                          isis        15       192.0.2.2
ifl-0/1/31/10
198.51.100.105/31                          isis        15       192.0.2.2
ifl-0/1/31/10
```

Ping the address 192.0.2.65 as follows:

```
supervisor@rtbrick>C-BNG.rtbrick.net: op> ping 192.0.2.65
68 bytes from 192.0.2.65: icmp_seq=1 ttl=64 time=9.0436 ms
68 bytes from 192.0.2.65: icmp_seq=2 ttl=64 time=2.0959 ms
68 bytes from 192.0.2.65: icmp_seq=3 ttl=64 time=4.7229 ms
68 bytes from 192.0.2.65: icmp_seq=4 ttl=64 time=9.2496 ms
68 bytes from 192.0.2.65: icmp_seq=5 ttl=64 time=2.6149 ms
Statistics: 5 sent, 5 received, 0% packet loss
```

Validating LDP Adjacency, Routes and Reachability

Run the following commands to show LDP neighbor and LDP session.

```
supervisor@rtbrick>C-BNG.rtbrick.net: op> show ldp neighbor
Instance: default
  Interface          LDP ID          Transport IP    Up Since           Expires
  ifl-0/1/31/10      192.0.2.65:0   192.0.2.65    Wed Mar 29 05:21:11   in 11s
```

```
supervisor@rtbrick>C-BNG.rtbrick.net: op> show ldp session
Instance: default
  LDP ID          Peer IP          State          Up/Down          FECRcvd    FECSent
  192.0.2.65:0      192.0.2.65    Operational    0d:03h:55m:49s      5          5
```

After configuring the LDP protocol, check the IPv4 labeled unicast routes, populated by LDP using the following command:

```
supervisor@rtbrick>C-BNG.rtbrick.net: op> show route ipv4 labeled-unicast source ldp
Instance: default, AFI: ipv4, SAFI: labeled-unicast
Prefix/Label                               Source      Pref     Next Hop
Interface                                Label
192.0.2.2/27                             ldp        9       192.0.2.2
ifl-0/1/31/10                            -
```

192.0.2.65/32		ldp	9	192.0.2.2
ifl-0/1/31/10	-	ldp	9	192.0.2.2
198.51.100.1/32		10000	9	192.0.2.2
ifl-0/1/31/10		ldp	9	192.0.2.2
198.51.100.2/32		10001	9	192.0.2.2
ifl-0/1/31/10		ldp	9	192.0.2.2
198.51.100.3/32		10002	9	192.0.2.2
ifl-0/1/31/10				

Ping the labeled unicast address 198.51.100.1 as follows:

```
supervisor@rtbrick>C-BNG.rtbrick.net: op> ping 198.51.100.1 instance default afi
ipv4 safi labeled-unicast
68 bytes from 198.51.100.1: icmp_seq=1 ttl=64 time=6.3289 ms
68 bytes from 198.51.100.1: icmp_seq=2 ttl=64 time=2.8249 ms
68 bytes from 198.51.100.1: icmp_seq=3 ttl=64 time=1.8587 ms
68 bytes from 198.51.100.1: icmp_seq=4 ttl=64 time=5.9599 ms
68 bytes from 198.51.100.1: icmp_seq=5 ttl=64 time=4.3811 ms
Statistics: 5 sent, 5 received, 0% packet loss
```



The command argument **labeled-unicast** takes the ICMP requests through a labeled path while validating IP connectivity and hence, it prepends an MPLS label.

Validating BGP Adjacency, Routes and Reachability

Run the following commands to show BGP session and state.

```
supervisor@rtbrick>C-BNG.rtbrick.net: op> show bgp peer
Instance: default
Peer                               Remote AS      State        Up/Down Time      PfxRcvd
PfxSent
  198.51.100.3                   4200000001    Established   0d:00h:01m:24s      1150000
  5
```

After configuring BGP, check the IPv4 unicast routes, populated by BGP using the following command:

```
supervisor@rtbrick>C-BNG.rtbrick.net: op> show route ipv4 unicast source bgp instance default
Instance: default, AFI: ipv4, SAFI: unicast
Prefix/Label                         Source      Pref      Next Hop
Interface
172.16.0.0/24                        bgp       200      198.51.100.2
ifl-0/1/31/10
172.16.1.0/24                        bgp       200      198.51.100.2
ifl-0/1/31/10
172.16.2.0/24                        bgp       200      198.51.100.2
ifl-0/1/31/10
172.16.3.0/24                        bgp       200      198.51.100.2
ifl-0/1/31/10
172.16.4.0/24                        bgp       200      198.51.100.2
ifl-0/1/31/10
172.16.5.0/24                        bgp       200      198.51.100.2
ifl-0/1/31/10
172.16.6.0/24                        bgp       200      198.51.100.2
ifl-0/1/31/10
172.16.7.0/24                        bgp       200      198.51.100.2
```

```

if1-0/1/31/10
172.16.8.0/24          bgp        200      198.51.100.2
if1-0/1/31/10
172.16.9.0/24          bgp        200      198.51.100.2
if1-0/1/31/10

<...>

```

This command will list all the 1 million IPv4 BGP internet prefixes.

Pinging an IPv4 route (source: bgp) from the C-BNG.

```

supervisor@rtbrick>C-BNG.rtbrick.net: op> ping 172.16.1.0
68 bytes from 172.16.1.0: icmp_seq=1 ttl=64 time=6.0527 ms
68 bytes from 172.16.1.0: icmp_seq=2 ttl=64 time=6.2893 ms
68 bytes from 172.16.1.0: icmp_seq=3 ttl=64 time=2.5573 ms
68 bytes from 172.16.1.0: icmp_seq=4 ttl=64 time=4.6964 ms
68 bytes from 172.16.1.0: icmp_seq=5 ttl=64 time=5.6455 ms
Statistics: 5 sent, 5 received, 0% packet loss

```

Check the IPv6 unicast routes, populated by BGP using the following command:

```

supervisor@rtbrick>C-BNG.rtbrick.net: op> show route ipv6 unicast source bgp
instance default
Instance: default, AFI: ipv6, SAFI: unicast
Prefix/Label                               Source      Pref   Next Hop
Interface

2004:::/48                                 bgp        200    198.51.100.2
if1-0/1/31/10
2004:0:1:::/48                            bgp        200    198.51.100.2
if1-0/1/31/10
2004:0:2:::/48                            bgp        200    198.51.100.2
if1-0/1/31/10
2004:0:3:::/48                            bgp        200    198.51.100.2
if1-0/1/31/10
2004:0:4:::/48                            bgp        200    198.51.100.2
if1-0/1/31/10
2004:0:5:::/48                            bgp        200    198.51.100.2
if1-0/1/31/10
2004:0:6:::/48                            bgp        200    198.51.100.2
if1-0/1/31/10
2004:0:7:::/48                            bgp        200    198.51.100.2
if1-0/1/31/10
2004:0:8:::/48                            bgp        200    198.51.100.2
if1-0/1/31/10
2004:0:9:::/48                            bgp        200    198.51.100.2
if1-0/1/31/10
2004:0:a:::/48                            bgp        200    198.51.100.2
if1-0/1/31/10
2004:0:b:::/48                            bgp        200    198.51.100.2
if1-0/1/31/10
2004:0:c:::/48                            bgp        200    198.51.100.2
if1-0/1/31/10
2004:0:d:::/48                            bgp        200    198.51.100.2
if1-0/1/31/10
2004:0:e:::/48                            bgp        200    198.51.100.2
if1-0/1/31/10

```

2004:0:f::/48 if1-0/1/31/10	bgp	200	198.51.100.2
<...>			

Pinging an IPv6 route (source: bgp) from the C-BNG.

```
supervisor@rtbrick>C-BNG.rtbrick.net: op> ping 2004:0:1:::  
68 bytes from 2004:0:1::: icmp_seq=1 ttl=253 time=10.0398 ms  
68 bytes from 2004:0:1::: icmp_seq=2 ttl=253 time=2.9673 ms  
68 bytes from 2004:0:1::: icmp_seq=3 ttl=253 time=6.2365 ms  
68 bytes from 2004:0:1::: icmp_seq=4 ttl=253 time=7.9022 ms  
68 bytes from 2004:0:1::: icmp_seq=5 ttl=253 time=1.5511 ms  
Statistics: 5 sent, 5 received, 0% packet loss
```

1.4. IPoE Subscriber Management Configuration

IP-over-Ethernet (IPoE) is an access technology that uses DHCP for IPv4 and DHCPv6 for IPv6 where both protocols are handled in the IPoE daemon ([ipoed](#)). IPoE subscribers are identified by IFP, VLANs and client MAC addresses.

The dynamic creation of IPoE subscribers is triggered by DHCPv4 discover or DHCPv6 solicit request from the subscriber. Response is postponed until the subscriber is successfully authenticated using the known authentication methods such as local or RADIUS, however authentication is not mandatory. After the authentication phase, IPv4/IPv6/IPv6-PD address is allocated to the subscriber either from the local pool or from RADIUS.

For IPoE Subscriber Management, the following configurations are mandatory:

1. Access Interface Configuration
2. Access Profile Configuration
3. AAA (Authentication, Authorization and Accounting) Profile Configuration.
Based on the authentication requirement, configure any one of the following:
 - a. Local Authentication
 - i. Pool Configuration
 - ii. User Profile Configuration
 - b. RADIUS Authentication
 - i. RADIUS Profile Configuration

ii. RADIUS Server Configuration

This solution section discusses RADIUS authentication.

NOTES:

- Access interfaces can be configured without VLAN tags (untagged) and with one (single tagged) or two (double tagged) VLAN tags.
- There can be more than one interface configured for subscriber management and each interface can reference the same profile.

Configuring IPoE Subscriber Management

For detailed information about the subscriber configuration options, see the [Subscriber Management Configuration Guide](#).

1. Configure the access profile ipoe.

```
set access access-profile ipoe
set access access-profile ipoe protocol dhcp enable true
set access access-profile ipoe protocol dhcp lease-time 60
set access access-profile ipoe protocol dhcpcv6 enable true
set access access-profile ipoe protocol dhcpcv6 lifetime 60
set access access-profile ipoe address-family ipv4 enable true
set access access-profile ipoe address-family ipv4 pool-name poolv4
set access access-profile ipoe address-family ipv4 instance default
set access access-profile ipoe address-family ipv4 dad-enable true
set access access-profile ipoe address-family ipv6 enable true
set access access-profile ipoe address-family ipv6 pool-name poolv6
set access access-profile ipoe address-family ipv6 prefix-delegation-pool-name
poolv6pd
set access access-profile ipoe address-family ipv6 instance default
set access access-profile ipoe address-family ipv6 dad-enable true
commit
```

The access profile configuration is shown below.

```
supervisor@rtbrick>C-BNG.rtbrick.net: op> show config access access-profile
{
  "rtbrick-config:access-profile": [
    {
      "profile-name": "ipoe",
      "protocol": {
        "dhcp": {
          "enable": "true",
          "lease-time": 60
        },
        "dhcpcv6": {
          "enable": "true",
          "lifetime": 60
        }
      }
    }
  ]
}
```

```

        "lifetime": 60
    }
},
"address-family": {
    "ipv4": {
        "enable": "true",
        "pool-name": "poolv4",
        "instance": "default",
        "dad-enable": "true"
    },
    "ipv6": {
        "enable": "true",
        "pool-name": "poolv6",
        "prefix-delegation-pool-name": "poolv6pd",
        "instance": "default",
        "dad-enable": "true"
    }
}
]
}
supervisor@rtbrick>C-BNG.rtbrick.net: op>
```

2. Configure the Authentication and Accounting (AAA) profile for [aaa-profile](#).

```

set access aaa-profile aaa-profile
set access aaa-profile aaa-profile session-timeout 0
set access aaa-profile aaa-profile idle-timeout 0
set access aaa-profile aaa-profile aaa-radius-profile radius-profile
set access aaa-profile aaa-profile authentication order RADIUS
set access aaa-profile aaa-profile accounting order RADIUS
set access aaa-profile aaa-profile accounting interim-interval 86400
set access aaa-profile aaa-profile accounting ingress accounting-source POLICER
set access aaa-profile aaa-profile accounting egress accounting-source CLASS
commit
```

The access AAA configuration is shown below.

```

supervisor@rtbrick>C-BNG.rtbrick.net: op> show config access aaa-profile
{
    "rtbrick-config:aaa-profile": [
        {
            "profile-name": "aaa-profile",
            "session-timeout": 0,
            "idle-timeout": 0,
            "aaa-radius-profile": "radius-profile",
            "authentication": {
                "order": "RADIUS"
            },
            "accounting": {
                "order": "RADIUS",
                "interim-interval": 86400,
                "ingress": {
                    "accounting-source": "POLICER"
                },
                "egress": {
                    "accounting-source": "CLASS"
                }
            }
        }
    ]
}
```

```

        }
    }
]
}
supervisor@rtbrick>C-BNG.rtbrick.net: op>
```

3. Configure the access interface. Double-tagged interface is configured in this case as the access interface ([ifp-0/1/30](#)). The interface configuration assigns the access type, access profile, AAA profile, and further optional attributes like service-profile to the specified access interface.

```

set access interface double-tagged ifp-0/1/30 1001 1100 1001 1100
set access interface double-tagged ifp-0/1/30 1001 1100 1001 1100 access-type IPOE
set access interface double-tagged ifp-0/1/30 1001 1100 1001 1100 access-profile-
name ipoe
set access interface double-tagged ifp-0/1/30 1001 1100 1001 1100 service-profile-
name qos_service
set access interface double-tagged ifp-0/1/30 1001 1100 1001 1100 aaa-profile-name
aaa-profile
set access interface double-tagged ifp-0/1/30 1001 1100 1001 1100 gateway-ifl lo-
0/0/1/0
commit
```

The double-tagged access interface configuration is shown below.

```

supervisor@rtbrick>C-BNG.rtbrick.net: op> show config access interface
{
  "rtbrick-config:interface": {
    "double-tagged": [
      {
        "interface-name": "ifp-0/1/30",
        "outer-vlan-min": 1001,
        "outer-vlan-max": 1100,
        "inner-vlan-min": 1001,
        "inner-vlan-max": 1100,
        "access-type": "IPOE",
        "access-profile-name": "ipoe",
        "service-profile-name": "qos_service",
        "aaa-profile-name": "aaa-profile",
        "gateway-ifl": "lo-0/0/1/0"
      }
    ]
  }
}
```

4. In this solution, we configure AAA authentication and accounting with RADIUS. To use RADIUS authentication and accounting both the RADIUS profile and RADIUS server configurations (see below) must be configured.

- a. Configure RADIUS profile [radius-profile](#).

```
set access radius-profile radius-profile
set access radius-profile radius-profile nas-ip-address 192.0.2.74
set access radius-profile radius-profile nas-port-format DEFAULT
set access radius-profile radius-profile nas-port-type Ethernet
set access radius-profile radius-profile authentication radius-server-profile-name
radius
set access radius-profile radius-profile accounting radius-server-profile-name
radius
commit
```

The RADIUS profile configuration is shown below.

```
supervisor@rtbrick>C-BNG.rtbrick.net: op> show config access radius-profile
radius-profile
{
    "rtbrick-config:radius-profile": [
        {
            "profile-name": "radius-profile",
            "nas-ip-address": "192.0.2.74",
            "nas-port-format": "DEFAULT",
            "nas-port-type": "Ethernet",
            "authentication": [
                "radius-server-profile-name": [
                    "radius"
                ]
            ],
            "accounting": [
                "radius-server-profile-name": [
                    "radius"
                ]
            ]
        }
    ]
}
supervisor@rtbrick>C-BNG.rtbrick.net: op>
```

b. Configure the RADIUS server [radius](#).

```
set access radius-server radius
set access radius-server radius address 192.0.2.34
set access radius-server radius source-address 192.0.2.74
set access radius-server radius secret-plain-text testing123
set access radius-server radius routing-instance default
set access radius-server radius rate 300
set access radius-server radius authentication enable true
set access radius-server radius authentication retry 3
set access radius-server radius authentication timeout 5
set access radius-server radius accounting enable true
set access radius-server radius accounting timeout 30
set access radius-server radius coa enable true
commit
```



The attribute `secret-plain-text` will be converted to [secret-](#)

encrypted-text in the show command output and value will be hashed.

The RADIUS server configuration is shown below.

```
supervisor@rtbrick>C-BNG.rtbrick.net: cfg> show config access radius-server radius
{
    "rtbrick-config:radius-server": [
        {
            "server-name": "radius",
            "address": "192.0.2.34",
            "source-address": "192.0.2.74",
            "secret-encrypted-text": "$2b2feb12f730107454b1be6a0f8242b0f",
            "routing-instance": "default",
            "rate": 300,
            "authentication": {
                "enable": "true",
                "retry": 3,
                "timeout": 5
            },
            "accounting": {
                "enable": "true",
                "timeout": 30
            },
            "coa": {
                "enable": "true"
            }
        }
    ]
}
supervisor@rtbrick>C-BNG.rtbrick.net: cfg>
```

5. Configure the IPv4 and IPv6 access pools.

```
set access pool poolv4
set access pool poolv4 ipv4-address low 203.0.113.1
set access pool poolv4 ipv4-address high 203.0.113.64
set access pool poolv6
set access pool poolv6 ipv6-prefix low 2001:db8:0:1::/64
set access pool poolv6 ipv6-prefix high 2001:db8:0:40::/64
set access pool poolv6pd
set access pool poolv6pd ipv6-prefix low 2001:db8:0:100::/56
set access pool poolv6pd ipv6-prefix high 2001:db8:0:4000::/56
commit
```

The access pool configuration is shown below.

```
supervisor@rtbrick>C-BNG.rtbrick.net: cfg> show config access pool
{
    "rtbrick-config:pool": [
        {
            "pool-name": "poolv4",
            "ipv4-address": {
```

```

        "low": "203.0.113.1",
        "high": "203.0.113.64"
    },
},
{
    "pool-name": "poolv6",
    "ipv6-prefix": {
        "low": "2001:db8:0:1::/64",
        "high": "2001:db8:0:40::/64"
    },
},
{
    "pool-name": "poolv6pd",
    "ipv6-prefix": {
        "low": "2001:db8:0:100::/56",
        "high": "2001:db8:0:4000::/56"
    }
}
]
}

```

IPoE Quality of Service (QoS) Configuration



The QoS model explained in this document uses a complex HQoS model with the intent to showcase the complete range of QoS features available in RBFS. However, it may not be needed or desirable for all deployments. In such a case it should be possible to conceive of a simple QoS model as required by simplifying the provided QoS model.

Following are the steps involved in configuring and verifying IPoE QoS:

1. Configuring service profile to enable QoS on IPoE subscriber
2. Configuring downstream QoS
3. Configuring upstream QoS
4. Configuring QoS remarking
5. Configuring IPoE subscriber accounting for upstream and downstream traffic
6. Configuring IPoE subscribers QoS on BNG Blaster
7. Validating IPoE QoS on BNG Blaster

The figure below shows how QoS is configured for ingress and egress traffic.




Fig. 2: Hierarchical Quality of Service primitives

For detailed information about the QoS configuration options, see the [HQoS Configuration Guide](#).

Configure Service Profile

Service profile configuration in subscriber management allows to assign QoS configurations to a subscriber.

1. Configure the service profile to enable QoS. The service profile defined to enable Quality of Service with profile name is **residential**.

```
set access service-profile qos_service qos profile residential
commit
```

The configuration of the service profile named **residential** is shown below.

```
supervisor@rtbrick>C-BNG.rtbrick.net: cfg> show config access service-profile
qos_service
{
  "rtbrick-config:service-profile": [
    {
      "profile-name": "qos_service",
      "qos": {
        "profile": "residential"
      }
    }
  ]
}
```

2. Enable QoS on IPoE subscriber access interface (**ifp-0/1/30**) to enable QoS for

IPoE subscriber.

```
set access interface double-tagged ifp-0/1/30 1001 1100 1001 1100 service-profile-name qos_service
commit
```

Below is the double-tagged access interface on which the service profile **qos_service** is configured.

```
supervisor@rtbrick>C-BNG.rtbrick.net: cfg> show config access interface double-tagged ifp-0/1/30

{
  "rtbrick-config:double-tagged": [
    {
      "interface-name": "ifp-0/1/30",
      "outer-vlan-min": 1001,
      "outer-vlan-max": 1100,
      "inner-vlan-min": 1001,
      "inner-vlan-max": 1100,
      "access-type": "IPoE",
      "access-profile-name": "ipoe",
      "service-profile-name": "qos_service",
      "aaa-profile-name": "aaa-profile",
      "gateway-ifl": "lo-0/0/1/0"
    }
  ]
}
```

3. Configure QoS profile to enable on IPoE subscriber.

```
set forwarding-options class-of-service profile residential
set forwarding-options class-of-service profile residential classifier-name subspbit-class
set forwarding-options class-of-service profile residential class-queue-map-name subs-4queues
set forwarding-options class-of-service profile residential remark-map-name sub remarking-residential
set forwarding-options class-of-service profile residential class-policer-map-name policer-map-residential
set forwarding-options class-of-service profile residential scheduler-map-name subs-4queues-residential
commit
```

The QoS Profile with all the primitives needed to enable traffic profiles on IPoE Subscribers is as follows:

```
supervisor@rtbrick>C-BNG.rtbrick.net: cfg> show config forwarding-options class-of-service profile residential
{
  "rtbrick-config:profile": [
```

```
{
    "profile-name": "residential",
    "classifier-name": "subs-pbit-class",
    "class-queue-map-name": "subs-4queues",
    "remark-map-name": "subs-remarking-residential",
    "class-policer-map-name": "policer-map-residential",
    "scheduler-map-name": "subs-4queues-residential"
}
]
}
```

Configure Downstream QoS

Downstream Quality of Service (QoS) is used to prioritize network traffic from the Internet to subscribers.

1. Enable global classification for downstream traffic.

```
set forwarding-options class-of-service global multifield-classifier-name
global_mfc
commit
```

Below is the multi-field-classifier (MFC) based classifier for global enabling of downstream traffic classification.

```
supervisor@rtbrick>C-BNG.rtbrick.net: cfg> show config forwarding-options class-
of-service global multifield-classifier-name
{
    "rtbrick-config:multifield-classifier-name": "global_mfc"
}
```

2. Configure the MFC-based classifier with qualifiers and actions.

```
set forwarding-options class-of-service multifield-classifier acl 13v4 rule
global_mfc
set forwarding-options class-of-service multifield-classifier acl 13v4 rule
global_mfc ordinal 1001
set forwarding-options class-of-service multifield-classifier acl 13v4 rule
global_mfc ordinal 1001 match ipv4-tos 128
set forwarding-options class-of-service multifield-classifier acl 13v4 rule
global_mfc ordinal 1001 match source-ipv4-prefix 132.1.1.3/32
set forwarding-options class-of-service multifield-classifier acl 13v4 rule
global_mfc ordinal 1001 action forward-class class-0
set forwarding-options class-of-service multifield-classifier acl 13v4 rule
global_mfc ordinal 1002
set forwarding-options class-of-service multifield-classifier acl 13v4 rule
global_mfc ordinal 1002 match ipv4-tos 160
set forwarding-options class-of-service multifield-classifier acl 13v4 rule
global_mfc ordinal 1002 match source-ipv4-prefix 132.1.1.3/32
set forwarding-options class-of-service multifield-classifier acl 13v4 rule
global_mfc ordinal 1002 action forward-class class-1
```

```

set forwarding-options class-of-service multifield-classifier acl 13v4 rule
global_mfc ordinal 1003
set forwarding-options class-of-service multifield-classifier acl 13v4 rule
global_mfc ordinal 1003 match ipv4-tos 192
set forwarding-options class-of-service multifield-classifier acl 13v4 rule
global_mfc ordinal 1003 match source-ipv4-prefix 132.1.1.3/32
set forwarding-options class-of-service multifield-classifier acl 13v4 rule
global_mfc ordinal 1003 action forward-class class-2
set forwarding-options class-of-service multifield-classifier acl 13v4 rule
global_mfc ordinal 1004
set forwarding-options class-of-service multifield-classifier acl 13v4 rule
global_mfc ordinal 1004 match ipv4-tos 224
set forwarding-options class-of-service multifield-classifier acl 13v4 rule
global_mfc ordinal 1004 match source-ipv4-prefix 132.1.1.3/32
set forwarding-options class-of-service multifield-classifier acl 13v4 rule
global_mfc ordinal 1004 action forward-class class-3
commit

```

The configuration of the QoS MFC-based Classifier for classification of downstream traffic from the core towards IPoE Subscriber is shown below.

```

supervisor@rtbrick>C-BNG.rtbrick.net: cfg> show config forwarding-options class-
of-service multifield-classifier acl 13v4 rule global_mfc
{
    "rtbrick-config:rule": [
        {
            "rule-name": "global_mfc",
            "ordinal": [
                {
                    "ordinal-value": 1001,
                    "match": {
                        "ipv4-tos": 128,
                        "source-ipv4-prefix": "132.1.1.3/32"
                    },
                    "action": {
                        "forward-class": "class-0"
                    }
                },
                {
                    "ordinal-value": 1002,
                    "match": {
                        "ipv4-tos": 160,
                        "source-ipv4-prefix": "132.1.1.3/32"
                    },
                    "action": {
                        "forward-class": "class-1"
                    }
                },
                {
                    "ordinal-value": 1003,
                    "match": {
                        "ipv4-tos": 192,
                        "source-ipv4-prefix": "132.1.1.3/32"
                    },
                    "action": {
                        "forward-class": "class-2"
                    }
                }
            ]
        }
    ]
}

```

```
{
    "ordinal-value": 1004,
    "match": {
        "ipv4-tos": 224,
        "source-ipv4-prefix": "132.1.1.3/32"
    },
    "action": {
        "forward-class": "class-3"
    }
}
]
}
}
```

3. Enqueue classified traffic to different queues using class-to-queue mapping.

```
set forwarding-options class-of-service queue-group subs-4queues queue-numbers 4
set forwarding-options class-of-service class-queue-map subs-4queues
set forwarding-options class-of-service class-queue-map subs-4queues class class-0
set forwarding-options class-of-service class-queue-map subs-4queues class class-0
queue-name BE_SUBS
set forwarding-options class-of-service class-queue-map subs-4queues class class-1
set forwarding-options class-of-service class-queue-map subs-4queues class class-1
queue-name LD_SUBS
set forwarding-options class-of-service class-queue-map subs-4queues class class-2
set forwarding-options class-of-service class-queue-map subs-4queues class class-2
queue-name LL_SUBS
set forwarding-options class-of-service class-queue-map subs-4queues class class-3
set forwarding-options class-of-service class-queue-map subs-4queues class class-3
queue-name VO_SUBS
commit
```

Below is the QoS class-queue mapping configuration:

```
supervisor@rtbrick>C-BNG.rtbrick.net: cfg> show config forwarding-options class-
of-service class-queue-map subs-4queues class
{
    "rtbrick-config:class": [
        {
            "class-type": "class-0",
            "queue-name": "BE_SUBS"
        },
        {
            "class-type": "class-1",
            "queue-name": "LD_SUBS"
        },
        {
            "class-type": "class-2",
            "queue-name": "LL_SUBS"
        },
        {
            "class-type": "class-3",
            "queue-name": "VO_SUBS"
        }
    ]
}
```

```
}
```

4. Configure the queues needed for enqueueing and dequeuing traffic streams.

```
set forwarding-options class-of-service queue BE_SUBS
set forwarding-options class-of-service queue BE_SUBS queue-size 375000
set forwarding-options class-of-service queue LD_SUBS
set forwarding-options class-of-service queue LD_SUBS queue-size 625000
set forwarding-options class-of-service queue LL_SUBS
set forwarding-options class-of-service queue LL_SUBS queue-size 625000
set forwarding-options class-of-service queue VO_SUBS
set forwarding-options class-of-service queue VO_SUBS queue-size 156250
set forwarding-options class-of-service queue VO_SUBS shaper-name shaper_VO
commit
```

The queue Configuration is shown below.

```
supervisor@rtbrick>C-BNG.rtbrick.net: cfg> show config forwarding-options class-
of-service queue
{
    "rtbrick-config:queue": [
        {
            "queue-name": "BE_SUBS",
            "queue-size": 375000,
        },
        {
            "queue-name": "LD_SUBS",
            "queue-size": 625000,
        },
        {
            "queue-name": "LL_SUBS",
            "queue-size": 625000,
        },
        {
            "queue-name": "VO_SUBS",
            "queue-size": 156250,
            "shaper-name": "shaper_VO",
        }
    ]
}
```

5. Configure the scheduler needed by Subscriber/Session scheduler-map and OLT scheduler-map.

```
set forwarding-options class-of-service scheduler pon0
set forwarding-options class-of-service scheduler pon0 type fair_queueing
set forwarding-options class-of-service scheduler pon0 shaper-name gpon-shaper
set forwarding-options class-of-service scheduler subs-4queues
set forwarding-options class-of-service scheduler subs-4queues shaper-name
shaper_session
set forwarding-options class-of-service scheduler subs-4queues type
strict_priority
set forwarding-options class-of-service scheduler subs-4queues composite false
```

```
commit
```

The configuration of the scheduler-map and OLT scheduler-map is shown below.

```
supervisor@rtbrick>C-BNG.rtbrick.net: cfg> show config forwarding-options class-of-service scheduler
{
    "rtbrick-config:scheduler": [
        {
            "scheduler-name": "pon0",
            "shaper-name": "gpon-shaper",
            "type": "fair_queueing"
        },
        {
            "scheduler-name": "subs-4queues",
            "shaper-name": "shaper_session",
            "type": "strict_priority",
            "composite": "false"
        }
    ]
}
```

6. Configure the session/subscriber scheduler mapping for dequeuing traffic based on scheduler type for each queue:

```
set forwarding-options class-of-service scheduler-map schedmap-olt
set forwarding-options class-of-service scheduler-map schedmap-olt scheduler-name
pon0
set forwarding-options class-of-service scheduler-map schedmap-olt scheduler-name
pon0 port-connection scheduler_to_port
set forwarding-options class-of-service scheduler-map subs-4queues-residential
set forwarding-options class-of-service scheduler-map subs-4queues-residential
queue-group-name subs-4queues
set forwarding-options class-of-service scheduler-map subs-4queues-residential
queue-group-name subs-4queues queue-name BE_SUBS
set forwarding-options class-of-service scheduler-map subs-4queues-residential
queue-group-name subs-4queues queue-name BE_SUBS parent-flow high-flow
set forwarding-options class-of-service scheduler-map subs-4queues-residential
queue-group-name subs-4queues queue-name BE_SUBS parent-scheduler-name subs-
4queues
set forwarding-options class-of-service scheduler-map subs-4queues-residential
queue-group-name subs-4queues queue-name BE_SUBS connection-point
strict_priority_3
set forwarding-options class-of-service scheduler-map subs-4queues-residential
queue-group-name subs-4queues queue-name LD_SUBS
set forwarding-options class-of-service scheduler-map subs-4queues-residential
queue-group-name subs-4queues queue-name LD_SUBS parent-flow high-flow
set forwarding-options class-of-service scheduler-map subs-4queues-residential
queue-group-name subs-4queues queue-name LD_SUBS parent-scheduler-name subs-
4queues
set forwarding-options class-of-service scheduler-map subs-4queues-residential
queue-group-name subs-4queues queue-name LD_SUBS connection-point
strict_priority_1
set forwarding-options class-of-service scheduler-map subs-4queues-residential
queue-group-name subs-4queues queue-name LL_SUBS
set forwarding-options class-of-service scheduler-map subs-4queues-residential
```

```

queue-group-name subs-4queues queue-name LL_SUBS parent-flow high-flow
set forwarding-options class-of-service scheduler-map subs-4queues-residential
queue-group-name subs-4queues queue-name LL_SUBS parent-scheduler-name subs-
4queues
set forwarding-options class-of-service scheduler-map subs-4queues-residential
queue-group-name subs-4queues queue-name LL_SUBS connection-point
strict_priority_2
set forwarding-options class-of-service scheduler-map subs-4queues-residential
queue-group-name subs-4queues queue-name VO_SUBS
set forwarding-options class-of-service scheduler-map subs-4queues-residential
queue-group-name subs-4queues queue-name VO_SUBS parent-flow high-flow
set forwarding-options class-of-service scheduler-map subs-4queues-residential
queue-group-name subs-4queues queue-name VO_SUBS parent-scheduler-name subs-
4queues
set forwarding-options class-of-service scheduler-map subs-4queues-residential
queue-group-name subs-4queues queue-name VO_SUBS connection-point
strict_priority_0
set forwarding-options class-of-service scheduler-map subs-4queues-residential
scheduler-name subs-4queues
set forwarding-options class-of-service scheduler-map subs-4queues-residential
scheduler-name subs-4queues port-connection scheduler_to_port
commit

```

The QoS Subscriber/Session Scheduler-Map configuration is shown below:

```

supervisor@rtbrick>C-BNG.rtbrick.net: cfg> show config forwarding-options class-
of-service scheduler-map subs-4queues-residential
{
    "rtbrick-config:scheduler-map": [
        {
            "scheduler-map-name": "subs-4queues-residential",
            "queue-group-name": [
                {
                    "group-name": "subs-4queues",
                    "queue-name": [
                        {
                            "name": "BE_SUBS",
                            "parent-flow": "high-flow",
                            "parent-scheduler-name": "subs-4queues",
                            "connection-point": "strict_priority_3"
                        },
                        {
                            "name": "LD_SUBS",
                            "parent-flow": "high-flow",
                            "parent-scheduler-name": "subs-4queues",
                            "connection-point": "strict_priority_1"
                        },
                        {
                            "name": "LL_SUBS",
                            "parent-flow": "high-flow",
                            "parent-scheduler-name": "subs-4queues",
                            "connection-point": "strict_priority_2"
                        },
                        {
                            "name": "VO_SUBS",
                            "parent-flow": "high-flow",
                            "parent-scheduler-name": "subs-4queues",
                            "connection-point": "strict_priority_0"
                        }
                    ]
                }
            ]
        }
    ]
}

```

```

        ]
    },
],
"scheduler-name": [
{
    "name": "subs-4queues",
    "port-connection": "scheduler_to_port"
}
]
}
]
```

- Configure the OLT scheduler-mapping for each PON to be scheduled according to the scheduler type.

```

set forwarding-options class-of-service scheduler-map schedmap-olt
set forwarding-options class-of-service scheduler-map schedmap-olt scheduler-name
pon0
set forwarding-options class-of-service scheduler-map schedmap-olt scheduler-name
pon0 port-connection scheduler_to_port
commit

```

The OLT Scheduler-Map configuration is shown below:

```

supervisor@rtbrick>C-BNG.rtbrick.net: cfg> show config forwarding-options class-
of-service scheduler-map schedmap-olt
{
    "rtbrick-config:scheduler-map": [
        {
            "scheduler-map-name": "schedmap-olt",
            "scheduler-name": [
                {
                    "name": "pon0",
                    "port-connection": "scheduler_to_port"
                }
            ]
        }
    ]
}
```

- Configure downstream traffic shaping for both session schedulers and queues.



Queue Shaping is only on VO_SUBS Queue.

```

set forwarding-options class-of-service shaper shaper_VO
set forwarding-options class-of-service shaper shaper_VO shaping-rate-high 2000
set forwarding-options class-of-service shaper shaper_VO shaping-rate-low 0
set forwarding-options class-of-service shaper shaper_session
set forwarding-options class-of-service shaper shaper_session shaping-rate-high
10000
set forwarding-options class-of-service shaper shaper_session shaping-rate-low 100

```

```
set forwarding-options class-of-service shaper gpon-shaper
set forwarding-options class-of-service shaper gpon-shaper shaping-rate-high
2488000
set forwarding-options class-of-service shaper gpon-shaper shaping-rate-low 32000
commit
```

The shaping Configuration is shown below.

```
supervisor@rtbrick>C-BNG.rtbrick.net: cfg> show config forwarding-options class-
of-service shaper
{
    "rtbrick-config:shaper": [
        {
            "shaper-name": "shaper_VO",
            "shaping-rate-high": 2000,
            "shaping-rate-low": 0
        },
        {
            "shaper-name": "shaper_session",
            "shaping-rate-high": 10000,
            "shaping-rate-low": 100
        },
        {
            "shaper-name": "gpon-shaper",
            "shaping-rate-high": 2488000,
            "shaping-rate-low": 32000
        }
    ]
}
```

Configure Upstream QoS

1. Configure the BA Classifier for the classification of multiple traffic streams targeted at IPoE subscribers:

```
set forwarding-options class-of-service classifier subs-pbit-class
set forwarding-options class-of-service classifier subs-pbit-class match-type
ieee-802.1
set forwarding-options class-of-service classifier subs-pbit-class match-type
ieee-802.1 codepoint 1
set forwarding-options class-of-service classifier subs-pbit-class match-type
ieee-802.1 codepoint 1 class class-0
set forwarding-options class-of-service classifier subs-pbit-class match-type
ieee-802.1 codepoint 1 remark-codepoint 7
set forwarding-options class-of-service classifier subs-pbit-class match-type
ieee-802.1 codepoint 2
set forwarding-options class-of-service classifier subs-pbit-class match-type
ieee-802.1 codepoint 2 class class-1
set forwarding-options class-of-service classifier subs-pbit-class match-type
ieee-802.1 codepoint 2 remark-codepoint 7
set forwarding-options class-of-service classifier subs-pbit-class match-type
ieee-802.1 codepoint 3
set forwarding-options class-of-service classifier subs-pbit-class match-type
ieee-802.1 codepoint 3 class class-2
```

```

set forwarding-options class-of-service classifier subs-pbit-class match-type
ieee-802.1 codepoint 3 remark-codepoint 7
set forwarding-options class-of-service classifier subs-pbit-class match-type
ieee-802.1 codepoint 4
set forwarding-options class-of-service classifier subs-pbit-class match-type
ieee-802.1 codepoint 4 class class-3
set forwarding-options class-of-service classifier subs-pbit-class match-type
ieee-802.1 codepoint 4 remark-codepoint 7
commit

```

The configuration of the QoS BA-based Classifier for classification of upstream traffic towards IPoE Subscriber is shown below.

```

supervisor@rtbrick>C-BNG.rtbrick.net: cfg> show config forwarding-options class-
of-service classifier subs-pbit-class
{
    "rtbrick-config:classifier": [
        {
            "classifier-name": "subs-pbit-class",
            "match-type": [
                {
                    "match-type": "ieee-802.1",
                    "codepoint": [
                        {
                            "codepoint": 1,
                            "class": "class-0",
                            "remark-codepoint": 7
                        },
                        {
                            "codepoint": 2,
                            "class": "class-1",
                            "remark-codepoint": 7
                        },
                        {
                            "codepoint": 3,
                            "class": "class-2",
                            "remark-codepoint": 7
                        },
                        {
                            "codepoint": 4,
                            "class": "class-3",
                            "remark-codepoint": 7
                        }
                    ]
                }
            ]
        }
    ]
}

```

2. Configure multi-level policer to police 4-Level traffic.

```

set forwarding-options class-of-service policer policer-residential
set forwarding-options class-of-service policer policer-residential level1-rates
cir 2000
set forwarding-options class-of-service policer policer-residential level1-rates

```

```

cbs 1000
set forwarding-options class-of-service policer policer-residential level1-rates
pir 2500
set forwarding-options class-of-service policer policer-residential level1-rates
pbs 1000
set forwarding-options class-of-service policer policer-residential level2-rates
cir 3000
set forwarding-options class-of-service policer policer-residential level2-rates
cbs 1000
set forwarding-options class-of-service policer policer-residential level2-rates
pir 3500
set forwarding-options class-of-service policer policer-residential level2-rates
pbs 1000
set forwarding-options class-of-service policer policer-residential level3-rates
cir 4000
set forwarding-options class-of-service policer policer-residential level3-rates
cbs 1000
set forwarding-options class-of-service policer policer-residential level3-rates
pir 4500
set forwarding-options class-of-service policer policer-residential level3-rates
pbs 1000
set forwarding-options class-of-service policer policer-residential level4-rates
cir 1000
set forwarding-options class-of-service policer policer-residential level4-rates
cbs 1000
set forwarding-options class-of-service policer policer-residential level4-rates
pir 1500
set forwarding-options class-of-service policer policer-residential level4-rates
pbs 1000
set forwarding-options class-of-service policer policer-residential levels 4
set forwarding-options class-of-service policer policer-residential type two-rate-
three-color
commit

```

The multi-level policer configuration is shown below:

```

supervisor@rtbrick>C-BNG.rtbrick.net: cfg> show config forwarding-options class-
of-service policer policer-residential
{
    "rtbrick-config:policer": [
        {
            "policer-name": "policer-residential",
            "level1-rates": {
                "cir": 2000,
                "cbs": 1000,
                "pir": 2500,
                "pbs": 1000
            },
            "level2-rates": {
                "cir": 3000,
                "cbs": 1000,
                "pir": 3500,
                "pbs": 1000
            },
            "level3-rates": {
                "cir": 4000,
                "cbs": 1000,
                "pir": 4500,
                "pbs": 1000
            }
        }
    ]
}

```

```

    },
    "level4-rates": {
        "cir": 1000,
        "cbs": 1000,
        "pir": 1500,
        "pbs": 1000
    },
    "levels": 4,
    "type": "two-rate-three-color"
}
]
}

```

3. Map the classified traffic streams to different policer levels using class-to-policer mapping:

```

set forwarding-options class-of-service class-policer-map policer-map-residential
set forwarding-options class-of-service class-policer-map policer-map-residential
class class-0
set forwarding-options class-of-service class-policer-map policer-map-residential
class class-0 policer-level level-1
set forwarding-options class-of-service class-policer-map policer-map-residential
class class-1
set forwarding-options class-of-service class-policer-map policer-map-residential
class class-1 policer-level level-2
set forwarding-options class-of-service class-policer-map policer-map-residential
class class-2
set forwarding-options class-of-service class-policer-map policer-map-residential
class class-2 policer-level level-3
set forwarding-options class-of-service class-policer-map policer-map-residential
class class-3
set forwarding-options class-of-service class-policer-map policer-map-residential
class class-3 policer-level level-4
commit

```

The class-policer-map configuration is shown below:

```

supervisor@rtbrick>C-BNG.rtbrick.net: cfg> show config forwarding-options class-
of-service class-policer-map policer-map-residential class
{
    "rtbrick-config:class": [
        {
            "class": "class-0",
            "policer-level": "level-1"
        },
        {
            "class": "class-1",
            "policer-level": "level-2"
        },
        {
            "class": "class-2",
            "policer-level": "level-3"
        },
        {
            "class": "class-3",
            "policer-level": "level-4"
        }
    ]
}

```

```

    }
]
}

```

Configure QoS Remarking

1. Remark downstream traffic egressing from subscriber interface (egress remarking).

```

set forwarding-options class-of-service remark-map subs-remarking-residential
set forwarding-options class-of-service remark-map subs-remarking-residential
remark-type ieee-802.1
set forwarding-options class-of-service remark-map subs-remarking-residential
remark-type ieee-802.1 match-codepoint 1
set forwarding-options class-of-service remark-map subs-remarking-residential
remark-type ieee-802.1 match-codepoint 1 color all
set forwarding-options class-of-service remark-map subs-remarking-residential
remark-type ieee-802.1 match-codepoint 1 color all remark-codepoint 6
set forwarding-options class-of-service remark-map subs-remarking-residential
remark-type ieee-802.1 match-codepoint 2
set forwarding-options class-of-service remark-map subs-remarking-residential
remark-type ieee-802.1 match-codepoint 2 color all
set forwarding-options class-of-service remark-map subs-remarking-residential
remark-type ieee-802.1 match-codepoint 2 color all remark-codepoint 6
set forwarding-options class-of-service remark-map subs-remarking-residential
remark-type ieee-802.1 match-codepoint 3
set forwarding-options class-of-service remark-map subs-remarking-residential
remark-type ieee-802.1 match-codepoint 3 color all
set forwarding-options class-of-service remark-map subs-remarking-residential
remark-type ieee-802.1 match-codepoint 3 color all remark-codepoint 6
set forwarding-options class-of-service remark-map subs-remarking-residential
remark-type ieee-802.1 match-codepoint 4
set forwarding-options class-of-service remark-map subs-remarking-residential
remark-type ieee-802.1 match-codepoint 4 color all
set forwarding-options class-of-service remark-map subs-remarking-residential
remark-type ieee-802.1 match-codepoint 4 color all remark-codepoint 6
commit

```

The remarking configuration is shown below:

```

supervisor@rtbrick>C-BNG.rtbrick.net: cfg> show config forwarding-options class-
of-service remark-map subs-remarking-residential
{
  "rtbrick-config:remark-map": [
    {
      "remark-map-name": "subs-remarking-residential",
      "remark-type": [
        {
          "remark-type": "ieee-802.1",
          "match-codepoint": [
            {
              "match-codepoint": 1,
              "color": [
                {

```

```
        "color": "all",
        "remark-codepoint": 6
    }
]
}
{
    "match-codepoint": 2,
    "color": [
        {
            "color": "all",
            "remark-codepoint": 6
        }
    ]
},
{
    "match-codepoint": 3,
    "color": [
        {
            "color": "all",
            "remark-codepoint": 6
        }
    ]
},
{
    "match-codepoint": 4,
    "color": [
        {
            "color": "all",
            "remark-codepoint": 6
        }
    ]
},
{
    "match-codepoint": 5,
    "color": [
        {
            "color": "all",
            "remark-codepoint": 6
        }
    ]
},
{
    "match-codepoint": 6,
    "color": [
        {
            "color": "all",
            "remark-codepoint": 6
        }
    ]
}
]
```

3. Remark upstream traffic ingressing to a subscriber's interface [ingress remarking]



In the upstream traffic classifier configuration shown below, remarking of all traffic streams with code point '7' is done.

```
set forwarding-options class-of-service classifier subs-pbit-class
set forwarding-options class-of-service classifier subs-pbit-class match-type
ieee-802.1
set forwarding-options class-of-service classifier subs-pbit-class match-type
ieee-802.1 codepoint 1
set forwarding-options class-of-service classifier subs-pbit-class match-type
ieee-802.1 codepoint 1 class class-0
set forwarding-options class-of-service classifier subs-pbit-class match-type
ieee-802.1 codepoint 1 remark-codepoint 7
set forwarding-options class-of-service classifier subs-pbit-class match-type
ieee-802.1 codepoint 2
set forwarding-options class-of-service classifier subs-pbit-class match-type
```

```

ieee-802.1 codepoint 2 class class-1
set forwarding-options class-of-service classifier subs-pbit-class match-type
ieee-802.1 codepoint 2 remark-codepoint 7
set forwarding-options class-of-service classifier subs-pbit-class match-type
ieee-802.1 codepoint 3
set forwarding-options class-of-service classifier subs-pbit-class match-type
ieee-802.1 codepoint 3 class class-2
set forwarding-options class-of-service classifier subs-pbit-class match-type
ieee-802.1 codepoint 3 remark-codepoint 7
set forwarding-options class-of-service classifier subs-pbit-class match-type
ieee-802.1 codepoint 4
set forwarding-options class-of-service classifier subs-pbit-class match-type
ieee-802.1 codepoint 4 class class-3
set forwarding-options class-of-service classifier subs-pbit-class match-type
ieee-802.1 codepoint 4 remark-codepoint 7
commit

```

Below is the remarking configuration:

```

supervisor@rtbrick>C-BNG.rtbrick.net: cfg> show config forwarding-options class-
of-service classifier subs-pbit-class
{
    "rtbrick-config:classifier": [
        {
            "classifier-name": "subs-pbit-class",
            "match-type": [
                {
                    "match-type": "ieee-802.1",
                    "codepoint": [
                        {
                            "codepoint": 1,
                            "class": "class-0",
                            "remark-codepoint": 7
                        },
                        {
                            "codepoint": 2,
                            "class": "class-1",
                            "remark-codepoint": 7
                        },
                        {
                            "codepoint": 3,
                            "class": "class-2",
                            "remark-codepoint": 7
                        },
                        {
                            "codepoint": 4,
                            "class": "class-3",
                            "remark-codepoint": 7
                        }
                    ]
                }
            ]
        }
    ]
}

```

Configure Mirroring for Downstream Traffic Remark Validation

Configure Mirroring for Downstream Traffic

```
set forwarding-options mirror m1 source interface ifp-0/1/30
set forwarding-options mirror m1 source direction egress
set forwarding-options mirror m1 destination interface cpu-0/0/200
commit
```

Validate the downstream traffic remarking



This validation requires mirroring the subscriber access interface on the C-BNG device.

```
supervisor@rtbrick>C-BNG.rtbrick.net: cfg> show config forwarding-options mirror
{
  "rtbrick-config:mirror": [
    {
      "name": "m1",
      "destination": {
        "interface": "cpu-0/0/200"
      },
      "source": {
        "direction": "egress",
        "interface": "ifp-0/1/30"
      }
    }
  ]
}
```

The capture mirroring can be performed as shown below.

```
supervisor@rtbrick>C-BNG.rtbrick.net: cfg> capture mirror

2023-04-03T13:58:59.651227+0000 e8:c5:7a:8f:76:f1 > 02:00:00:00:00:01, ethertype
802.1Q (0x8100), length 1022: vlan 1001, p 6, ethertype 802.1Q, vlan 1001, p 6,
ethertype IPv4, (tos 0xe0, ttl 63, id 0, offset 0, flags [DF], proto UDP (17),
length 1000)
  192.0.2.2.65056 > 203.0.113.1.65056: UDP, length 972

2023-04-03T13:58:59.651306+0000 e8:c5:7a:8f:76:f1 > 02:00:00:00:00:01, ethertype
802.1Q (0x8100), length 1022: vlan 1001, p 6, ethertype 802.1Q, vlan 1001, p 6,
ethertype IPv4, (tos 0xe0, ttl 63, id 0, offset 0, flags [DF], proto UDP (17),
length 1000)
  192.0.2.2.65056 > 203.0.113.1.65056: UDP, length 972
```

Configure Mirroring for Upstream Traffic Remark Validation

```
set forwarding-options mirror m1 source interface ifp-0/1/30
set forwarding-options mirror m1 source direction ingress
set forwarding-options mirror m1 destination interface cpu-0/0/200
commit
```

Validating the upstream traffic remarking



Mirror the core facing port on the C-BNG device as shown below.

```
supervisor@rtbrick>C-BNG.rtbrick.net: cfg> show config forwarding-options mirror m1
{
  "rtbrick-config:mirror": [
    {
      "name": "m1",
      "destination": {
        "interface": "cpu-0/0/200"
      },
      "source": {
        "direction": "ingress",
        "interface": "ifp-0/1/30"
      }
    }
  ]
}
```

The capture mirroring can be performed as shown below. It confirms all four traffic streams noted with codepoint=7.

```
supervisor@rtbrick>C-BNG.rtbrick.net: cfg> capture mirror

2023-04-03T13:53:31.400011+0000 02:00:00:00:00:01 > e8:c5:7a:8f:76:f1, ethertype
802.1Q (0x8100), length 1022: vlan 1001, p 2, ethertype 802.1Q, vlan 1001, p 2,
ethertype IPv4, (tos 0xa0, ttl 64, id 0, offset 0, flags [DF], proto UDP (17),
length 1000)
  203.0.113.1.65056 > 192.0.2.2.65056: UDP, length 972

2023-04-03T13:53:31.400167+0000 02:00:00:00:00:01 > e8:c5:7a:8f:76:f1, ethertype
802.1Q (0x8100), length 1022: vlan 1001, p 3, ethertype 802.1Q, vlan 1001, p 3,
ethertype IPv4, (tos 0xc0, ttl 64, id 0, offset 0, flags [DF], proto UDP (17),
length 1000)
  203.0.113.1.65056 > 192.0.2.2.65056: UDP, length 972
```

Configure FreeRADIUS Server

Installation of FreeRADIUS

FreeRADIUS server can be installed on any Linux OS distribution. For information about installing FreeRADIUS, see [Installing the FreeRADIUS Server](#).

Remove the Unsupported Files

It is necessary to remove `echo`, `ntlm_auth`, `eap`, `echo`, and `mschap` files once FreeRadius has been installed, since they are not required by this reference design. To remove these files, enter the following commands:

```
rm -rf /etc/freeradius/3.0/mods-enabled/echo
rm -rf /etc/freeradius/3.0/mods-enabled/ntlm_auth
rm -rf /etc/freeradius/3.0/mods-enabled/eap
rm -rf /etc/freeradius/3.0/mods-enabled/echo
rm -rf /etc/freeradius/3.0/mods-enabled/mschap
```

Configure the FreeRADIUS Files

It is necessary to configure the FreeRADIUS files once FreeRadius has been installed. The configuration files can be found under [/etc/freeradius/3.0/](#).

authorize

Using the following command, one can view the `authorize` file in its default location.

```
~:/etc/freeradius/3.0 # cat mods-config/files/authorize
```

Replace the content of the `authorize` file with the following:

```
$INCLUDE /etc/freeradius/3.0/ipoe_users_file
```



This file can also be downloaded from the appendix (Appendix C: RADIUS Server Configuration).

ipoe_users_file

The IPoE Users file (`ipoe_users_file`) mentioned in the above section includes subscriber profile parameters as shown below.

```

"02:00:00:00:00:01@ipoe" Cleartext-Password := "ipoe"
  Service-Type = Framed-User,
  Class = IPOE,
  Framed-IP-Address = 203.0.113.1,
  Framed-IP-Netmask = 255.255.255.255,
  RtBrick-DNS-Primary = 203.0.113.200,
  RtBrick-DNS-Secondary = 203.0.113.201,
  Framed-IPv6-Prefix = 2001:db8:0:1::1/128,
  Delegated-IPv6-Prefix = 2001:db8:0:3::/64,
  RtBrick-DNS-Primary-IPv6 = 2001:db8:0:20::1,
  RtBrick-DNS-Secondary-IPv6 = 2001:db8:0:20::2,
  Session-Timeout = 0,
  Idle-Timeout = 0,
  Reply-Message = "FOOBAR Internet",
  Acct-Interim-Interval = 120,
  RtBrick-QoS-Profile = "residential"

DEFAULT User-Name =~ '^[0-9a-f\\:]+@ipoe$', Cleartext-Password := 'ipoe'
  Service-Type = Framed-User,
  Class = "IPOE",
  Acct-Interim-Interval = 900

```

The `ipoe_users_file` can be created with the above content in the `/etc/freeradius/3.0/` path. Alternatively, this file can be downloaded from the appendix section of this guide and placed at `/etc/freeradius/3.0/`.

clients.conf

Clients.conf file shall be configured with the expected RADIUS client IP address and secret.

```

~:/etc/freeradius/3.0 # cat clients.conf
client rtbrick {
    ipaddr      = 192.0.2.74
    secret      = testing123
    shortname   = rtbrick
    nas_type    = other
    require_message_authenticator = no
}

```

The `clients.conf` file (`/etc/freeradius/3.0/clients.conf`) used for this reference design can be downloaded from the appendix section of this guide.

radiusd.conf

The `radiusd.conf` file should be configured with the expected RADIUS authentication and accounting parameters.

```

prefix = /usr
exec_prefix = /usr
sysconfdir = /etc
localstatedir = /var
sbindir = ${exec_prefix}/sbin
logdir = /var/log/freeradius
raddbdir = /etc/freeradius
radacctdir = ${logdir}/radacct
name = freeradius
confdir = ${raddbdir}
modconfdir = ${confdir}/mods-config
run_dir = ${localstatedir}/run/${name}
db_dir = ${raddbdir}
libdir = /usr/lib/freeradius
pidfile = ${run_dir}/${name}.pid
correct_escapes = true
max_request_time = 5
cleanup_delay = 0
max_requests = 16384
hostname_lookups = no
log {
    destination = files
    file = ${logdir}/radius.log
    stripped_names = no
    auth = yes
}
checkrad = ${sbindir}/checkrad
security {
    # user = radius
    # group = radius
    allow_core_dumps = no
    max_attributes = 200
    reject_delay = 0
    status_server = no
@openssl_version_check_config@
}
proxy_requests = no
$INCLUDE clients.conf
thread pool {
    start_servers = 32
    max_servers = 128
    min_spare_servers = 8
    max_spare_servers = 16
    max_queue_size = 16384
    max_requests_per_server = 0
    auto_limit_acct = no
}
modules {
    $INCLUDE mods-enabled/
}
instantiate {
    files
    linelog
}
server default {
    listen {
        type = auth
        ipaddr = *
        port = 1812
    }
}

```

```

listen {
    type = acct
    ipaddr = *
    port = 1813
}
authorize {
    update request {
        FreeRADIUS-Client-Shortname = "%{&request:Client-Shortname}"
    }
    if (&request:Client-Shortname == "rtbrick-server") {
        rtbrick-server-log
    }
    files
    pap
}
authenticate {
    pap
}
post-auth {
    if (&request:Client-Shortname == "rtbrick-server") {
        rtbrick-server-log
    }
    Post-Auth-Type REJECT {
        update reply {
            Reply-Message := "Login Failed. Please check your username and
password."
        }
        attr_filter.access_reject
    }
}
preacct {
    ok
}
accounting {
    if (&request:Client-Shortname == "rtbrick-server") {
        rtbrick-server-log
    }
}
ok
}
session {
}
}

```

Radiusd.conf should be configured to use UDP ports 1812 and 1813 for authentication and accounting, respectively. Additionally, **rtbrick-server-log** should be added to the parameters for authorise, authenticate, and accounting.

The **radiusd.conf** file (`/etc/freeradius/3.0/radiusd.conf`) used for this reference design can be downloaded from the appendix section (Appendix C) of this guide.

detail

The **detail** file shall be configured for the RADIUS accounting logs.

```
/etc/freeradius/3.0 # cat mods-enabled/detail
permissions = 0666
detail rtbrick-server-log {
    filename = ${radacctdir}/rtbrick-server-detail.log

    header = "%t; %{NAS-IP-Address};%I;%{Packet-Src-Port}"
    log_packet_header = no
}
```

Ensure that **rtbrick-server-log** is specified in the **detail** file.

The **detail** file (`/etc/freeradius/3.0/mods-enabled/detail`) used for this reference design can be downloaded from the appendix section (Appendix C) of this guide.

dictionary.rtbrick

Add the RtBrick RADIUS dictionary (`dictionary.rtbrick`) to `/usr/share/freeradius/dictionary.rtbrick` and include it in `/usr/share/freeradius/dictionary``.

The `dictionary.rtbrick` contains the RBFS attributes in FreeRADIUS format.

→ Click [here](#) to download the `radius_config.zip`, which contains the `dictionary.rtbrick` file.

Stopping and Starting the FreeRADIUS Server for any Changes

For any changes, stop and restart the FreeRADIUS server.

To stop the server, enter the following command:

```
sudo service freeradius stop
```

To start the server, enter the following command:

```
sudo service freeradius start
```

The FreeRadius server is now ready to provide AAA (Authentication, Accounting & Authorization) services to logging in subscribers.

Displaying the RADIUS Service Status

Run the following command to determine whether RADIUS service is active:

```
sudo service freeradius status
```

Validating IPoE Subscriber Bring-Up

Using traffic streams on both upstream and downstream directions with traffic packets and bytes statistics, IPoE Subscriber sessions can be "ESTABLISHED".

The validation can be performed in two steps:

1. Establishing the IPoE subscriber
2. Pinging the subscriber IPv4/IPv6 address

BNG Blaster - IPoE Subscribers with Traffic Streams

Using BNG Blaster, which emulates IPoE clients, session traffic("session-traffic") and streams traffic with different code-points("streams"), one can test IPoE subscriber management feature.

The data traffic can be defined in Blaster by configuring session/streams traffic.

- Session Traffic in Blaster can be enabled by specifying "["autostart": true](#)". Once the session is established, traffic starts automatically. Eventually if you want to stop or start the traffic (session or streams), press F7/F8.
- Streams traffic in Blaster can be enabled by specifying [stream-group-id](#) at both streams (["streams":](#)) and access interface levels ([interfaces:access](#)).

For information about using BNG Blaster, see [\[refdesign:cbngipoe_refdesign_ipoe_subscriber_mgmt:::starting-bng-blaster\]](#).

Validating the IPoE Session on BNG Blaster

To validate the IPoE Session on BNG Blaster, switch to the Service Node. On the BNG Blaster terminal, the count of the "Established" session will be 1. Also, the logging of the same terminal will display "ALL SESSIONS ESTABLISHED" and "ALL SESSION TRAFFIC FLOWS VERIFIED" as highlighted in the below image.

In the image below, one can see the details of the established Single Subscriber session.

```

F1: Select View F7/F8: Start/Stop Traffic F9: Terminate Sessions
F2: Network Interface Left/Right: Access Interface

Test Duration: 3289s All Sessions Established: 3287s

Sessions          1 (0 PPPoE / 1 IPoE)
Established      1 [██████████]
Outstanding      0 []
Terminated       0 []
DHCPv4           1/1 [████████████████████████████████████████]
DHCPv6           1/1 [████████████████████████████████████████]
Setup Time        1516 ns
Setup Rate        0.66 CPS (MIN: 0.66 AVG: 0.66 MAX: 0.66)
Flapped          0

Traffic Flows Verified
Stream           8/8 [████████████████████████████████████████]

Network Interface ( SNI-3-C1 )
Tx Packets       26380283 | 8001 PPS   64982 Kbps
34376Packets    4849162 | 1475 PPS   11951 Kbps
9590 Stream Packets 26291586 | 8000 PPS
68866Stream Packets 48498989 | 1474 PPS 21444691 Loss
TX Multicast Packets 0 | 0 PPS
RX Multicast Packets 0 | 0 PPS   0 Loss

Access Interface ( SNI-2-C1 )
0 TX Packets     26292242 | 8001 PPS   65414 Kbps
9899 Packets    4228993 | 1286 PPS   10476 kbps
67587Stream Packets 26291587 | 8000 PPS
8627 Stream Packets 42289913 | 1286 PPS 8914863 Loss
RX Multicast Packets 0 | 0 PPS   0 Loss

Apr 03 12:37:44.884538 Loaded BGP RAW update file /home/supervisor/Internet.bgp (5434.80 KB, 1361 updates)
Apr 03 12:37:44.884683 Loaded LDP RAW update file /home/supervisor/out.ldp (0.11 KB, 3 pdu, 3 messages)
Apr 03 12:37:44.885876 Warning: Interfaces must be up on an interface before it can be used in host OS
Apr 03 12:37:44.948354 Warning: IP address fe80::fe80:cafe%fe80:181 on interface SNI-2-C1 is conflicting!
Apr 03 12:37:45.004357 Opened control socket run.sock
Apr 03 12:37:46.003916 Resolve network interfaces
Apr 03 12:37:46.004059 All network interfaces resolved
Apr 03 12:37:47.519782 ALL SESSIONS ESTABLISHED
Apr 03 12:37:47.671506 ALL STREAM TRAFFIC FLOWS VERIFIED

```

Fig 3: BNG Blaster terminal view

Visit the following URL for more information on BNG Blaster:

<https://rtbrick.github.io/bngblaster/>

Viewing the Subscribers and the Subscriber Details on RBFS

Enter the following command to view the list of subscribers.

```

supervisor@rtbrick>C-BNG.rtbrick.net: cfg> show subscriber
Subscriber-Id          Interface          VLAN      Type      State
216454257090494470    ifp-0/1/30      1001:1001  IPOE     ESTABLISHED
supervisor@rtbrick>C-BNG.rtbrick.net: cfg>

```

Enter the following command to view the details of the subscriber with ID **216454257090494470**.

```

supervisor@rtbrick>C-BNG.rtbrick.net: cfg> show subscriber 216454257090494470
detail
Subscriber-Id: 216454257090494470
  Type: IPOE
  State: ESTABLISHED
  Created: Mon Apr 03 13:51:17 GMT +0000 2023
  Interface: ifp-0/1/30
  Outer VLAN: 1001
  Inner VLAN: 1001
  Client MAC: 02:00:00:00:00:01
  Server MAC: e8:c5:7a:8f:76:f1
  IFL: ipoe-0/1/30/216454257090494470
  Username: 02:00:00:00:00:01@ipoe

```

```

Access-Profile: ipoe
AAA-Profile: aaa-profile
Service-Profile: qos_service
Reply-Message: FOOBAR Internet
Session-Timeout: 0 (disabled)
Idle-Timeout: 0 (disabled)
MTU: 1500 Profile: N/A
IPv4:
    Instance: default
    Address: 203.0.113.1/255.255.255.255
    Address Active: True
    Primary DNS: 203.0.113.200
    Secondary DNS: 203.0.113.201
IPv6:
    Instance: default
    RA Prefix: 2001:db8:0:1::1/128
    RA Prefix Active: True
    Delegated Prefix (DHCPv6): 2001:db8:0:3::/64
    Delegated Prefix Active: True
    Primary DNS: 2001:db8:0:20::1
    Secondary DNS: 2001:db8:0:20::2
Accounting:
    Session-Id: 216454257090494470:1680529877
    Start-Time: 2023-04-03T13:51:18.543868+0000
    Interims Interval: 120 seconds
supervisor@rtbrick>C-BNG.rtbrick.net: cfg>

```

Pinging the Subscriber (source: IPOE) from C-BNG

Before pinging a subscriber, use the `show route <...>` command to display the subscriber IPs at the C-BNG.

```

supervisor@rtbrick>C-BNG.rtbrick.net: cfg> show route ipv4 unicast source ipoe
Instance: default, AFI: ipv4, SAFI: unicast
Prefix/Label                               Source          Pref      Next Hop
Interface
203.0.113.1/32                           ipoe           7        -
ipoe-0/1/30/216454257090494470
supervisor@rtbrick>C-BNG.rtbrick.net: cfg>

```

```

supervisor@rtbrick>C-BNG.rtbrick.net: cfg> show route ipv6 unicast source ipoe
Instance: default, AFI: ipv6, SAFI: unicast
Prefix/Label                               Source          Pref      Next Hop
Interface
2001:db8:0:1::1/128                      ipoe           7        -
ipoe-0/1/30/216454257090494470
2001:db8:0:3::/64                         ipoe           7        -
fe80::ffff:ffff:ff00:1                   ipoe-0/1/30/216454257090494470

```

From the above list, ping `203.0.113.1` as shown below.

```

supervisor@rtbrick>C-BNG.rtbrick.net: cfg> ping 203.0.113.1
68 bytes from 203.0.113.1: icmp_seq=1 ttl=64 time=1.3463 ms

```

```

68 bytes from 203.0.113.1: icmp_seq=2 ttl=64 time=10.5234 ms
68 bytes from 203.0.113.1: icmp_seq=3 ttl=64 time=9.8053 ms
68 bytes from 203.0.113.1: icmp_seq=4 ttl=64 time=11.0041 ms
68 bytes from 203.0.113.1: icmp_seq=5 ttl=64 time=10.9300 ms
Statistics: 5 sent, 5 received, 0% packet loss
supervisor@rtbrick>C-BNG.rtbrick.net: cfg>

```

Validating Traffic Streams

Traffic streams can be used to perform various forwarding verifications.

For upstream traffic capture, enter the following command:

```
capture interface ifp-0/1/30 direction in
```

For downstream traffic capture, enter the following command:

```
capture interface ifp-0/1/30 direction out
```

Here, **ifp-0/1/30** refers to the access interface.

Validating the IPoE QoS on BNG Blaster

To validate the IPoE QoS on BNG Blaster, switch to the Service Node. Navigate to the Streams and Session Traffic terminal by pressing F1 function key in your keyboard.




Fig 4: Reading output from BNG Blaster

As shown in the above image, the VoIP downstream traffic has been shaped (session shaping) to 2Mbps. Similarly, the total subscriber traffic has been shaped approximately to 10Mbps.

Following are the upstream traffic rates of different policer levels:

- Level-1 Rates ~=2.5Mbps
- Level-2 Rates ~=3.5Mbps
- Level-3 Rates ~=4.5Mbps
- Level-4 Rates ~=1.5Mbps

IPoE Subscriber Accounting for Upstream and Downstream Traffic

Run the "show subscriber" command to view the list of subscribers.

```
supervisor@rtbrick>C-BNG.rtbrick.net: cfg> show subscriber
Subscriber-Id          Interface        VLAN      Type     State
216454257090494470    ifp-0/1/30    1001:1001  IPoE    ESTABLISHED
ESTABLISHEDsupervisor@rtbrick>C-BNG.rtbrick.net: cfg>
```

Specify the Subscriber-ID to find the specific subscriber's accounting details:

```
supervisor@rtbrick>C-BNG.rtbrick.net: cfg> show subscriber 216454257090494470
accounting
Subscriber-Id: 216454257090494470
  IFL: ipoe-0/1/30/216454257090494470
  Start Timestamp: Mon Apr 03 13:51:18 GMT +0000 2023
  Idle Timestamp: Mon Apr 03 13:51:38 GMT +0000 2023
  Session-Timeout: 0 seconds
  Idle-Timeout: 0 seconds
  Session Statistics:
    Ingress: 28185 packets 27339450 bytes
    Egress: 23990 packets 23990000 bytes
  LIF Statistics:
    Ingress: 0 packets 0 bytes
    Egress: 0 packets 0 bytes
  Egress Class (Queue) Statistics:
    class-0: 4 packets 4000 bytes dropped: 0 packets 0 bytes
    class-1: 19191 packets 19191000 bytes dropped: 0 packets 0 bytes
    class-2: 3 packets 3000 bytes dropped: 0 packets 0 bytes
    class-3: 4792 packets 4792000 bytes dropped: 0 packets 0 bytes
    class-4: 0 packets 0 bytes dropped: 0 packets 0 bytes
    class-5: 0 packets 0 bytes dropped: 0 packets 0 bytes
    class-6: 0 packets 0 bytes dropped: 0 packets 0 bytes
```

```

class-7: 0 packets 0 bytes dropped: 0 packets 0 bytes
Ingress Policer Statistics:
    Level 1: 5819 packets 5644430 bytes dropped: 31270 packets 30331900 bytes
    Level 2: 8170 packets 7924900 bytes dropped: 29029 packets 28158130 bytes
    Level 3: 10540 packets 10223800 bytes dropped: 26638 packets 25838860
bytes
    Level 4: 3656 packets 3546320 bytes dropped: 33614 packets 32605580 bytes
supervisor@rtbrick>C-BNG.rtbrick.net: cfg>

```

Configuring Lawful Intercept (LI)



This section is still a work in progress.

1.5. Appendixes

Appendix A: RBFS C-BNG Configuration

The RBFS C-BNG configuration file ([c-bng.json](#)) can be downloaded from here.

Click [here](#) to download the RBFS C-BNG configuration file.

Appendix B: TACACS+ Server Configuration

The TACACS+ server configuration file ([tac_plus.conf](#)) can be downloaded from here.

Click [here](#) to download the TACACS+ server configuration file.

Appendix C: RADIUS Server Configuration

The RADIUS server configuration files ([radius_config.zip](#)) can be downloaded from here. The zip archive contains the set of configuration files needed to configure the RADIUS server.

Click [here](#) to download the RADIUS server configuration files.

Appendix D: BNG Blaster Configuration

The BNG Blaster configuration file ([blaster.json](#)) can be downloaded from here.

Click [here](#) to download the BNG Blaster configuration files.

The JSON file ([isis_3node.json](#)) which is used to simulate R-1, R-2, and RR on BNG Blaster, can be downloaded from here.

Click [here](#) to download the [isis_3node.json](#) file.

2. RBFS C-BNG with Redundancy for IPoE Subscribers

2.1. RBFS C-BNG with Redundancy for IPoE Subscribers

Overview

RtBrick provides reference design architectures designed and validated with in-house testing tools and methods. This document guides you to validate RBFS Consolidated BNG - IPoE with Redundancy implementation.

About RBFS Redundancy

RBFS Redundancy protects subscriber services from node and link outages. It provides mechanisms to enhance network resiliency that enables subscriber workloads to remain functional by ensuring a reliable switchover in the event of a node or link outage. With RBFS Redundancy, if one node/protected link goes down, another node can automatically take over the services for a subscriber group.

RBFS Redundancy protects subscriber groups using an active-standby node cluster model. The active node for a subscriber group runs the workload, and the peer node, which acts as standby, mirrors the subscriber state data from the peer (active) and takes over the workload in the event of a node or link failure. It ensures that traffic can keep flowing in the event of an outage. For more information about RBFS redundancy solution, see [RBFS Redundancy Solution Guide](#).

About this Guide

It is recommended that you read this document after reading the [RBFS C-BNG for IPoE Subscribers Reference Design Guide](#), which provides all required configuration information and quick steps for validating the RBFS C-BNG with IPoE implementation. The configurations related to the protocols, Quality of Service (QoS), subscriber management, and FreeRADIUS Server are part of the [RBFS C-BNG for IPoE Subscribers Reference Design Guide](#).

This document provides information about the RBFS C-BNG - IPoE deployment in Redundancy (high availability) mode. It is mandatory to complete all the required configurations described in the [RBFS C-BNG for IPoE Subscribers Reference Design Guide](#) before deploying the C-BNG in the redundancy mode.

The document presents a single use case scenario and provides information on validating this implementation. For more information on any specific application, refer to <https://documents.rtbrick.com/>.


Currently, the guide's scope is limited to the basic features and configurations for validation purposes. This guide does not provide information about the advanced RBFS features such as multicast.

RBFS CBNG- IPoE with Redundancy Implementation Architecture

The architectural redundancy diagram below for RBFS C-BNG IPoE shows two bare metal switches installed with RBFS C-BNG software. This topology aims to demonstrate complete IPoE subscriber emulation with redundancy and routing to connect to the network uplink.

The devices are deployed in active and standby mode with respect to the lag bundles. `cbng1` is configured as the active device for lag-1, and `cbng2` is the standby device for lag-1. If one node goes down, the other node becomes stand-alone and takes over the subscribers for a subscriber group. RBFS devices (CBNGs) are connected to core routers on one side and OLTs (simulated by BNGBlaster) on the other.

When the active device goes down or a link failure occurs between the active RBFS device and the OLT device, the standby RBFS device detects the same and takes over from the previously active device.



In this topology:

- SN-19-RR is the Service Node which is a Linux container running on an Ubuntu server. BNG Blaster, which emulates routing and access functions, runs on this container. This container also runs FreeRADIUS, which emulates RADIUS functions.
- There are three routers; two acting as core routers (R-1 & R-2) and the third one as the Edge router. R-1, R-2, and Edge Router are RBFS virtual helper modes. The devices need not be RtBrick C-BNGs.

- CBNG1 and CBNG2 are the DUTs, which are two bare metal switches installed with the RBFS C-BNG software. On one side, these are connected to the Access Network, while on the other side, they are connected to the Core Network.
- The CBNGs form IS-IS adjacency and LDP session with the core routers R1 and R2, and the route reflectors (2 of them advertising 1M IPv4 prefixes each and the other two advertising 250K IPv6 prefixes each) are simulated by the BNG-Blaster.
- The topology brings up 20K IPoE subscribers (2 OLTs with 10K subscribers each simulated by BNG Blaster) over a LAG interface. A failure of a CBNG does not affect a subscriber's services since they are backed up among the CBNGs.

2.2. RBFS Redundancy Configurations

Configure RBFS Redundancy

To deploy RBFS in redundancy mode, you must complete the following configuration on both C-BNG nodes on top of the configuration explained in the *RBFS C-BNG for IPoE Subscribers: Reference Design Guide*.

- Redundancy Profile
- Redundancy Session
- Link Aggregation Group for the Redundancy Session
- Access for the Redundancy Session

The following steps provide the commands to configure RBFS Redundancy on both devices, which comprise the redundancy pair. For more detailed information about RBFS Redundancy Deployment, see [RBFS Redundancy Solution Guide](#).

Redundancy Profile Configuration

Run the following commands to configure the redundancy profile on both devices (CBNG1 and CBNG2). Redundancy profile configuration is required to enable the devices to identify the peer in the network.

```
set redundancy profile rd_ipoe_olt1
set redundancy profile rd_ipoe_olt1 switchover-hold-timer 0
set redundancy profile rd_ipoe_olt1 peer ipv4 remote-address 192.0.2.200
set redundancy profile rd_ipoe_olt1 peer ipv4 update-source 192.0.2.100
set redundancy profile rd_ipoe_olt1 peer ipv4 instance default
```

```
set redundancy profile rd_ipoe_olt2
set redundancy profile rd_ipoe_olt2 switchover-hold-timer 0
set redundancy profile rd_ipoe_olt2 peer ipv4 remote-address 192.0.2.20
set redundancy profile rd_ipoe_olt2 peer ipv4 update-source 192.0.2.10
set redundancy profile rd_ipoe_olt2 peer ipv4 instance default
```

Redundancy Session Configuration

Run the following commands to configure the session for redundancy. Redundancy sessions can be uniquely identified by session IDs, which are used to store subscriber-specific data between active and standby devices.

```
set redundancy session 100
set redundancy session 100 priority 20
set redundancy session 100 profile rd_ipoe_olt1
set redundancy session 200
set redundancy session 200 priority 210
set redundancy session 200 profile rd_ipoe_olt2
```

Redundancy configuration from the node **CBNG1** is shown below:

```
supervisor@rtbrick>cbng1.rtbrick.net: cfg> show config redundancy
{
  "rtbrick-config:redundancy": {
    "profile": [
      {
        "name": "rd_ipoe_olt1",
        "switchover-hold-timer": 0,
        "peer": {
          "ipv4": {
            "remote-address": "192.0.2.200",
            "update-source": "192.0.2.100",
            "instance": "default"
          }
        }
      },
      {
        "name": "rd_ipoe_olt2",
        "switchover-hold-timer": 0,
        "peer": {
          "ipv4": {
            "remote-address": "192.0.2.20",
            "update-source": "192.0.2.10",
            "instance": "default"
          }
        }
      }
    ],
    "session": [
      {
        "session-id": 100,
        "priority": 20,
        "profile": "rd_ipoe_olt1"
      },
      {
        "session-id": 200,
        "priority": 210,
        "profile": "rd_ipoe_olt2"
      }
    ]
  }
}
```

```
{
    "session-id": 200,
    "priority": 210,
    "profile": "rd_ipoe_olt2"
}
]
}
}
```

The redundancy configuration from the node **CBNG2** is shown below:

```
supervisor@rtbrick>cbng2.rtbrick.net: cfg> show config redundancy
{
    "rtbrick-config:redundancy": {
        "profile": [
            {
                "name": "rd_ipoe_olt1",
                "switchover-hold-timer": 0,
                "peer": {
                    "ipv4": {
                        "remote-address": "192.0.2.100",
                        "update-source": "192.0.2.200",
                        "instance": "default"
                    }
                }
            },
            {
                "name": "rd_ipoe_olt2",
                "switchover-hold-timer": 0,
                "peer": {
                    "ipv4": {
                        "remote-address": "192.0.2.10",
                        "update-source": "192.0.2.20",
                        "instance": "default"
                    }
                }
            }
        ],
        "session": [
            {
                "session-id": 100,
                "priority": 10,
                "profile": "rd_ipoe_olt1"
            },
            {
                "session-id": 200,
                "priority": 220,
                "profile": "rd_ipoe_olt2"
            }
        ]
    }
}
```



The session **priority** value determines the active/standby nodes for a session.

LAG Configuration for Redundancy

Run the following commands to configure LAG on both devices (**CBNG1** and **CBNG2**) for redundancy. This configuration is required to associate the redundancy session with LAG.

Run the following commands to configure LAG on **CBNG1** for redundancy.

```
set link-aggregation interface lag-1
set link-aggregation interface lag-1 mode lacp
set link-aggregation interface lag-1 minimum-link-count 3
set link-aggregation interface lag-1 redundancy-session-id 100
set link-aggregation interface lag-1 system-id a0:aa:aa:aa:aa:aa
set link-aggregation interface lag-1 member-interface ifp-0/1/26
set link-aggregation interface lag-1 member-interface ifp-0/1/27
set link-aggregation interface lag-1 member-interface ifp-0/1/28
set link-aggregation interface lag-11
set link-aggregation interface lag-11 mode lacp
set link-aggregation interface lag-11 minimum-link-count 3
set link-aggregation interface lag-11 redundancy-session-id 200
set link-aggregation interface lag-11 system-id a0:aa:aa:aa:aa:a0
set link-aggregation interface lag-11 member-interface ifp-0/1/31
set link-aggregation interface lag-11 member-interface ifp-0/1/33
set link-aggregation interface lag-11 member-interface ifp-0/1/35
set link-aggregation interface lag-2
set link-aggregation interface lag-2 mode lacp
set link-aggregation interface lag-2 minimum-link-count 1
set link-aggregation interface lag-2 member-interface ifp-0/1/14
set link-aggregation interface lag-2 member-interface ifp-0/1/15
set link-aggregation interface lag-3
set link-aggregation interface lag-3 mode lacp
set link-aggregation interface lag-3 minimum-link-count 1
set link-aggregation interface lag-3 member-interface ifp-0/1/23
set link-aggregation interface lag-3 member-interface ifp-0/1/24
```

LAG configuration for redundancy on CBNG1 is shown below:

```
supervisor@rtbrick>cbng1.rtbrick.net: cfg> show config link-aggregation
{
    "rtbrick-config:link-aggregation": {
        "interface": [
            {
                "interface-name": "lag-1",
                "mode": "lacp",
                "minimum-link-count": 3,
                "redundancy-session-id": 100,
                "system-id": "a0:aa:aa:aa:aa:aa",
                "member-interface": [
                    {
                        "member-interface-name": "ifp-0/1/26"
                    },
                    {
                        "member-interface-name": "ifp-0/1/27"
                    },
                    {
                        "member-interface-name": "ifp-0/1/28"
                    }
                ]
            }
        ]
    }
}
```

```

    {
        "member-interface-name": "ifp-0/1/28"
    }
]
},
{
    "interface-name": "lag-11",
    "mode": "lacp",
    "minimum-link-count": 3,
    "redundancy-session-id": 200,
    "system-id": "a0:aa:aa:aa:a0",
    "member-interface": [
        {
            "member-interface-name": "ifp-0/1/31"
        },
        {
            "member-interface-name": "ifp-0/1/33"
        },
        {
            "member-interface-name": "ifp-0/1/35"
        }
    ]
},
{
    "interface-name": "lag-2",
    "mode": "lacp",
    "minimum-link-count": 1,
    "member-interface": [
        {
            "member-interface-name": "ifp-0/1/14"
        },
        {
            "member-interface-name": "ifp-0/1/15"
        }
    ]
},
{
    "interface-name": "lag-3",
    "mode": "lacp",
    "minimum-link-count": 1,
    "member-interface": [
        {
            "member-interface-name": "ifp-0/1/23"
        },
        {
            "member-interface-name": "ifp-0/1/24"
        }
    ]
}
]
}
}

```

Run the following commands to configure LAG on **CBNG2** for redundancy.

```

set link-aggregation interface lag-1
set link-aggregation interface lag-1 mode lacp
set link-aggregation interface lag-1 minimum-link-count 3
set link-aggregation interface lag-1 redundancy-session-id 100

```

```

set link-aggregation interface lag-1 system-id a0:aa:aa:aa:aa:aa
set link-aggregation interface lag-1 member-interface ifp-0/1/26
set link-aggregation interface lag-1 member-interface ifp-0/1/27
set link-aggregation interface lag-1 member-interface ifp-0/1/28
set link-aggregation interface lag-11
set link-aggregation interface lag-11 mode lacp
set link-aggregation interface lag-11 minimum-link-count 3
set link-aggregation interface lag-11 redundancy-session-id 200
set link-aggregation interface lag-11 system-id a0:aa:aa:aa:aa:a0
set link-aggregation interface lag-11 member-interface ifp-0/1/31
set link-aggregation interface lag-11 member-interface ifp-0/1/33
set link-aggregation interface lag-11 member-interface ifp-0/1/35
set link-aggregation interface lag-2
set link-aggregation interface lag-2 mode lacp
set link-aggregation interface lag-2 minimum-link-count 1
set link-aggregation interface lag-2 member-interface ifp-0/1/14
set link-aggregation interface lag-2 member-interface ifp-0/1/15
set link-aggregation interface lag-3
set link-aggregation interface lag-3 mode lacp
set link-aggregation interface lag-3 minimum-link-count 1
set link-aggregation interface lag-3 member-interface ifp-0/1/23
set link-aggregation interface lag-3 member-interface ifp-0/1/24

```

LAG configuration for redundancy on CBNG2 is shown below:

```

supervisor@rtbrick>cbng2.rtbrick.net: cfg> show config link-aggregation
{
  "rtbrick-config:link-aggregation": {
    "interface": [
      {
        "interface-name": "lag-1",
        "mode": "lacp",
        "minimum-link-count": 3,
        "redundancy-session-id": 100,
        "system-id": "a0:aa:aa:aa:aa:aa",
        "member-interface": [
          {
            "member-interface-name": "ifp-0/1/30"
          },
          {
            "member-interface-name": "ifp-0/1/32"
          },
          {
            "member-interface-name": "ifp-0/1/33"
          }
        ]
      },
      {
        "interface-name": "lag-11",
        "mode": "lacp",
        "minimum-link-count": 3,
        "redundancy-session-id": 200,
        "system-id": "a0:aa:aa:aa:aa:a0",
        "member-interface": [
          {
            "member-interface-name": "ifp-0/1/34"
          },
          {
            "member-interface-name": "ifp-0/1/35"
          }
        ]
      }
    ]
  }
}

```

```
        },
        {
            "member-interface-name": "ifp-0/1/47"
        }
    ]
},
{
    "interface-name": "lag-2",
    "mode": "lacp",
    "minimum-link-count": 1,
    "member-interface": [
        {
            "member-interface-name": "ifp-0/1/14"
        },
        {
            "member-interface-name": "ifp-0/1/15"
        }
    ]
},
{
    "interface-name": "lag-3",
    "mode": "lacp",
    "minimum-link-count": 1,
    "member-interface": [
        {
            "member-interface-name": "ifp-0/1/25"
        },
        {
            "member-interface-name": "ifp-0/1/26"
        }
    ]
}
}
```

Access Configuration for Redundancy

Run the following commands to configure access interfaces on both of the devices (CBNG1 and CBNG2) for enabling redundancy.

```
set access chassis-id 1
set access aaa-profile ipoe-aaa
set access aaa-profile ipoe-aaa session-timeout 0
set access aaa-profile ipoe-aaa idle-timeout 0
set access aaa-profile ipoe-aaa aaa-radius-profile aaa-radius1
set access aaa-profile ipoe-aaa authentication order RADIUS
set access aaa-profile ipoe-aaa accounting order RADIUS
set access aaa-profile ipoe-aaa accounting interim-interval 30
set access aaa-profile ipoe-aaa accounting session-id-format DEFAULT
set access radius-profile aaa-radius1
set access radius-profile aaa-radius1 nas-identifier 192.0.2.1
set access radius-profile aaa-radius1 nas-port-type Ethernet
set access radius-profile aaa-radius1 authentication radius-server-profile-name radius-srv1
set access radius-profile aaa-radius1 accounting radius-server-profile-name radius-srv1
set access radius-server radius-srv1
set access radius-server radius-srv1 address 198.51.100.98
set access radius-server radius-srv1 source-address 192.0.2.1
```

```

set access radius-server radius-srv1 secret-encrypted-text $2b2feb12f730107454b1be6a0f8242b0f
set access radius-server radius-srv1 routing-instance default
set access radius-server radius-srv1 authentication enable true
set access radius-server radius-srv1 authentication timeout 10
set access radius-server radius-srv1 accounting enable true
set access radius-server radius-srv1 accounting timeout 10
set access radius-server radius-srv1 coa enable true
set access access-profile ipoe
set access access-profile ipoe protocol dhcp enable true
set access access-profile ipoe protocol dhcp lease-time 3600
set access access-profile ipoe protocol dhcipv6 enable true
set access access-profile ipoe protocol dhcipv6 lifetime 3600
set access access-profile ipoe address-family ipv4 enable true
set access access-profile ipoe address-family ipv4 pool-name pool1
set access access-profile ipoe address-family ipv4 instance default
set access access-profile ipoe address-family ipv6 enable true
set access access-profile ipoe address-family ipv6 pool-name pool1
set access access-profile ipoe address-family ipv6 prefix-delegation-pool-name pool2
set access access-profile ipoe address-family ipv6 instance default
set access interface double-tagged lag-1 1001 2000 1001 1100
set access interface double-tagged lag-1 1001 2000 1001 1100 access-type IPoE
set access interface double-tagged lag-1 1001 2000 1001 1100 access-profile-name ipoe
set access interface double-tagged lag-1 1001 2000 1001 1100 aaa-profile-name ipoe-aaa
set access interface double-tagged lag-1 1001 2000 1001 1100 gateway-ifl lo-0/0/0/10
set access interface double-tagged lag-1 1001 2000 1001 1100 redundancy-session-id 100
set access interface double-tagged lag-11 2001 3000 1001 1100
set access interface double-tagged lag-11 2001 3000 1001 1100 access-type IPoE
set access interface double-tagged lag-11 2001 3000 1001 1100 access-profile-name ipoe
set access interface double-tagged lag-11 2001 3000 1001 1100 aaa-profile-name ipoe-aaa
set access interface double-tagged lag-11 2001 3000 1001 1100 gateway-ifl lo-0/0/0/10
set access interface double-tagged lag-11 2001 3000 1001 1100 redundancy-session-id 200
set access pool pool1
set access pool pool1 ipv4-address low 11.100.128.1
set access pool pool1 ipv4-address high 15.100.128.255
set access pool pool1 ipv6-prefix low fc55:100:1:1::1/128
set access pool pool1 ipv6-prefix high fc55:100:1:2::5555/128
set access pool pool2
set access pool pool2 ipv6-prefix low fc56:100:1::/56
set access pool pool2 ipv6-prefix high fc56:100:5000::/56
set redundancy profile rd_ipoe_olt1

```

Access Configuration for Redundancy on CBNG-1 is shown below:

```

supervisor@rtbrick>cbng1.rtbrick.net: cfg> show config access
{
  "rtbrick-config:access": {
    "chassis-id": 1,
    "aaa-profile": [
      {
        "profile-name": "ipoe-aaa",
        "session-timeout": 0,
        "idle-timeout": 0,
        "aaa-radius-profile": "aaa-radius1",
        "authentication": {
          "order": "RADIUS"
        },
        "accounting": {
          "order": "RADIUS",
          "interim-interval": 30,
          "session-id-format": "DEFAULT"
        }
      }
    ],
    "radius-profile": [
      {
        "name": "aaa-radius1",
        "server": "radius-srv1"
      }
    ]
  }
}

```

```

"radius-profile": [
    {
        "profile-name": "aaa-radius1",
        "nas-identifier": "192.0.2.1",
        "nas-port-type": "Ethernet",
        "authentication": {
            "radius-server-profile-name": [
                "radius-srv1"
            ]
        },
        "accounting": {
            "radius-server-profile-name": [
                "radius-srv1"
            ]
        }
    }
],
"radius-server": [
    {
        "server-name": "radius-srv1",
        "address": "198.51.100.98",
        "source-address": "192.0.2.1",
        "secret-encrypted-text": "$2b2feb12f730107454b1be6a0f8242b0f",
        "routing-instance": "default",
        "authentication": {
            "enable": "true",
            "timeout": 10
        },
        "accounting": {
            "enable": "true",
            "timeout": 10
        },
        "coa": {
            "enable": "true"
        }
    }
],
"access-profile": [
    {
        "profile-name": "ipoe",
        "protocol": {
            "dhcp": {
                "enable": "true",
                "lease-time": 3600
            },
            "dhcpv6": {
                "enable": "true",
                "lifetime": 3600
            }
        },
        "address-family": {
            "ipv4": {
                "enable": "true",
                "pool-name": "pool1",
                "instance": "default"
            },
            "ipv6": {
                "enable": "true",
                "pool-name": "pool1",
                "prefix-delegation-pool-name": "pool2",
                "instance": "default"
            }
        }
    }
]

```

```

        }
    }
],
"interface": {
    "double-tagged": [
        {
            "interface-name": "lag-1",
            "outer-vlan-min": 1001,
            "outer-vlan-max": 2000,
            "inner-vlan-min": 1001,
            "inner-vlan-max": 1100,
            "access-type": "IPoE",
            "access-profile-name": "ipoe",
            "aaa-profile-name": "ipoe-aaa",
            "gateway-ifl": "lo-0/0/0/10",
            "redundancy-session-id": 100
        },
        {
            "interface-name": "lag-11",
            "outer-vlan-min": 2001,
            "outer-vlan-max": 3000,
            "inner-vlan-min": 1001,
            "inner-vlan-max": 1100,
            "access-type": "IPoE",
            "access-profile-name": "ipoe",
            "aaa-profile-name": "ipoe-aaa",
            "gateway-ifl": "lo-0/0/0/10",
            "redundancy-session-id": 200
        }
    ]
},
"pool": [
    {
        "pool-name": "pool1",
        "ipv4-address": {
            "low": "11.100.128.1",
            "high": "15.100.128.255"
        },
        "ipv6-prefix": {
            "low": "fc55:100:1:1::1/128",
            "high": "fc55:100:1:2::5555/128"
        }
    },
    {
        "pool-name": "pool2",
        "ipv6-prefix": {
            "low": "fc56:100:1::/56",
            "high": "fc56:100:5000::/56"
        }
    }
]
}
}

```

Access Configuration for Redundancy on CBNG-2 is shown below:

```
supervisor@rtbrick>cbng2.rtbrick.net: cfg> show config access
{
```

```

"rtbrick-config:access": {
    "chassis-id": 2,
    "aaa-profile": [
        {
            "profile-name": "ipoe-aaa",
            "session-timeout": 0,
            "idle-timeout": 0,
            "aaa-radius-profile": "aaa-radius1",
            "authentication": {
                "order": "RADIUS"
            },
            "accounting": {
                "order": "RADIUS",
                "interim-interval": 30,
                "session-id-format": "DEFAULT"
            }
        }
    ],
    "radius-profile": [
        {
            "profile-name": "aaa-radius1",
            "nas-identifier": "192.0.2.2",
            "nas-port-type": "Ethernet",
            "authentication": {
                "radius-server-profile-name": [
                    "radius-srv1"
                ]
            },
            "accounting": {
                "radius-server-profile-name": [
                    "radius-srv1"
                ]
            }
        }
    ],
    "radius-server": [
        {
            "server-name": "radius-srv1",
            "address": "198.51.100.98",
            "source-address": "192.0.2.2",
            "secret-encrypted-text": "$2b2feb12f730107454b1be6a0f8242b0f",
            "routing-instance": "default",
            "authentication": {
                "enable": "true",
                "timeout": 10
            },
            "accounting": {
                "enable": "true",
                "timeout": 10
            },
            "coa": {
                "enable": "true"
            }
        }
    ],
    "access-profile": [
        {
            "profile-name": "ipoe",
            "protocol": {
                "dhcp": {
                    "enable": "true",

```

```

        "lease-time": 3600
    },
    "dhcpv6": {
        "enable": "true",
        "lifetime": 3600
    }
},
"address-family": {
    "ipv4": {
        "enable": "true",
        "pool-name": "pool1",
        "instance": "default"
    },
    "ipv6": {
        "enable": "true",
        "pool-name": "pool1",
        "prefix-delegation-pool-name": "pool2",
        "instance": "default"
    }
}
],
"interface": {
    "double-tagged": [
        {
            "interface-name": "lag-1",
            "outer-vlan-min": 1001,
            "outer-vlan-max": 2000,
            "inner-vlan-min": 1001,
            "inner-vlan-max": 1100,
            "access-type": "IPoE",
            "access-profile-name": "ipoe",
            "aaa-profile-name": "ipoe-aaa",
            "gateway-ifl": "lo-0/0/0/10",
            "redundancy-session-id": 100
        },
        {
            "interface-name": "lag-11",
            "outer-vlan-min": 2001,
            "outer-vlan-max": 3000,
            "inner-vlan-min": 1001,
            "inner-vlan-max": 1100,
            "access-type": "IPoE",
            "access-profile-name": "ipoe",
            "aaa-profile-name": "ipoe-aaa",
            "gateway-ifl": "lo-0/0/0/10",
            "redundancy-session-id": 200
        }
    ]
},
"pool": [
    {
        "pool-name": "pool1",
        "ipv4-address": {
            "low": "16.100.128.1",
            "high": "20.100.128.255"
        },
        "ipv6-prefix": {
            "low": "fc66:100:1:1::1/128",
            "high": "fc66:100:1:2::5555/128"
        }
    }
]
}

```

```

    },
    {
      "pool-name": "pool2",
      "ipv6-prefix": {
        "low": "fc67:100:1::/56",
        "high": "fc67:100:5000::/56"
      }
    }
  ]
}
supervisor@rtbrick>ufi09.q2c.u19.r4.nbg.rtbrick.net: cfg>

```

BNG Blaster Configuration

BNG Blaster is an open-source network testing platform for access and routing protocols. It can emulate massive PPPoE and IPoE (DHCP) subscribers, including IPTV, and L2TP (LNS). One can use this platform for end-to-end BNG and non-BNG router testing. For more information about BNG Blaster, see <https://github.com/rtbrick/bngblaster>

Configure LAG on BNG Blaster for Redundancy Validation

With BNG blaster, you can validate the C-BNG - IPoE with Redundancy solution implementation and the traffic streams. BNG Blaster uses the following configuration file to validate C-BNG - IPoE with Redundancy.

```

{
  "interfaces": {
    "tx-interval": 1,
    "rx-interval": 1,
    "lag": [
      {
        "interface": "lag1",
        "lacp": true,
        "lacp-timeout-short": true
      },
      {
        "interface": "lag11",
        "lacp": true,
        "lacp-timeout-short": true
      }
    ],
    "links": [
      {
        "interface": "SN-5-C1",
        "lag-interface": "lag1"
      },
      {
        "interface": "SN-6-C1",
        "lag-interface": "lag1"
      },
    ],
  }
}

```

```
{
  "interface": "SN-7-C1",
  "lag-interface": "lag1"
},
{
  "interface": "SN-11-C2",
  "lag-interface": "lag1"
},
{
  "interface": "SN-12-C2",
  "lag-interface": "lag1"
},
{
  "interface": "SN-13-C2",
  "lag-interface": "lag1"
},
{
  "interface": "SN-20-C1",
  "lag-interface": "lag11"
},
{
  "interface": "SN-21-C1",
  "lag-interface": "lag11"
},
{
  "interface": "SN-22-C1",
  "lag-interface": "lag11"
},
{
  "interface": "SN-23-C2",
  "lag-interface": "lag11"
},
{
  "interface": "SN-24-C2",
  "lag-interface": "lag11"
},
{
  "interface": "SN-25-C2",
  "lag-interface": "lag11"
}
],
"network": [
  {
    "interface": "SN-19-RR",
    "address": "192.0.2.130/30",
    "gateway": "192.0.2.129",
    "address-ipv6": "2001:db8::130",
    "gateway-ipv6": "2001:db8::129",
    "isis-instance-id": 1,
    "isis-level": 1,
    "ldp-instance-id": 1
  }
],
"access": [
  {
    "interface": "lag1",
    "type": "ipoe",
    "agent-remote-id": "CBNG1.RTBRICK.{session-global}",
    "outer-vlan-min": 1001,
    "outer-vlan-max": 2000,
    "inner-vlan-min": 1001,
    "inner-vlan-max": 2000
  }
]
```

```

    "inner-vlan-max": 1100
  },
  {
    "interface": "lag11",
    "type": "ipoe",
    "agent-remote-id": "CBNG2.RTBRICK.{session-global}",
    "outer-vlan-min": 2001,
    "outer-vlan-max": 3000,
    "inner-vlan-min": 1001,
    "inner-vlan-max": 1100
  }
]
},
"sessions": {
  "count": 20000,
  "max-outstanding": 800,
  "start-rate": 400,
  "stop-rate": 400
},
"access-line": {
  "agent-remote-id": "DEU.RTBRICK.{session-global}",
  "agent-circuit-id": "0.0.0.0/0.0.0.0 eth 0:{session-global}",
  "rate-up": 2000,
  "rate-down": 16384,
  "dsl-type": 5
},
"dhcp": {
  "enable": true
},
"dhcpv6": {
  "ldra": true,
  "enable": true
},
"session-traffic": {
  "ipv4-pps": 1,
  "ipv6-pps": 1,
  "ipv6pd-pps": 1,
  "autostart": false
},
"ldp": [
  {
    "instance-id": 1,
    "lsr-id": "192.0.2.6",
    "keepalive-time": 30,
    "raw-update-file": "/home/supervisor/ldp_1000.ldp"
  }
],
"isis": [
  {
    "instance-id": 1,
    "area": [
      "49.0002/24"
    ],
    "system-id": "0204.0000.0001",
    "router-id": "192.0.2.6",
    "hostname": "BBL-RR",
    "hello-padding": true,
    "teardown-time": 30,
    "external": {
      "mrt-file": "/home/supervisor/isis_1000.mrt",
      "connections": [
        {
          "peer": "192.0.2.7"
        }
      ]
    }
  }
]
}

```

```

        }
        "system-id": "0300.1001.0001",
        "ll-metric": 10
    }
}
],
"bgp": [
{
    "__comment__": "RR1-C1-IPv4",
    "network-interface": "SN-19-RR",
    "local-ipv4-address": "198.51.100.10",
    "peer-ipv4-address": "192.0.2.1",
    "raw-update-file": "/home/supervisor/ipv4_nlri_nh1.bgp",
    "local-as": 4200000001,
    "peer-as": 4200000001
},
{
    "__comment__": "RR1-C1-IPv6",
    "network-interface": "SN-19-RR",
    "local-ipv4-address": "198.51.100.20",
    "peer-ipv4-address": "192.0.2.1",
    "raw-update-file": "/home/supervisor/ipv6_nlri_nh1.bgp",
    "local-as": 4200000001,
    "peer-as": 4200000001
},
{
    "__comment__": "RR1-C2-IPv4",
    "network-interface": "SN-19-RR",
    "local-ipv4-address": "198.51.100.10",
    "peer-ipv4-address": "192.0.2.2",
    "raw-update-file": "/home/supervisor/ipv4_nlri_nh1.bgp",
    "local-as": 4200000001,
    "peer-as": 4200000001
},
{
    "__comment__": "RR1-C2-IPv6",
    "network-interface": "SN-19-RR",
    "local-ipv4-address": "198.51.100.20",
    "peer-ipv4-address": "192.0.2.2",
    "raw-update-file": "/home/supervisor/ipv6_nlri_nh1.bgp",
    "local-as": 4200000001,
    "peer-as": 4200000001
},
{
    "__comment__": "RR2-C1-IPv4",
    "network-interface": "SN-19-RR",
    "local-ipv4-address": "198.51.100.30",
    "peer-ipv4-address": "192.0.2.1",
    "raw-update-file": "/home/supervisor/ipv4_nlri_nh2.bgp",
    "local-as": 4200000001,
    "peer-as": 4200000001
},
{
    "__comment__": "RR2-C1-IPv6",
    "network-interface": "SN-19-RR",
    "local-ipv4-address": "198.51.100.40",
    "peer-ipv4-address": "192.0.2.1",
    "raw-update-file": "/home/supervisor/ipv6_nlri_nh2.bgp",
    "local-as": 4200000001,
    "peer-as": 4200000001
}
]

```

```

    "peer-as": 4200000001
  },
  {
    "__comment__": "RR2-C2-IPv4",
    "network-interface": "SN-19-RR",
    "local-ipv4-address": "198.51.100.30",
    "peer-ipv4-address": "192.0.2.2",
    "raw-update-file": "/home/supervisor/ipv4_nlri_nh2.bgp",
    "local-as": 4200000001,
    "peer-as": 4200000001
  },
  {
    "__comment__": "RR2-C2-IPv6",
    "network-interface": "SN-19-RR",
    "local-ipv4-address": "198.51.100.40",
    "peer-ipv4-address": "192.0.2.2",
    "raw-update-file": "/home/supervisor/ipv6_nlri_nh2.bgp",
    "local-as": 4200000001,
    "peer-as": 4200000001
  }
]
}

```

Validating C-BNG Redundancy and Reachability

The following command line string shows how to start a BNG Blaster instance:

```
sudo bngblaster -C <filename> -I -c10
```

Redundancy Session Data and Subscriber States on Active and Standby Nodes

CBNG-1: Before switchover, which is the actual state

```

supervisor@rtbrick>cbng1.rtbrick.net: op> show redundancy session
Instance: default
Session ID      Interface     Peer          Source        State       Peer state   Keepalive rcvd
Keepalive sent
  100           lag-1         192.0.2.200  192.0.2.100  active      standby      91
  92
  200           lag-11        192.0.2.20   192.0.2.10   standby      active      91
  91
supervisor@rtbrick>cbng1.rtbrick.net: op>

```

```

supervisor@rtbrick>cbng1.rtbrick.net: op> show subscriber
Subscriber-Id      Interface     VLAN      Type      State
1369375761697341441  lag-1       1001:1001  IPoE     ESTABLISHED
1369375761697341442  lag-1       1001:1002  IPoE     ESTABLISHED
1369375761697341443  lag-1       1001:1003  IPoE     ESTABLISHED
1369375761697341444  lag-1       1001:1004  IPoE     ESTABLISHED
1369375761697341445  lag-1       1001:1005  IPoE     ESTABLISHED
2522297266304188417  lag-11      2001:1001  IPoE     STANDBY
2522297266304188418  lag-11      2001:1002  IPoE     STANDBY

```

```
2522297266304188419    lag-11          2001:1003  IPoE   STANDBY
2522297266304188420    lag-11          2001:1004  IPoE   STANDBY
2522297266304188421    lag-11          2001:1005  IPoE   STANDBY
supervisor@rtbrick>cbng1.rtbrick.net: op>
```

CBNG-2: Before switchover, which is the actual state

```
supervisor@rtbrick>cbng2.rtbrick.net: op> show redundancy session
Instance: default
Session ID      Interface     Peer           Source        State       Peer state   Keepalive rcvd
Keepalive sent
  100           lag-1         192.0.2.100  192.0.2.200  standby      active       94
  93
  200           lag-11        192.0.2.10   192.0.2.20   active       standby      93
supervisor@rtbrick>cbng2.rtbrick.net: op>
```

```
supervisor@rtbrick>cbng2.rtbrick.net: op> show subscriber
Subscriber-Id      Interface     VLAN        Type       State
1369375761697341441  lag-1         1001:1001  IPoE   STANDBY
1369375761697341442  lag-1         1001:1002  IPoE   STANDBY
1369375761697341443  lag-1         1001:1003  IPoE   STANDBY
1369375761697341444  lag-1         1001:1004  IPoE   STANDBY
1369375761697341445  lag-1         1001:1005  IPoE   STANDBY
2522297266304188417  lag-11        2001:1001  IPoE   ESTABLISHED
2522297266304188418  lag-11        2001:1002  IPoE   ESTABLISHED
2522297266304188419  lag-11        2001:1003  IPoE   ESTABLISHED
2522297266304188420  lag-11        2001:1004  IPoE   ESTABLISHED
2522297266304188421  lag-11        2001:1005  IPoE   ESTABLISHED
supervisor@rtbrick>cbng2.rtbrick.net: op>
```

Switchover Scenario for Link Failure Between Active C-BNG Node and Access (OLT) Node

After link (connecting OLT1 to CBNG1) is brought down, the state becomes **down** for the RD session 100 and for the same session, the other CBNG becomes **stand-alone**.

CBNG-1:

```
supervisor@rtbrick>cbng1.rtbrick.net: op> show redundancy session
Instance: default
Session ID      Interface     Peer           Source        State       Peer state   Keepalive rcvd
Keepalive sent
  100           lag-1         192.0.2.200  192.0.2.100  down        stand-alone  113
  114
  200           lag-11        192.0.2.20   192.0.2.10   standby      active       114
supervisor@rtbrick>cbng1.rtbrick.net: op>
```

```
supervisor@rtbrick>cbng1.rtbrick.net: op> show subscriber
Subscriber-Id      Interface     VLAN        Type       State
1369375761697341441  lag-1         1001:1001  IPoE   STANDBY
```

```

1369375761697341442    lag-1          1001:1002  IPoE   STANDBY
1369375761697341443    lag-1          1001:1003  IPoE   STANDBY
1369375761697341444    lag-1          1001:1004  IPoE   STANDBY
1369375761697341445    lag-1          1001:1005  IPoE   STANDBY
2522297266304188417    lag-11         2001:1001  IPoE   STANDBY
2522297266304188418    lag-11         2001:1002  IPoE   STANDBY
2522297266304188419    lag-11         2001:1003  IPoE   STANDBY
2522297266304188420    lag-11         2001:1004  IPoE   STANDBY
2522297266304188421    lag-11         2001:1005  IPoE   STANDBY
supervisor@rtbrick>cbng1.rtbrick.net: op>

```

CBNG-2:

```

supervisor@rtbrick>cbng2.rtbrick.net: op> show redundancy session
Instance: default
Session ID      Interface     Peer           Source        State       Peer state   Keepalive rcvd
Keepalive sent
  100            lag-1          192.0.2.100  192.0.2.200  stand-alone  down          115
  114
  200            lag-11         192.0.2.10   192.0.2.20   active        standby       115
supervisor@rtbrick>cbng2.rtbrick.net: op>

```

```

supervisor@rtbrick>cbng2.rtbrick.net: op> show subscriber
Subscriber-Id      Interface     VLAN        Type      State
1369375761697341441  lag-1          1001:1001  IPoE   ESTABLISHED
1369375761697341442  lag-1          1001:1002  IPoE   ESTABLISHED
1369375761697341443  lag-1          1001:1003  IPoE   ESTABLISHED
1369375761697341444  lag-1          1001:1004  IPoE   ESTABLISHED
1369375761697341445  lag-1          1001:1005  IPoE   ESTABLISHED
2522297266304188417  lag-11         2001:1001  IPoE   ESTABLISHED
2522297266304188418  lag-11         2001:1002  IPoE   ESTABLISHED
2522297266304188419  lag-11         2001:1003  IPoE   ESTABLISHED
2522297266304188420  lag-11         2001:1004  IPoE   ESTABLISHED
2522297266304188421  lag-11         2001:1005  IPoE   ESTABLISHED
supervisor@rtbrick>cbng2.rtbrick.net: op>

```

Failed OLT link comes up back (before node failure)

CBNG-1:

```

supervisor@rtbrick>cbng1.rtbrick.net: op> show redundancy session
Instance: default
Session ID      Interface     Peer           Source        State       Peer state   Keepalive rcvd
Keepalive sent
  100            lag-1          192.0.2.200  192.0.2.100  standby      active        163
  164
  200            lag-11         192.0.2.20   192.0.2.10   standby      active        163
supervisor@rtbrick>cbng1.rtbrick.net: op>

```

```

supervisor@rtbrick>cbng1.rtbrick.net: op> show subscriber
Subscriber-Id      Interface     VLAN        Type      State
1369375761697341441  lag-1          1001:1001  IPoE   STANDBY
1369375761697341442  lag-1          1001:1002  IPoE   STANDBY

```

```

1369375761697341443    lag-1          1001:1003  IPoE   STANDBY
1369375761697341444    lag-1          1001:1004  IPoE   STANDBY
1369375761697341445    lag-1          1001:1005  IPoE   STANDBY
2522297266304188417    lag-11         2001:1001  IPoE   STANDBY
2522297266304188418    lag-11         2001:1002  IPoE   STANDBY
2522297266304188419    lag-11         2001:1003  IPoE   STANDBY
2522297266304188420    lag-11         2001:1004  IPoE   STANDBY
2522297266304188421    lag-11         2001:1005  IPoE   STANDBY
supervisor@rtbrick>cbng1.rtbrick.net: op>

```

CBNG-2:

```

supervisor@rtbrick>cbng2.rtbrick.net: op> show redundancy session
Instance: default
Session ID      Interface     Peer           Source        State       Peer state   Keepalive rcvd
Keepalive sent
  100            lag-1          192.0.2.100  192.0.2.200  active      standby      166
165
  200            lag-11         192.0.2.10   192.0.2.20   active      standby      165
165
supervisor@rtbrick>cbng2.rtbrick.net: op>

```

```

supervisor@rtbrick>cbng2.rtbrick.net: op> show subscriber
Subscriber-Id      Interface     VLAN        Type       State
1369375761697341441  lag-1          1001:1001  IPoE   ESTABLISHED
1369375761697341442  lag-1          1001:1002  IPoE   ESTABLISHED
1369375761697341443  lag-1          1001:1003  IPoE   ESTABLISHED
1369375761697341444  lag-1          1001:1004  IPoE   ESTABLISHED
1369375761697341445  lag-1          1001:1005  IPoE   ESTABLISHED
2522297266304188417  lag-11         2001:1001  IPoE   ESTABLISHED
2522297266304188418  lag-11         2001:1002  IPoE   ESTABLISHED
2522297266304188419  lag-11         2001:1003  IPoE   ESTABLISHED
2522297266304188420  lag-11         2001:1004  IPoE   ESTABLISHED
2522297266304188421  lag-11         2001:1005  IPoE   ESTABLISHED
supervisor@rtbrick>cbng2.rtbrick.net: op>

```



To revert to the original active-standby mode based on the priority, a manual switchover can be performed using the [switch-over session 100 confirm](#) command.

Switchover Scenario for Active C-BNG Node Failure

CBNG-2's Session State and Subscriber State After node failure

```

supervisor@rtbrick>cbng2.rtbrick.net: op> show redundancy session
Instance: default
Session ID      Interface     Peer           Source        State       Peer state   Keepalive rcvd
Keepalive sent
  100            lag-1          192.0.2.100  192.0.2.200  stand-alone  invalid      194
196
  200            lag-11         192.0.2.10   192.0.2.20   stand-alone  invalid      193
196
supervisor@rtbrick>cbng2.rtbrick.net: op>

```

```
supervisor@rtbrick>cbng2.rtbrick.net: op> show subscriber
Subscriber-Id      Interface     VLAN    Type   State
1369375761697341441  lag-1       1001:1001  IPOE  ESTABLISHED
1369375761697341442  lag-1       1001:1002  IPOE  ESTABLISHED
1369375761697341443  lag-1       1001:1003  IPOE  ESTABLISHED
1369375761697341444  lag-1       1001:1004  IPOE  ESTABLISHED
1369375761697341445  lag-1       1001:1005  IPOE  ESTABLISHED
2522297266304188417  lag-11      2001:1001  IPOE  ESTABLISHED
2522297266304188418  lag-11      2001:1002  IPOE  ESTABLISHED
2522297266304188419  lag-11      2001:1003  IPOE  ESTABLISHED
2522297266304188420  lag-11      2001:1004  IPOE  ESTABLISHED
2522297266304188421  lag-11      2001:1005  IPOE  ESTABLISHED
supervisor@rtbrick>cbng2.rtbrick.net: op>
```

Appendix A: CBNG1 Configuration

Show CBNG1 Configuration

```
{
  "ietf-restconf:data": {
    "rtbrick-config:system": {
      "load-last-config": "true",
      "host": {
        "element-name": "ufi08.q2c.u23.r4.nbg.rtbrick.net",
        "pod-name": "nbg4"
      }
    },
    "rtbrick-config:redundancy": {
      "profile": [
        {
          "name": "rd_ipoe_olt1",
          "switchover-hold-timer": 0,
          "peer": {
            "ipv4": {
              "remote-address": "192.0.2.200",
              "update-source": "192.0.2.100",
              "instance": "default"
            }
          }
        },
        {
          "name": "rd_ipoe_olt2",
          "switchover-hold-timer": 0,
          "peer": {
            "ipv4": {
              "remote-address": "192.0.2.20",
              "update-source": "192.0.2.10",
              "instance": "default"
            }
          }
        }
      ],
      "session": [
        {
          "session-id": 100,
          "priority": 20,
          "profile": "rd_ipoe_olt1"
        },
        {
          "session-id": 101,
          "priority": 20,
          "profile": "rd_ipoe_olt2"
        }
      ]
    }
  }
}
```

```
{  
    "session-id": 200,  
    "priority": 210,  
    "profile": "rd_ipoe_olt2"  
}  
]  
},  
"rtbrick-config:interface": [  
    {  
        "name": "ifp-0/1/23",  
        "speed": "10G"  
    },  
    {  
        "name": "ifp-0/1/24",  
        "speed": "10G"  
    },  
    {  
        "name": "ifp-0/1/25",  
        "speed": "10G"  
    },  
    {  
        "name": "ifp-0/1/26",  
        "speed": "10G"  
    },  
    {  
        "name": "ifp-0/1/27",  
        "speed": "10G"  
    },  
    {  
        "name": "ifp-0/1/28",  
        "speed": "10G"  
    },  
    {  
        "name": "ifp-0/1/31",  
        "speed": "10G"  
    },  
    {  
        "name": "ifp-0/1/33",  
        "speed": "10G"  
    },  
    {  
        "name": "ifp-0/1/35",  
        "speed": "10G"  
    },  
    {  
        "name": "ifp-0/1/37",  
        "speed": "10G"  
    },  
    {  
        "name": "ifp-0/1/40",  
        "speed": "10G"  
    },  
    {  
        "name": "ifp-0/1/41",  
        "speed": "10G"  
    },  
    {  
        "name": "ifp-0/1/42",  
        "speed": "10G"  
    },  
]
```

```
        "name": "ifp-0/1/43",
        "speed": "10G"
    },
    {
        "name": "lag-2",
        "unit": [
            {
                "unit-id": 10,
                "address": {
                    "ipv4": [
                        {
                            "prefix4": "192.0.2.61/30"
                        }
                    ],
                    "ipv6": [
                        {
                            "prefix6": "2001:db8::61/127"
                        }
                    ]
                }
            }
        ]
    },
    {
        "name": "lag-3",
        "unit": [
            {
                "unit-id": 10,
                "address": {
                    "ipv4": [
                        {
                            "prefix4": "192.0.2.69/30"
                        }
                    ],
                    "ipv6": [
                        {
                            "prefix6": "2001:db8::69/127"
                        }
                    ]
                }
            }
        ]
    },
    {
        "name": "lo-0/0/0",
        "unit": [
            {
                "unit-id": 10,
                "address": {
                    "ipv4": [
                        {
                            "prefix4": "192.0.2.1/32"
                        }
                    ],
                    "ipv6": [
                        {
                            "prefix6": "2001:db8::1/128"
                        }
                    ]
                }
            }
        ]
    }
}
```

```

        ],
    },
{
    "name": "lo-0/0/1",
    "unit": [
        {
            "unit-id": 10,
            "address": {
                "ipv4": [
                    {
                        "prefix4": "192.0.2.100/32"
                    }
                ],
                "ipv6": [
                    {
                        "prefix6": "2001:db8::100/128"
                    }
                ]
            }
        }
    ],
{
    "name": "lo-0/0/2",
    "unit": [
        {
            "unit-id": 10,
            "address": {
                "ipv4": [
                    {
                        "prefix4": "192.0.2.10/32"
                    }
                ],
                "ipv6": [
                    {
                        "prefix6": "2001:db8::10/128"
                    }
                ]
            }
        }
    ]
},
"rtbrick-config:forwarding-options": {
    "class-of-service": {
        "classifier": [
            {
                "classifier-name": "subs-exp-class",
                "match-type": [
                    {
                        "match-type": "exp",
                        "codepoint": [
                            {
                                "codepoint": 1,
                                "class": "class-0"
                            },
                            {
                                "codepoint": 2,
                                "class": "class-1"
                            }
                        ]
                    }
                ]
            }
        ]
    }
}

```

```

        "codepoint": 3,
        "class": "class-2"
    },
    {
        "codepoint": 4,
        "class": "class-3"
    }
]
}
],
{
    "classifier-name": "subs-pbit-class",
    "match-type": [
        {
            "match-type": "ieee-802.1",
            "codepoint": [
                {
                    "codepoint": 1,
                    "class": "class-0"
                },
                {
                    "codepoint": 2,
                    "class": "class-1"
                },
                {
                    "codepoint": 3,
                    "class": "class-2"
                },
                {
                    "codepoint": 4,
                    "class": "class-3"
                }
            ]
        }
    ]
},
"class-policer-map": [
    {
        "class-policer-map-name": "policer-map-residential",
        "class": [
            {
                "class": "class-0",
                "policer-level": "level-1"
            },
            {
                "class": "class-1",
                "policer-level": "level-2"
            },
            {
                "class": "class-2",
                "policer-level": "level-3"
            },
            {
                "class": "class-3",
                "policer-level": "level-4"
            }
        ]
    }
],

```

```

"class-queue-map": [
    {
        "class-queue-map-name": "subs-4queues",
        "class": [
            {
                "class-type": "class-0",
                "queue-name": "BE_SUBS"
            },
            {
                "class-type": "class-1",
                "queue-name": "LD_SUBS"
            },
            {
                "class-type": "class-2",
                "queue-name": "LL_SUBS"
            },
            {
                "class-type": "class-3",
                "queue-name": "VO_SUBS"
            }
        ]
    }
],
"global": {
    "multifield-classifier-name": "global_udpmfc"
},
"interface": [
    {
        "name": "lag-1",
        "ingress-header-compensation": {
            "bytes": 34,
            "decrement": "true"
        },
        "scheduler-map-name": "schedmap-olt"
    },
    {
        "name": "lag-11",
        "ingress-header-compensation": {
            "bytes": 34,
            "decrement": "true"
        },
        "scheduler-map-name": "schedmap-olt"
    }
],
"policer": [
    {
        "policer-name": "policer-residential",
        "level1-rates": {
            "cir": 2000,
            "cbs": 1000,
            "pir": 2500,
            "pbs": 1000
        },
        "level2-rates": {
            "cir": 3000,
            "cbs": 1000,
            "pir": 3500,
            "pbs": 1000
        },
        "level3-rates": {
            "cir": 4000,
            "cbs": 1000,
            "pir": 4500,
            "pbs": 1000
        }
    }
]
}

```

```
        "cbs": 1000,
        "pir": 4500,
        "pbs": 1000
    },
    "level4-rates": {
        "cir": 1000,
        "cbs": 1000,
        "pir": 1500,
        "pbs": 1000
    },
    "levels": 4,
    "type": "two-rate-three-color"
},
{
    "policer-name": "policer-residential-gold",
    "level1-rates": {
        "cir": 1000,
        "cbs": 1000,
        "pir": 1500,
        "pbs": 1000
    },
    "level2-rates": {
        "cir": 2000,
        "cbs": 1000,
        "pir": 2500,
        "pbs": 1000
    },
    "level3-rates": {
        "cir": 3000,
        "cbs": 1000,
        "pir": 3500,
        "pbs": 1000
    },
    "level4-rates": {
        "cir": 1000,
        "cbs": 1000,
        "pir": 1500,
        "pbs": 1000
    },
    "levels": 4,
    "type": "two-rate-three-color"
},
{
    "policer-name": "policer-residential-platinum",
    "level1-rates": {
        "cir": 5000,
        "cbs": 1000,
        "pir": 5500,
        "pbs": 1000
    },
    "level2-rates": {
        "cir": 6000,
        "cbs": 1000,
        "pir": 6500,
        "pbs": 1000
    },
    "level3-rates": {
        "cir": 5000,
        "cbs": 1000,
        "pir": 5500,
        "pbs": 1000
    }
}
```

```

        },
        "level4-rates": {
            "cir": 6000,
            "cbs": 1000,
            "pir": 6500,
            "pbs": 1000
        },
        "levels": 4,
        "type": "two-rate-three-color"
    }
],
"profile": [
{
    "profile-name": "subs-triple-play",
    "classifier-name": "subs-pbit-class",
    "class-queue-map-name": "subs-4queues",
    "remark-map-name": "subs-remarking-triple-play",
    "class-policer-map-name": "policer-map-residential",
    "policer-name": "policer-residential",
    "scheduler-map-name": "subs-4queues-triple-play"
},
{
    "profile-name": "subs-triple-play-gold",
    "classifier-name": "subs-pbit-class",
    "class-queue-map-name": "subs-4queues",
    "remark-map-name": "subs-remarking-triple-play",
    "class-policer-map-name": "policer-map-residential",
    "policer-name": "policer-residential-gold",
    "scheduler-map-name": "subs-4queues-triple-play-gold"
},
{
    "profile-name": "subs-triple-play-platinum",
    "classifier-name": "subs-pbit-class",
    "class-queue-map-name": "subs-4queues",
    "remark-map-name": "subs-remarking-triple-play",
    "class-policer-map-name": "policer-map-residential",
    "policer-name": "policer-residential-platinum",
    "scheduler-map-name": "subs-4queues-triple-play-platinum"
}
],
"queue": [
{
    "queue-name": "BE_SUBS",
    "queue-size": 375000,
    "header-compensation": {
        "bytes": 22,
        "decrement": "true"
    }
},
{
    "queue-name": "LD_SUBS",
    "queue-size": 625000,
    "header-compensation": {
        "bytes": 22,
        "decrement": "true"
    }
},
{
    "queue-name": "LL_SUBS",
    "queue-size": 625000,
    "header-compensation": {

```

```

        "bytes": 22,
        "decrement": "true"
    }
},
{
    "queue-name": "VO_SUBS",
    "queue-size": 156250,
    "shaper-name": "shaper_VO",
    "header-compensation": {
        "bytes": 22,
        "decrement": "true"
    }
}
],
"queue-group": [
{
    "queue-group-name": "subs-4queues",
    "queue-numbers": 4
}
],
"remark-map": [
{
    "remark-map-name": "subs-remarking-triple-play",
    "remark-type": [
        {
            "remark-type": "ieee-802.1",
            "match-codepoint": [
                {
                    "match-codepoint": 1,
                    "color": [
                        {
                            "color": "all",
                            "remark-codepoint": 3
                        }
                    ]
                },
                {
                    "match-codepoint": 2,
                    "color": [
                        {
                            "color": "all",
                            "remark-codepoint": 4
                        }
                    ]
                },
                {
                    "match-codepoint": 3,
                    "color": [
                        {
                            "color": "all",
                            "remark-codepoint": 5
                        }
                    ]
                },
                {
                    "match-codepoint": 224,
                    "color": [
                        {
                            "color": "all",
                            "remark-codepoint": 6
                        }
                    ]
                }
            ]
        }
    ]
}
]

```

```

        ]
    }
]
}
],
"scheduler": [
{
    "scheduler-name": "pon0",
    "shaper-name": "pon_shaper",
    "type": "fair_queueing"
},
{
    "scheduler-name": "pon1",
    "type": "fair_queueing"
},
{
    "scheduler-name": "subs-4queues",
    "shaper-name": "shaper_session",
    "type": "strict_priority",
    "composite": "false"
},
{
    "scheduler-name": "subs-4queues-gold",
    "shaper-name": "shaper_session_gold",
    "type": "strict_priority",
    "composite": "false"
},
{
    "scheduler-name": "subs-4queues-platinum",
    "shaper-name": "shaper_session_platinum",
    "type": "strict_priority",
    "composite": "false"
}
],
"scheduler-map": [
{
    "scheduler-map-name": "schedmap-olt",
    "scheduler-name": [
        {
            "name": "pon0",
            "port-connection": "scheduler_to_port"
        },
        {
            "name": "pon1",
            "port-connection": "scheduler_to_port"
        }
    ]
},
{
    "scheduler-map-name": "subs-4queues-triple-play",
    "queue-group-name": [
        {
            "group-name": "subs-4queues",
            "queue-name": [
                {
                    "name": "BE_SUBS",
                    "parent-flow": "low-flow",
                    "parent-scheduler-name": "subs-4queues",
                    "connection-point": "strict_priority_3"
                }
            ]
        }
    ]
}
]
```

```

        },
        {
            "name": "LD_SUBS",
            "parent-flow": "high-flow",
            "parent-scheduler-name": "subs-4queues",
            "connection-point": "strict_priority_1"
        },
        {
            "name": "LL_SUBS",
            "parent-flow": "high-flow",
            "parent-scheduler-name": "subs-4queues",
            "connection-point": "strict_priority_2"
        },
        {
            "name": "VO_SUBS",
            "parent-flow": "high-flow",
            "parent-scheduler-name": "subs-4queues",
            "connection-point": "strict_priority_0"
        }
    ]
}
],
"scheduler-name": [
{
    "name": "subs-4queues",
    "port-connection": "scheduler_to_port"
}
]
},
{
    "scheduler-map-name": "subs-4queues-triple-play-gold",
    "queue-group-name": [
    {
        "group-name": "subs-4queues",
        "queue-name": [
        {
            "name": "BE_SUBS",
            "parent-flow": "low-flow",
            "parent-scheduler-name": "subs-4queues-gold",
            "connection-point": "strict_priority_3"
        },
        {
            "name": "LD_SUBS",
            "parent-flow": "high-flow",
            "parent-scheduler-name": "subs-4queues-gold",
            "connection-point": "strict_priority_1"
        },
        {
            "name": "LL_SUBS",
            "parent-flow": "high-flow",
            "parent-scheduler-name": "subs-4queues-gold",
            "connection-point": "strict_priority_2"
        },
        {
            "name": "VO_SUBS",
            "parent-flow": "high-flow",
            "parent-scheduler-name": "subs-4queues-gold",
            "connection-point": "strict_priority_0"
        }
    ]
}
]
}

```

```

] ,
"scheduler-name": [
{
  "name": "subs-4queues-gold",
  "port-connection": "scheduler_to_port"
}
]
},
{
  "scheduler-map-name": "subs-4queues-triple-play-platinum",
  "queue-group-name": [
{
  "group-name": "subs-4queues",
  "queue-name": [
{
  "name": "BE_SUBS",
  "parent-flow": "low-flow",
  "parent-scheduler-name": "subs-4queues-platinum",
  "connection-point": "strict_priority_3"
},
{
  "name": "LD_SUBS",
  "parent-flow": "high-flow",
  "parent-scheduler-name": "subs-4queues-platinum",
  "connection-point": "strict_priority_1"
},
{
  "name": "LL_SUBS",
  "parent-flow": "high-flow",
  "parent-scheduler-name": "subs-4queues-platinum",
  "connection-point": "strict_priority_2"
},
{
  "name": "VO_SUBS",
  "parent-flow": "high-flow",
  "parent-scheduler-name": "subs-4queues-platinum",
  "connection-point": "strict_priority_0"
}
]
}
],
"scheduler-name": [
{
  "name": "subs-4queues-platinum",
  "port-connection": "scheduler_to_port"
}
]
},
],
"shaper": [
{
  "shaper-name": "pon_shaper",
  "shaping-rate-high": 1000000,
  "shaping-rate-low": 1000000
},
{
  "shaper-name": "shaper_VO",
  "shaping-rate-high": 1000,
  "shaping-rate-low": 0
}
]
}

```

```

        "shaper-name": "shaper_session",
        "shaping-rate-high": 10000,
        "shaping-rate-low": 2000
    },
    {
        "shaper-name": "shaper_session_gold",
        "shaping-rate-high": 13000,
        "shaping-rate-low": 1000
    },
    {
        "shaper-name": "shaper_session_platinum",
        "shaping-rate-high": 15000,
        "shaping-rate-low": 1000
    }
],
"multifield-classifier": {
    "acl": {
        "l3v4": {
            "rule": [
                {
                    "rule-name": "global_mfc",
                    "ordinal": [
                        {
                            "ordinal-value": 101,
                            "match": {
                                "ipv4-tos": 128,
                                "source-ipv4-prefix": "192.0.2.132/32"
                            },
                            "action": {
                                "forward-class": "class-0"
                            }
                        },
                        {
                            "ordinal-value": 102,
                            "match": {
                                "ipv4-tos": 64,
                                "source-ipv4-prefix": "192.0.2.132/32"
                            },
                            "action": {
                                "forward-class": "class-1"
                            }
                        },
                        {
                            "ordinal-value": 103,
                            "match": {
                                "ipv4-tos": 96,
                                "source-ipv4-prefix": "192.0.2.132/32"
                            },
                            "action": {
                                "forward-class": "class-2"
                            }
                        },
                        {
                            "ordinal-value": 104,
                            "match": {
                                "ipv4-tos": 32,
                                "source-ipv4-prefix": "192.0.2.132/32"
                            },
                            "action": {
                                "forward-class": "class-3"
                            }
                        }
                    ]
                }
            ]
        }
    }
}

```

```

        }
    ]
},
{
    "rule-name": "global_udpmfrc",
    "ordinal": [
        {
            "ordinal-value": 101,
            "match": {
                "source-ipv4-prefix": "192.0.2.132/32",
                "source-l4-port": 65001
            },
            "action": {
                "forward-class": "class-0"
            }
        },
        {
            "ordinal-value": 102,
            "match": {
                "source-ipv4-prefix": "192.0.2.132/32",
                "source-l4-port": 65002
            },
            "action": {
                "forward-class": "class-1"
            }
        },
        {
            "ordinal-value": 103,
            "match": {
                "source-ipv4-prefix": "192.0.2.132/32",
                "source-l4-port": 65003
            },
            "action": {
                "forward-class": "class-2"
            }
        },
        {
            "ordinal-value": 104,
            "match": {
                "source-ipv4-prefix": "192.0.2.132/32",
                "source-l4-port": 65004
            },
            "action": {
                "forward-class": "class-3"
            }
        }
    ]
},
{
    "rtbrick-config:link-aggregation": {
        "interface": [
            {
                "interface-name": "lag-1",
                "mode": "lacp",
                "minimum-link-count": 3,
                "redundancy-session-id": 100,

```

```

    "system-id": "a0:aa:aa:aa:aa:aa",
    "member-interface": [
        {
            "member-interface-name": "ifp-0/1/26"
        },
        {
            "member-interface-name": "ifp-0/1/27"
        },
        {
            "member-interface-name": "ifp-0/1/28"
        }
    ]
},
{
    "interface-name": "lag-11",
    "mode": "lacp",
    "minimum-link-count": 3,
    "redundancy-session-id": 200,
    "system-id": "a0:aa:aa:aa:aa:a0",
    "member-interface": [
        {
            "member-interface-name": "ifp-0/1/31"
        },
        {
            "member-interface-name": "ifp-0/1/33"
        },
        {
            "member-interface-name": "ifp-0/1/35"
        }
    ]
},
{
    "interface-name": "lag-2",
    "mode": "lacp",
    "minimum-link-count": 1,
    "member-interface": [
        {
            "member-interface-name": "ifp-0/1/14"
        },
        {
            "member-interface-name": "ifp-0/1/15"
        }
    ]
},
{
    "interface-name": "lag-3",
    "mode": "lacp",
    "minimum-link-count": 1,
    "member-interface": [
        {
            "member-interface-name": "ifp-0/1/23"
        },
        {
            "member-interface-name": "ifp-0/1/24"
        }
    ]
},
{
    "rtbrick-config:lldp": {
        "system-name": "ufi08.q2c.u23.r4.nbg.rtbrick.net"
    }
}

```

```

},
"rtbrick-config:instance": [
{
  "name": "default",
  "protocol": {
    "isis": {
      "system-id": "1921.6800.1001",
      "area": [
        "49.0002/24"
      ],
      "interface": [
        {
          "name": "lag-2/10",
          "type": "point-to-point",
          "ldp-synchronization": "enable",
          "level-2": {
            "adjacency-disable": "true"
          }
        },
        {
          "name": "lag-3/10",
          "type": "point-to-point",
          "ldp-synchronization": "enable",
          "level-2": {
            "adjacency-disable": "true"
          }
        },
        {
          "name": "lo-0/0/0/10",
          "type": "point-to-point",
          "passive": "true"
        }
      ]
    },
    "bgp": {
      "domain-name": "CBNG1",
      "enforce-first-as": "disable",
      "hostname": "CBNG1",
      "local-as": 4200000001,
      "router-id": "192.1.0.1",
      "address-family": [
        {
          "afi": "ipv4",
          "safi": "unicast",
          "multipath": 10,
          "resolve-nexthop": {
            "safi": "labeled-unicast"
          },
          "redistribute": [
            {
              "source": "static",
              "policy": "SEND_AGGREGATED_V4"
            }
          ]
        },
        {
          "afi": "ipv6",
          "safi": "labeled-unicast"
        },
        {
          "afi": "ipv6",
        }
      ]
    }
  }
}
]
}

```

```

        "safi": "unicast",
        "multipath": 10,
        "resolve-nexthop": {
            "safi": "labeled-unicast"
        },
        "redistribute": [
            {
                "source": "static",
                "policy": "SEND_AGGREGATED_V6"
            }
        ]
    },
    "peer": [
        "ipv4": [
            {
                "peer-address": "192.0.2.51",
                "update-source": "192.0.2.1",
                "peer-group": "send_aggregated"
            },
            {
                "peer-address": "198.51.100.10",
                "update-source": "192.0.2.1",
                "peer-group": "reflector"
            },
            {
                "peer-address": "198.51.100.20",
                "update-source": "192.0.2.1",
                "peer-group": "reflector"
            },
            {
                "peer-address": "198.51.100.30",
                "update-source": "192.0.2.1",
                "peer-group": "reflector"
            },
            {
                "peer-address": "198.51.100.40",
                "update-source": "192.0.2.1",
                "peer-group": "reflector"
            }
        ],
        "peer-group": [
            {
                "pg-name": "reflector",
                "remote-as": 4200000001,
                "address-family": [
                    {
                        "afi": "ipv4",
                        "safi": "unicast"
                    },
                    {
                        "afi": "ipv6",
                        "safi": "labeled-unicast"
                    },
                    {
                        "afi": "ipv6",
                        "safi": "unicast",
                        "send-label": "true"
                    }
                ]
            }
        ]
    ]
}

```

```

},
{
  "pg-name": "send_aggregated",
  "remote-as": 4200000001,
  "address-family": [
    {
      "afi": "ipv4",
      "safi": "unicast"
    },
    {
      "afi": "ipv6",
      "safi": "labeled-unicast"
    },
    {
      "afi": "ipv6",
      "safi": "unicast",
      "send-label": "true"
    }
  ]
}
],
"ldp": {
  "router-id": "192.0.2.1",
  "interface": [
    {
      "name": "lag-2/10"
    },
    {
      "name": "lag-3/10"
    },
    {
      "name": "lo-0/0/0/10"
    }
  ]
},
"static": {
  "route": {
    "ipv4": [
      {
        "prefix4": "11.100.0.0/16",
        "safi": "unicast",
        "nexthop-profile": "subscriber"
      },
      {
        "prefix4": "12.100.0.0/16",
        "safi": "unicast",
        "nexthop-profile": "subscriber"
      },
      {
        "prefix4": "13.100.0.0/16",
        "safi": "unicast",
        "nexthop-profile": "subscriber"
      },
      {
        "prefix4": "14.100.0.0/16",
        "safi": "unicast",
        "nexthop-profile": "subscriber"
      }
    ]
  }
}

```

```

        "prefix4": "15.100.0.0/16",
        "safi": "unicast",
        "nexthop-profile": "subscriber"
    },
{
    "prefix4": "16.100.0.0/16",
    "safi": "unicast",
    "nexthop-profile": "subscriber"
},
{
    "prefix4": "17.100.0.0/16",
    "safi": "unicast",
    "nexthop-profile": "subscriber"
},
{
    "prefix4": "18.100.0.0/16",
    "safi": "unicast",
    "nexthop-profile": "subscriber"
},
{
    "prefix4": "19.100.0.0/16",
    "safi": "unicast",
    "nexthop-profile": "subscriber"
},
{
    "prefix4": "192.0.2.20/32",
    "safi": "unicast",
    "nexthop-profile": "rd_route"
},
{
    "prefix4": "192.0.2.200/32",
    "safi": "unicast",
    "nexthop-profile": "rd_route"
},
{
    "prefix4": "198.51.100.96/30",
    "safi": "unicast",
    "nexthop-profile": "radius"
},
{
    "prefix4": "20.100.0.0/16",
    "safi": "unicast",
    "nexthop-profile": "subscriber"
}
],
"ipv6": [
{
    "prefix6": "fc55::/16",
    "safi": "unicast",
    "nexthop-profile": "subscriber"
},
{
    "prefix6": "fc56::/16",
    "safi": "unicast",
    "nexthop-profile": "subscriber"
},
{
    "prefix6": "fc66::/16",
    "safi": "unicast",
    "nexthop-profile": "subscriber"
}
],

```

```

        {
            "prefix6": "fc67::/16",
            "safi": "unicast",
            "nexthop-profile": "subscriber"
        }
    ],
},
"nexthop-profile": [
{
    "name": "radius",
    "nexthop": "192.0.2.51",
    "lookup-instance": "default",
    "lookup-afi": "ipv4",
    "lookup-safi": "labeled-unicast"
},
{
    "name": "rd_route",
    "nexthop": "192.0.2.2",
    "lookup-instance": "default",
    "lookup-afi": "ipv4",
    "lookup-safi": "labeled-unicast"
},
{
    "name": "subscriber",
    "exit-interface": "null0"
}
]
},
],
"rtbrick-config:policy": {
"statement": [
{
    "name": "SEND_AGGREGATED_V4",
    "ordinal": [
{
        "ordinal": 1,
        "match": {
            "rule": [
{
                "rule": 1,
                "type": "ipv4-prefix",
                "value-type": "discrete",
                "match-type": "regex",
                "value": [
                    ".*/16"
                ]
}
]
}
]
}
],
},
{
    "name": "SEND_AGGREGATED_V6",
    "ordinal": [
{
        "ordinal": 1,
        "match": {
            "rule": [
{
}
]
}
]
}
],
}
}

```



```

    "accounting": {
        "enable": "true",
        "timeout": 10
    },
    "coa": {
        "enable": "true"
    }
}
],
"access-profile": [
{
    "profile-name": "ipoe",
    "protocol": {
        "dhcp": {
            "enable": "true",
            "lease-time": 3600
        },
        "dhcpv6": {
            "enable": "true",
            "lifetime": 3600
        }
    },
    "address-family": {
        "ipv4": {
            "enable": "true",
            "pool-name": "pool1",
            "instance": "default"
        },
        "ipv6": {
            "enable": "true",
            "pool-name": "pool1",
            "prefix-delegation-pool-name": "pool2",
            "instance": "default"
        }
    }
}
],
"interface": {
    "double-tagged": [
{
        "interface-name": "lag-1",
        "outer-vlan-min": 1001,
        "outer-vlan-max": 2000,
        "inner-vlan-min": 1001,
        "inner-vlan-max": 1100,
        "access-type": "IPoE",
        "access-profile-name": "ipoe",
        "aaa-profile-name": "ipoe-aaa",
        "gateway-ifl": "lo-0/0/0/10",
        "redundancy-session-id": 100
},
{
        "interface-name": "lag-11",
        "outer-vlan-min": 2001,
        "outer-vlan-max": 3000,
        "inner-vlan-min": 1001,
        "inner-vlan-max": 1100,
        "access-type": "IPoE",
        "access-profile-name": "ipoe",
        "aaa-profile-name": "ipoe-aaa",
        "qateway-ifl": "lo-0/0/0/10",
        "redundancy-session-id": 100
}
]
}
]
```

```
        "redundancy-session-id": 200
    }
]
},
"pool": [
{
    "pool-name": "pool1",
    "ipv4-address": {
        "low": "11.100.128.1",
        "high": "15.100.128.255"
    },
    "ipv6-prefix": {
        "low": "fc55:100:1:1::1/128",
        "high": "fc55:100:1:2::5555/128"
    }
},
{
    "pool-name": "pool2",
    "ipv6-prefix": {
        "low": "fc56:100:1::/56",
        "high": "fc56:100:5000::/56"
    }
}
]
```

Appendix B: CBNG2 Configuration

Show CBNG2 Configuration

```
{
    "ietf-restconf:config": {
        "rtbrick-config:system": {
            "load-last-config": "true",
            "host": {
                "element-name": "ufi09.q2c.u19.r4.nbg.rtbrick.net",
                "pod-name": "nbg4"
            }
        },
        "rtbrick-config:redundancy": {
            "profile": [
                {
                    "name": "rd_ipoe_olt1",
                    "switchover-hold-timer": 0,
                    "peer": {
                        "ipv4": {
                            "remote-address": "192.0.2.100",
                            "update-source": "192.0.2.200",
                            "instance": "default"
                        }
                    }
                },
                {
                    "name": "rd_ipoe_olt2",
                    "switchover-hold-timer": 0,
                    "peer": {
                        "ipv4": {
                            "remote-address": "192.0.2.101",
                            "update-source": "192.0.2.201",
                            "instance": "default"
                        }
                    }
                }
            ]
        }
    }
}
```

```

        "ipv4": [
            {
                "remote-address": "192.0.2.10",
                "update-source": "192.0.2.20",
                "instance": "default"
            }
        ]
    ],
    "session": [
        {
            "session-id": 100,
            "priority": 10,
            "profile": "rd_ipoe_olt1"
        },
        {
            "session-id": 200,
            "priority": 220,
            "profile": "rd_ipoe_olt2"
        }
    ]
},
"rtbrick-config:interface": [
    {
        "name": "ifp-0/1/25",
        "speed": "10G"
    },
    {
        "name": "ifp-0/1/26",
        "speed": "10G"
    },
    {
        "name": "ifp-0/1/28",
        "speed": "10G"
    },
    {
        "name": "ifp-0/1/30",
        "speed": "10G"
    },
    {
        "name": "ifp-0/1/32",
        "speed": "10G"
    },
    {
        "name": "ifp-0/1/33",
        "speed": "10G"
    },
    {
        "name": "ifp-0/1/34",
        "speed": "10G"
    },
    {
        "name": "ifp-0/1/35",
        "speed": "10G"
    },
    {
        "name": "ifp-0/1/40",
        "speed": "10G"
    },
    {
        "name": "ifp-0/1/41",
        "speed": "10G"
    }
]
}

```

```

} ,
{
  "name": "ifp-0/1/42",
  "speed": "10G"
},
{
  "name": "ifp-0/1/43",
  "speed": "10G"
},
{
  "name": "ifp-0/1/47",
  "speed": "10G"
},
{
  "name": "lag-2",
  "unit": [
    {
      "unit-id": 10,
      "address": {
        "ipv4": [
          {
            "prefix4": "192.0.2.62/30"
          }
        ],
        "ipv6": [
          {
            "prefix6": "2001:db8::62/127"
          }
        ]
      }
    }
  ]
},
{
  "name": "lag-3",
  "unit": [
    {
      "unit-id": 10,
      "address": {
        "ipv4": [
          {
            "prefix4": "192.0.2.77/30"
          }
        ],
        "ipv6": [
          {
            "prefix6": "2001:db8::77/127"
          }
        ]
      }
    }
  ]
},
{
  "name": "lo-0/0/0",
  "unit": [
    {
      "unit-id": 10,
      "address": {
        "ipv4": [
          {

```

```

        "prefix4": "192.0.2.2/32"
    }
],
"ipv6": [
{
    "prefix6": "2001:db8::2/128"
}
]
}
]
},
{
"name": "lo-0/0/1",
"unit": [
{
"unit-id": 10,
"address": {
"ipv4": [
{
"prefix4": "192.0.2.200/32"
}
],
"ipv6": [
{
"prefix6": "2001:db8::200/128"
}
]
}
}
]
},
{
"name": "lo-0/0/2",
"unit": [
{
"unit-id": 10,
"address": {
"ipv4": [
{
"prefix4": "192.0.2.20/32"
}
],
"ipv6": [
{
"prefix6": "2001:db8::20/128"
}
]
}
}
]
},
{
"rtbrick-config:forwarding-options": {
"class-of-service": {
"classifier": [
{
"classifier-name": "subs-exp-class",
"match-type": [
{
"match-type": "exp",

```

```

    "codepoint": [
        {
            "codepoint": 1,
            "class": "class-0"
        },
        {
            "codepoint": 2,
            "class": "class-1"
        },
        {
            "codepoint": 3,
            "class": "class-2"
        },
        {
            "codepoint": 4,
            "class": "class-3"
        }
    ]
},
{
    "classifier-name": "subs-pbit-class",
    "match-type": [
        {
            "match-type": "ieee-802.1",
            "codepoint": [
                {
                    "codepoint": 1,
                    "class": "class-0"
                },
                {
                    "codepoint": 2,
                    "class": "class-1"
                },
                {
                    "codepoint": 3,
                    "class": "class-2"
                },
                {
                    "codepoint": 4,
                    "class": "class-3"
                }
            ]
        }
    ]
},
{
    "class-policer-map": [
        {
            "class-policer-map-name": "policer-map-residential",
            "class": [
                {
                    "class": "class-0",
                    "policer-level": "level-1"
                },
                {
                    "class": "class-1",
                    "policer-level": "level-2"
                }
            ]
        }
    ]
}
]

```

```

        "class": "class-2",
        "policer-level": "level-3"
    },
    {
        "class": "class-3",
        "policer-level": "level-4"
    }
]
],
"class-queue-map": [
{
    "class-queue-map-name": "subs-4queues",
    "class": [
        {
            "class-type": "class-0",
            "queue-name": "BE_SUBS"
        },
        {
            "class-type": "class-1",
            "queue-name": "LD_SUBS"
        },
        {
            "class-type": "class-2",
            "queue-name": "LL_SUBS"
        },
        {
            "class-type": "class-3",
            "queue-name": "VO_SUBS"
        }
    ]
},
{
    "global": {
        "multifield-classifier-name": "global_udpmfc"
    },
    "interface": [
        {
            "name": "lag-1",
            "ingress-header-compensation": {
                "bytes": 34,
                "decrement": "true"
            },
            "scheduler-map-name": "schedmap-olt"
        },
        {
            "name": "lag-11",
            "ingress-header-compensation": {
                "bytes": 34,
                "decrement": "true"
            },
            "scheduler-map-name": "schedmap-olt"
        }
    ],
    "policer": [
        {
            "policer-name": "policer-residential",
            "level1-rates": {
                "cir": 2000,
                "cbs": 1000,
                "pir": 2500,
            }
        }
    ]
}
]
}
]
```

```

        "pbs": 1000
    },
    "level2-rates": {
        "cir": 3000,
        "cbs": 1000,
        "pir": 3500,
        "pbs": 1000
    },
    "level3-rates": {
        "cir": 4000,
        "cbs": 1000,
        "pir": 4500,
        "pbs": 1000
    },
    "level4-rates": {
        "cir": 1000,
        "cbs": 1000,
        "pir": 1500,
        "pbs": 1000
    },
    "levels": 4,
    "type": "two-rate-three-color"
},
{
    "policer-name": "policer-residential-gold",
    "level1-rates": {
        "cir": 1000,
        "cbs": 1000,
        "pir": 1500,
        "pbs": 1000
    },
    "level2-rates": {
        "cir": 2000,
        "cbs": 1000,
        "pir": 2500,
        "pbs": 1000
    },
    "level3-rates": {
        "cir": 3000,
        "cbs": 1000,
        "pir": 3500,
        "pbs": 1000
    },
    "level4-rates": {
        "cir": 1000,
        "cbs": 1000,
        "pir": 1500,
        "pbs": 1000
    },
    "levels": 4,
    "type": "two-rate-three-color"
},
{
    "policer-name": "policer-residential-platinum",
    "level1-rates": {
        "cir": 5000,
        "cbs": 1000,
        "pir": 5500,
        "pbs": 1000
    },
    "level2-rates": {

```

```

        "cir": 6000,
        "cbs": 1000,
        "pir": 6500,
        "pbs": 1000
    },
    "level3-rates": {
        "cir": 5000,
        "cbs": 1000,
        "pir": 5500,
        "pbs": 1000
    },
    "level4-rates": {
        "cir": 6000,
        "cbs": 1000,
        "pir": 6500,
        "pbs": 1000
    },
    "levels": 4,
    "type": "two-rate-three-color"
}
],
"profile": [
{
    "profile-name": "subs-triple-play",
    "classifier-name": "subs-pbit-class",
    "class-queue-map-name": "subs-4queues",
    "remark-map-name": "subs-remarking-triple-play",
    "class-policer-map-name": "policer-map-residential",
    "policer-name": "policer-residential",
    "scheduler-map-name": "subs-4queues-triple-play"
},
{
    "profile-name": "subs-triple-play-gold",
    "classifier-name": "subs-pbit-class",
    "class-queue-map-name": "subs-4queues",
    "remark-map-name": "subs-remarking-triple-play",
    "class-policer-map-name": "policer-map-residential",
    "policer-name": "policer-residential-gold",
    "scheduler-map-name": "subs-4queues-triple-play-gold"
},
{
    "profile-name": "subs-triple-play-platinum",
    "classifier-name": "subs-pbit-class",
    "class-queue-map-name": "subs-4queues",
    "remark-map-name": "subs-remarking-triple-play",
    "class-policer-map-name": "policer-map-residential",
    "policer-name": "policer-residential-platinum",
    "scheduler-map-name": "subs-4queues-triple-play-platinum"
}
],
"queue": [
{
    "queue-name": "BE_SUBS",
    "queue-size": 375000,
    "header-compensation": {
        "bytes": 22,
        "decrement": "true"
    }
},
{
    "queue-name": "LD_SUBS",

```

```

    "queue-size": 625000,
    "header-compensation": {
        "bytes": 22,
        "decrement": "true"
    }
},
{
    "queue-name": "LL_SUBS",
    "queue-size": 625000,
    "header-compensation": {
        "bytes": 22,
        "decrement": "true"
    }
},
{
    "queue-name": "VO_SUBS",
    "queue-size": 156250,
    "shaper-name": "shaper_VO",
    "header-compensation": {
        "bytes": 22,
        "decrement": "true"
    }
}
],
"queue-group": [
{
    "queue-group-name": "subs-4queues",
    "queue-numbers": 4
}
],
"remark-map": [
{
    "remark-map-name": "subs-remarking-triple-play",
    "remark-type": [
        {
            "remark-type": "ieee-802.1",
            "match-codepoint": [
                {
                    "match-codepoint": 1,
                    "color": [
                        {
                            "color": "all",
                            "remark-codepoint": 3
                        }
                    ]
                },
                {
                    "match-codepoint": 2,
                    "color": [
                        {
                            "color": "all",
                            "remark-codepoint": 4
                        }
                    ]
                },
                {
                    "match-codepoint": 3,
                    "color": [
                        {
                            "color": "all",
                            "remark-codepoint": 5
                        }
                    ]
                }
            ]
        }
    ]
}
]
}

```

```

        }
    ]
},
{
    "match-codepoint": 224,
    "color": [
        {
            "color": "all",
            "remark-codepoint": 6
        }
    ]
}
],
"scheduler": [
{
    "scheduler-name": "pon0",
    "shaper-name": "pon_shaper",
    "type": "fair_queueing"
},
{
    "scheduler-name": "pon1",
    "type": "fair_queueing"
},
{
    "scheduler-name": "subs-4queues",
    "shaper-name": "shaper_session",
    "type": "strict_priority",
    "composite": "false"
},
{
    "scheduler-name": "subs-4queues-gold",
    "shaper-name": "shaper_session_gold",
    "type": "strict_priority",
    "composite": "false"
},
{
    "scheduler-name": "subs-4queues-platinum",
    "shaper-name": "shaper_session_platinum",
    "type": "strict_priority",
    "composite": "false"
}
],
"scheduler-map": [
{
    "scheduler-map-name": "schedmap-olt",
    "scheduler-name": [
        {
            "name": "pon0",
            "port-connection": "scheduler_to_port"
        },
        {
            "name": "pon1",
            "port-connection": "scheduler_to_port"
        }
    ]
},
{
}
]
}

```

```

    "scheduler-map-name": "subs-4queues-triple-play",
    "queue-group-name": [
        {
            "group-name": "subs-4queues",
            "queue-name": [
                {
                    "name": "BE_SUBS",
                    "parent-flow": "low-flow",
                    "parent-scheduler-name": "subs-4queues",
                    "connection-point": "strict_priority_3"
                },
                {
                    "name": "LD_SUBS",
                    "parent-flow": "high-flow",
                    "parent-scheduler-name": "subs-4queues",
                    "connection-point": "strict_priority_1"
                },
                {
                    "name": "LL_SUBS",
                    "parent-flow": "high-flow",
                    "parent-scheduler-name": "subs-4queues",
                    "connection-point": "strict_priority_2"
                },
                {
                    "name": "VO_SUBS",
                    "parent-flow": "high-flow",
                    "parent-scheduler-name": "subs-4queues",
                    "connection-point": "strict_priority_0"
                }
            ]
        }
    ],
    "scheduler-name": [
        {
            "name": "subs-4queues",
            "port-connection": "scheduler_to_port"
        }
    ]
},
{
    "scheduler-map-name": "subs-4queues-triple-play-gold",
    "queue-group-name": [
        {
            "group-name": "subs-4queues",
            "queue-name": [
                {
                    "name": "BE_SUBS",
                    "parent-flow": "low-flow",
                    "parent-scheduler-name": "subs-4queues-gold",
                    "connection-point": "strict_priority_3"
                },
                {
                    "name": "LD_SUBS",
                    "parent-flow": "high-flow",
                    "parent-scheduler-name": "subs-4queues-gold",
                    "connection-point": "strict_priority_1"
                },
                {
                    "name": "LL_SUBS",
                    "parent-flow": "high-flow",
                    "parent-scheduler-name": "subs-4queues-gold",
                    "connection-point": "strict_priority_2"
                }
            ]
        }
    ],
    "scheduler-name": [
        {
            "name": "subs-4queues-gold",
            "port-connection": "scheduler_to_port"
        }
    ]
}

```

```

        "connection-point": "strict_priority_2"
    },
    {
        "name": "VO_SUBS",
        "parent-flow": "high-flow",
        "parent-scheduler-name": "subs-4queues-gold",
        "connection-point": "strict_priority_0"
    }
]
}
],
"scheduler-name": [
{
    "name": "subs-4queues-gold",
    "port-connection": "scheduler_to_port"
}
]
},
{
"scheduler-map-name": "subs-4queues-triple-play-platinum",
"queue-group-name": [
{
    "group-name": "subs-4queues",
    "queue-name": [
{
        "name": "BE_SUBS",
        "parent-flow": "low-flow",
        "parent-scheduler-name": "subs-4queues-platinum",
        "connection-point": "strict_priority_3"
},
{
        "name": "LD_SUBS",
        "parent-flow": "high-flow",
        "parent-scheduler-name": "subs-4queues-platinum",
        "connection-point": "strict_priority_1"
},
{
        "name": "LL_SUBS",
        "parent-flow": "high-flow",
        "parent-scheduler-name": "subs-4queues-platinum",
        "connection-point": "strict_priority_2"
}
],
{
        "name": "VO_SUBS",
        "parent-flow": "high-flow",
        "parent-scheduler-name": "subs-4queues-platinum",
        "connection-point": "strict_priority_0"
}
]
}
],
"scheduler-name": [
{
    "name": "subs-4queues-platinum",
    "port-connection": "scheduler_to_port"
}
]
},
],
"shaper": [
{

```

```

        "shaper-name": "pon_shaper",
        "shaping-rate-high": 1000000,
        "shaping-rate-low": 1000000
    },
    {
        "shaper-name": "shaper_VO",
        "shaping-rate-high": 1000,
        "shaping-rate-low": 0
    },
    {
        "shaper-name": "shaper_session",
        "shaping-rate-high": 10000,
        "shaping-rate-low": 2000
    },
    {
        "shaper-name": "shaper_session_gold",
        "shaping-rate-high": 13000,
        "shaping-rate-low": 1000
    },
    {
        "shaper-name": "shaper_session_platinum",
        "shaping-rate-high": 15000,
        "shaping-rate-low": 1000
    }
],
"multifield-classifier": {
    "acl": {
        "l3v4": {
            "rule": [
                {
                    "rule-name": "global_mfc",
                    "ordinal": [
                        {
                            "ordinal-value": 101,
                            "match": {
                                "ipv4-tos": 128,
                                "source-ipv4-prefix": "192.0.2.132/32"
                            },
                            "action": {
                                "forward-class": "class-0"
                            }
                        },
                        {
                            "ordinal-value": 102,
                            "match": {
                                "ipv4-tos": 64,
                                "source-ipv4-prefix": "192.0.2.132/32"
                            },
                            "action": {
                                "forward-class": "class-1"
                            }
                        },
                        {
                            "ordinal-value": 103,
                            "match": {
                                "ipv4-tos": 96,
                                "source-ipv4-prefix": "192.0.2.132/32"
                            },
                            "action": {
                                "forward-class": "class-2"
                            }
                        }
                    ]
                }
            ]
        }
    }
}

```

```

        },
        {
          "ordinal-value": 104,
          "match": {
            "ipv4-tos": 32,
            "source-ipv4-prefix": "192.0.2.132/32"
          },
          "action": {
            "forward-class": "class-3"
          }
        }
      ]
    },
    {
      "rule-name": "global_udpmfc",
      "ordinal": [
        {
          "ordinal-value": 101,
          "match": {
            "source-ipv4-prefix": "192.0.2.132/32",
            "source-l4-port": 65001
          },
          "action": {
            "forward-class": "class-0"
          }
        },
        {
          "ordinal-value": 102,
          "match": {
            "source-ipv4-prefix": "192.0.2.132/32",
            "source-l4-port": 65002
          },
          "action": {
            "forward-class": "class-1"
          }
        },
        {
          "ordinal-value": 103,
          "match": {
            "source-ipv4-prefix": "192.0.2.132/32",
            "source-l4-port": 65003
          },
          "action": {
            "forward-class": "class-2"
          }
        },
        {
          "ordinal-value": 104,
          "match": {
            "source-ipv4-prefix": "192.0.2.132/32",
            "source-l4-port": 65004
          },
          "action": {
            "forward-class": "class-3"
          }
        }
      ]
    }
  }
}

```

```

        }
    },
},
"rtbrick-config:link-aggregation": {
    "interface": [
        {
            "interface-name": "lag-1",
            "mode": "lacp",
            "minimum-link-count": 3,
            "redundancy-session-id": 100,
            "system-id": "a0:aa:aa:aa:aa:aa",
            "member-interface": [
                {
                    "member-interface-name": "ifp-0/1/30"
                },
                {
                    "member-interface-name": "ifp-0/1/32"
                },
                {
                    "member-interface-name": "ifp-0/1/33"
                }
            ]
        },
        {
            "interface-name": "lag-11",
            "mode": "lacp",
            "minimum-link-count": 3,
            "redundancy-session-id": 200,
            "system-id": "a0:aa:aa:aa:aa:a0",
            "member-interface": [
                {
                    "member-interface-name": "ifp-0/1/34"
                },
                {
                    "member-interface-name": "ifp-0/1/35"
                },
                {
                    "member-interface-name": "ifp-0/1/47"
                }
            ]
        },
        {
            "interface-name": "lag-2",
            "mode": "lacp",
            "minimum-link-count": 1,
            "member-interface": [
                {
                    "member-interface-name": "ifp-0/1/14"
                },
                {
                    "member-interface-name": "ifp-0/1/15"
                }
            ]
        },
        {
            "interface-name": "lag-3",
            "mode": "lacp",
            "minimum-link-count": 1,
            "member-interface": [
                {
                    "member-interface-name": "ifp-0/1/25"
                }
            ]
        }
    ]
}

```

```

        },
        {
            "member-interface-name": "ifp-0/1/26"
        }
    ]
}
},
"rtbrick-config:lldp": {
    "system-name": "ufi09.q2c.ul9.r4.nbg.rtbrick.net"
},
"rtbrick-config:instance": [
{
    "name": "default",
    "protocol": {
        "isis": {
            "system-id": "1920.0000.2002",
            "area": [
                "49.0002/24"
            ],
            "interface": [
                {
                    "name": "lag-2/10",
                    "type": "point-to-point",
                    "ldp-synchronization": "enable",
                    "level-2": {
                        "adjacency-disable": "true"
                    }
                },
                {
                    "name": "lag-3/10",
                    "type": "point-to-point",
                    "ldp-synchronization": "enable",
                    "level-2": {
                        "adjacency-disable": "true"
                    }
                },
                {
                    "name": "lo-0/0/0/10",
                    "type": "point-to-point",
                    "passive": "true"
                }
            ]
        }
    }
},
"bgp": {
    "domain-name": "CBNG2",
    "enforce-first-as": "disable",
    "hostname": "CBNG2",
    "local-as": 4200000001,
    "router-id": "192.1.0.2",
    "address-family": [
    {
        "afi": "ipv4",
        "safi": "unicast",
        "multipath": 10,
        "resolve-nexthop": {
            "safi": "labeled-unicast"
        },
        "redistribute": [
        {
            "source": "static",

```

```

        "policy": "SEND_AGGREGATED_V4"
    }
]
},
{
    "afi": "ipv6",
    "safi": "labeled-unicast"
},
{
    "afi": "ipv6",
    "safi": "unicast",
    "multipath": 10,
    "resolve-nexthop": {
        "safi": "labeled-unicast"
    },
    "redistribute": [
        {
            "source": "static",
            "policy": "SEND_AGGREGATED_V6"
        }
    ]
}
],
"peer": {
    "ipv4": [
        {
            "peer-address": "192.0.2.51",
            "update-source": "192.0.2.2",
            "peer-group": "send_aggregated"
        },
        {
            "peer-address": "198.51.100.10",
            "update-source": "192.0.2.2",
            "peer-group": "reflector"
        },
        {
            "peer-address": "198.51.100.20",
            "update-source": "192.0.2.2",
            "peer-group": "reflector"
        },
        {
            "peer-address": "198.51.100.30",
            "update-source": "192.0.2.2",
            "peer-group": "reflector"
        },
        {
            "peer-address": "198.51.100.40",
            "update-source": "192.0.2.2",
            "peer-group": "reflector"
        }
    ]
},
"peer-group": [
    {
        "pg-name": "reflector",
        "remote-as": 4200000001,
        "address-family": [
            {
                "afi": "ipv4",
                "safi": "unicast"
            },

```

```

        {
          "afi": "ipv6",
          "safi": "labeled-unicast"
        },
        {
          "afi": "ipv6",
          "safi": "unicast",
          "send-label": "true"
        }
      ]
    },
    {
      "pg-name": "send_aggregated",
      "remote-as": 4200000001,
      "address-family": [
        {
          "afi": "ipv4",
          "safi": "unicast"
        },
        {
          "afi": "ipv6",
          "safi": "labeled-unicast"
        },
        {
          "afi": "ipv6",
          "safi": "unicast",
          "send-label": "true"
        }
      ]
    }
  ],
  "ldp": {
    "router-id": "192.0.2.2",
    "interface": [
      {
        "name": "lag-2/10"
      },
      {
        "name": "lag-3/10"
      },
      {
        "name": "lo-0/0/0/10"
      }
    ]
  },
  "static": {
    "route": [
      {
        "ipv4": [
          {
            "prefix4": "11.100.0.0/16",
            "safi": "unicast",
            "nexthop-profile": "subscriber"
          },
          {
            "prefix4": "12.100.0.0/16",
            "safi": "unicast",
            "nexthop-profile": "subscriber"
          }
        ]
      }
    ]
  }
}

```

```

        "prefix4": "13.100.0.0/16",
        "safi": "unicast",
        "nexthop-profile": "subscriber"
    },
{
    "prefix4": "14.100.0.0/16",
    "safi": "unicast",
    "nexthop-profile": "subscriber"
},
{
    "prefix4": "15.100.0.0/16",
    "safi": "unicast",
    "nexthop-profile": "subscriber"
},
{
    "prefix4": "16.100.0.0/16",
    "safi": "unicast",
    "nexthop-profile": "subscriber"
},
{
    "prefix4": "17.100.0.0/16",
    "safi": "unicast",
    "nexthop-profile": "subscriber"
},
{
    "prefix4": "18.100.0.0/16",
    "safi": "unicast",
    "nexthop-profile": "subscriber"
},
{
    "prefix4": "19.100.0.0/16",
    "safi": "unicast",
    "nexthop-profile": "subscriber"
},
{
    "prefix4": "192.0.2.10/32",
    "safi": "unicast",
    "nexthop-profile": "rd_route"
},
{
    "prefix4": "192.0.2.100/32",
    "safi": "unicast",
    "nexthop-profile": "rd_route"
},
{
    "prefix4": "198.51.100.96/30",
    "safi": "unicast",
    "nexthop-profile": "radius"
},
{
    "prefix4": "20.100.0.0/16",
    "safi": "unicast",
    "nexthop-profile": "subscriber"
}
],
"ipv6": [
{
    "prefix6": "fc55::/16",
    "safi": "unicast",
    "nexthop-profile": "subscriber"
}
],

```

```

    {
      "prefix6": "fc56::/16",
      "safi": "unicast",
      "nexthop-profile": "subscriber"
    },
    {
      "prefix6": "fc66::/16",
      "safi": "unicast",
      "nexthop-profile": "subscriber"
    },
    {
      "prefix6": "fc67::/16",
      "safi": "unicast",
      "nexthop-profile": "subscriber"
    }
  ]
},
"nexthop-profile": [
  {
    "name": "radius",
    "nexthop": "192.0.2.51",
    "lookup-instance": "default",
    "lookup-afi": "ipv4",
    "lookup-safi": "labeled-unicast"
  },
  {
    "name": "rd_route",
    "nexthop": "192.0.2.1",
    "lookup-instance": "default",
    "lookup-afi": "ipv4",
    "lookup-safi": "labeled-unicast"
  },
  {
    "name": "subscriber",
    "exit-interface": "null0"
  }
]
}
],
"rtbrick-config:policy": {
  "statement": [
    {
      "name": "SEND_AGGREGATED_V4",
      "ordinal": [
        {
          "ordinal": 1,
          "match": {
            "rule": [
              {
                "rule": 1,
                "type": "ipv4-prefix",
                "value-type": "discrete",
                "match-type": "regex",
                "value": [
                  ".*/16"
                ]
              }
            ]
          }
        }
      ]
    }
  ]
}

```

```

        ]
    },
{
    "name": "SEND_AGGREGATED_V6",
    "ordinal": [
        {
            "ordinal": 1,
            "match": {
                "rule": [
                    {
                        "rule": 1,
                        "type": "ipv6-prefix",
                        "value-type": "discrete",
                        "match-type": "regex",
                        "value": [
                            ".*/16"
                        ]
                    }
                ]
            }
        }
    ]
},
"rtbrick-config:access": {
    "chassis-id": 2,
    "aaa-profile": [
        {
            "profile-name": "ipoe-aaa",
            "session-timeout": 0,
            "idle-timeout": 0,
            "aaa-radius-profile": "aaa-radius1",
            "authentication": {
                "order": "RADIUS"
            },
            "accounting": {
                "order": "RADIUS",
                "interim-interval": 30,
                "session-id-format": "DEFAULT"
            }
        }
    ],
    "radius-profile": [
        {
            "profile-name": "aaa-radius1",
            "nas-identifier": "192.0.2.2",
            "nas-port-type": "Ethernet",
            "authentication": {
                "radius-server-profile-name": [
                    "radius-srv1"
                ]
            },
            "accounting": {
                "radius-server-profile-name": [
                    "radius-srv1"
                ]
            }
        }
    ],
    "radius-server": [

```

```
{
    "server-name": "radius-srv1",
    "address": "198.51.100.98",
    "source-address": "192.0.2.2",
    "secret-encrypted-text": "$2b2feb12f730107454b1be6a0f8242b0f",
    "routing-instance": "default",
    "authentication": {
        "enable": "true",
        "timeout": 10
    },
    "accounting": {
        "enable": "true",
        "timeout": 10
    },
    "coa": {
        "enable": "true"
    }
},
"access-profile": [
{
    "profile-name": "ipoe",
    "protocol": {
        "dhcp": {
            "enable": "true",
            "lease-time": 3600
        },
        "dhcipv6": {
            "enable": "true",
            "lifetime": 3600
        }
    },
    "address-family": {
        "ipv4": {
            "enable": "true",
            "pool-name": "pool1",
            "instance": "default"
        },
        "ipv6": {
            "enable": "true",
            "pool-name": "pool1",
            "prefix-delegation-pool-name": "pool2",
            "instance": "default"
        }
    }
},
"interface": {
    "double-tagged": [
{
        "interface-name": "lag-1",
        "outer-vlan-min": 1001,
        "outer-vlan-max": 2000,
        "inner-vlan-min": 1001,
        "inner-vlan-max": 1100,
        "access-type": "IPoE",
        "access-profile-name": "ipoe",
        "aaa-profile-name": "ipoe-aaa",
        "gateway-ifl": "lo-0/0/0/10",
        "redundancy-session-id": 100
}
]
}
]
```

```
{
    "interface-name": "lag-11",
    "outer-vlan-min": 2001,
    "outer-vlan-max": 3000,
    "inner-vlan-min": 1001,
    "inner-vlan-max": 1100,
    "access-type": "IPoE",
    "access-profile-name": "ipoe",
    "aaa-profile-name": "ipoe-aaa",
    "gateway-ifl": "lo-0/0/0/10",
    "redundancy-session-id": 200
}
]
},
"pool": [
{
    "pool-name": "pool1",
    "ipv4-address": {
        "low": "16.100.128.1",
        "high": "20.100.128.255"
    },
    "ipv6-prefix": {
        "low": "fc66:100:1:1::1/128",
        "high": "fc66:100:1:2::5555/128"
    }
},
{
    "pool-name": "pool2",
    "ipv6-prefix": {
        "low": "fc67:100:1::/56",
        "high": "fc67:100:5000::/56"
    }
}
]
}
}
```

Appendix C: R-1 Configuration

Show R1 Configuration

```
{
    "ietf-restconf:data": {
        "rtbrick-config:system": {
            "load-last-config": "true"
        },
        "rtbrick-config:interface": [
            {
                "name": "hostif-0/0/0",
                "host-if": "R1-2-C1"
            },
            {
                "name": "hostif-0/0/1",
                "host-if": "R1-3-C1"
            },
            {
                "name": "hostif-0/0/2",
                "host-if": "R1-4-C1"
            }
        ]
    }
}
```

```

"host-if": "R1-14-R2",
"unit": [
{
    "unit-id": 10,
    "address": {
        "ipv4": [
            {
                "prefix4": "192.0.2.85/30"
            }
        ],
        "ipv6": [
            {
                "prefix6": "2001:db8::85/127"
            }
        ]
    }
},
{
    "name": "hostif-0/0/3",
    "host-if": "R1-16-RR",
    "unit": [
    {
        "unit-id": 10,
        "address": {
            "ipv4": [
                {
                    "prefix4": "192.0.2.93/30"
                }
            ],
            "ipv6": [
                {
                    "prefix6": "2001:db8::93/127"
                }
            ]
        }
    }
],
{
    "name": "hostif-0/0/4",
    "host-if": "R1-15-SN"
},
{
    "name": "lag-3",
    "unit": [
    {
        "unit-id": 10,
        "address": {
            "ipv4": [
                {
                    "prefix4": "192.0.2.70/30"
                }
            ],
            "ipv6": [
                {
                    "prefix6": "2001:db8::70/127"
                }
            ]
        }
    }
]
}

```

```

        }
    ],
},
{
    "name": "lo-0/0/0",
    "unit": [
        {
            "unit-id": 10,
            "address": {
                "ipv4": [
                    {
                        "prefix4": "192.0.2.3/32"
                    }
                ],
                "ipv6": [
                    {
                        "prefix6": "2001:db8::3/128"
                    }
                ]
            }
        }
    ]
},
"rtbrick-config:link-aggregation": {
    "interface": [
        {
            "interface-name": "lag-3",
            "mode": "lacp",
            "minimum-link-count": 1,
            "member-interface": [
                {
                    "member-interface-name": "hostif-0/0/0"
                },
                {
                    "member-interface-name": "hostif-0/0/1"
                }
            ]
        }
    ]
},
"rtbrick-config:instance": [
    {
        "name": "default",
        "protocol": {
            "isis": {
                "system-id": "1920.0000.2003",
                "area": [
                    "49.0002/24"
                ],
                "interface": [
                    {
                        "name": "hostif-0/0/2/10",
                        "type": "point-to-point",
                        "ldp-synchronization": "enable",
                        "level-2": {
                            "adjacency-disable": "true"
                        }
                    },
                    {
                        "name": "hostif-0/0/3/10",
                    }
                ]
            }
        }
    }
]
}

```

```

        "type": "point-to-point",
        "ldp-synchronization": "enable",
        "level-2": {
            "adjacency-disable": "true"
        }
    },
    {
        "name": "lag-3/10",
        "type": "point-to-point",
        "ldp-synchronization": "enable",
        "level-2": {
            "adjacency-disable": "true"
        }
    },
    {
        "name": "lo-0/0/0/10",
        "type": "point-to-point",
        "passive": "true"
    }
]
},
"ldp": {
    "router-id": "192.0.2.3",
    "interface": [
        {
            "name": "hostif-0/0/2/10"
        },
        {
            "name": "hostif-0/0/3/10"
        },
        {
            "name": "lag-3/10"
        },
        {
            "name": "lo-0/0/0/10"
        }
    ]
}
}
]
```

Appendix D: R-2 Configuration

Show R2 Configuration

```
{
    "ietf-restconf:data": {
        "rtbrick-config:system": {
            "load-last-config": "true"
        },
        "rtbrick-config:interface": [
            {
                "name": "hostif-0/0/0",
                "host-if": "R2-8-C2"
            }
        ]
    }
}
```

```
{
    "name": "hostif-0/0/1",
    "host-if": "R2-9-C2"
},
{
    "name": "hostif-0/0/2",
    "host-if": "R2-14-R1",
    "unit": [
        {
            "unit-id": 10,
            "address": {
                "ipv4": [
                    {
                        "prefix4": "192.0.2.86/30"
                    }
                ],
                "ipv6": [
                    {
                        "prefix6": "2001:db8::86/127"
                    }
                ]
            }
        }
    ]
},
{
    "name": "hostif-0/0/3",
    "host-if": "R2-18-RR",
    "unit": [
        {
            "unit-id": 10,
            "address": {
                "ipv4": [
                    {
                        "prefix4": "192.0.2.97/30"
                    }
                ],
                "ipv6": [
                    {
                        "prefix6": "2001:db8::97/127"
                    }
                ]
            }
        }
    ]
},
{
    "name": "hostif-0/0/4",
    "host-if": "R2-17-SN"
},
{
    "name": "lag-3",
    "unit": [
        {
            "unit-id": 10,
            "address": {
                "ipv4": [
                    {
                        "prefix4": "192.0.2.78/30"
                    }
                ],
            }
        }
    ]
}
```

```

        "ipv6": [
            {
                "prefix6": "2001:db8::78/127"
            }
        ]
    }
},
{
    "name": "lo-0/0/0",
    "unit": [
        {
            "unit-id": 10,
            "address": {
                "ipv4": [
                    {
                        "prefix4": "192.0.2.4/32"
                    }
                ],
                "ipv6": [
                    {
                        "prefix6": "2001:db8::4/128"
                    }
                ]
            }
        }
    ]
},
"rtbrick-config:link-aggregation": {
    "interface": [
        {
            "interface-name": "lag-3",
            "mode": "lacp",
            "minimum-link-count": 1,
            "member-interface": [
                {
                    "member-interface-name": "hostif-0/0/0"
                },
                {
                    "member-interface-name": "hostif-0/0/1"
                }
            ]
        }
    ],
    "rtbrick-config:instance": [
        {
            "name": "default",
            "protocol": {
                "isis": {
                    "system-id": "1920.0000.2004",
                    "area": [
                        "49.0002/24"
                    ],
                    "interface": [
                        {
                            "name": "hostif-0/0/2/10",
                            "type": "point-to-point",
                            "ldp-synchronization": "enable",
                            "label": "LDP Sync"
                        }
                    ]
                }
            }
        }
    ]
}

```

Appendix E: Edge Router Configuration

Show Edge Router Configuration

```
{  
    "ietf-restconf:data": {  
        "rtbrick-config:system": {  
            "load-last-config": "true"  
        }  
    }  
}
```

```

} ,
"rtbrick-config:interface": [
{
  "name": "hostif-0/0/0",
  "host-if": "RR-16-R1",
  "unit": [
    {
      "unit-id": 10,
      "address": {
        "ipv4": [
          {
            "prefix4": "192.0.2.94/30"
          }
        ],
        "ipv6": [
          {
            "prefix6": "2001:db8::94/127"
          }
        ]
      }
    }
  ]
},
{
  "name": "hostif-0/0/1",
  "host-if": "RR-18-R2",
  "unit": [
    {
      "unit-id": 10,
      "address": {
        "ipv4": [
          {
            "prefix4": "192.0.2.98/30"
          }
        ],
        "ipv6": [
          {
            "prefix6": "2001:db8::98/127"
          }
        ]
      }
    }
  ]
},
{
  "name": "hostif-0/0/2",
  "host-if": "RR-19-SN",
  "unit": [
    {
      "unit-id": 10,
      "address": {
        "ipv4": [
          {
            "prefix4": "192.0.2.129/30"
          }
        ],
        "ipv6": [
          {
            "prefix6": "2001:db8::129/127"
          }
        ]
      }
    }
  ]
}
]
}

```

```

        }
    },
    {
        "unit-id": 20,
        "vlan": 20,
        "address": {
            "ipv4": [
                {
                    "prefix4": "198.51.100.97/30"
                }
            ]
        }
    }
],
{
    "name": "lo-0/0/0",
    "unit": [
        {
            "unit-id": 10,
            "address": {
                "ipv4": [
                    {
                        "prefix4": "192.0.2.51/32"
                    }
                ],
                "ipv6": [
                    {
                        "prefix6": "2001:db8::51/128"
                    }
                ]
            }
        },
        {
            "unit-id": 20,
            "address": {
                "ipv4": [
                    {
                        "prefix4": "192.0.2.52/32"
                    }
                ],
                "ipv6": [
                    {
                        "prefix6": "2001:db8::52/128"
                    }
                ]
            }
        }
    ]
},
"rtbrick-config:instance": [
    {
        "name": "default",
        "protocol": {
            "isis": {
                "system-id": "1921.6800.1005",
                "area": [
                    "49.0002/24"
                ],
                "interface": [

```

```
{
    "name": "hostif-0/0/0/10",
    "type": "point-to-point",
    "ldp-synchronization": "enable",
    "level-2": {
        "adjacency-disable": "true"
    }
},
{
    "name": "hostif-0/0/1/10",
    "type": "point-to-point",
    "ldp-synchronization": "enable",
    "level-2": {
        "adjacency-disable": "true"
    }
},
{
    "name": "hostif-0/0/2/10",
    "type": "point-to-point",
    "ldp-synchronization": "enable",
    "level-2": {
        "adjacency-disable": "true"
    }
},
{
    "name": "lo-0/0/0/10",
    "type": "point-to-point",
    "passive": "true"
},
],
},
"bgp": {
    "domain-name": "aggregated_route",
    "hostname": "aggregated_route",
    "local-as": 4200000001,
    "router-id": "192.0.2.51",
    "address-family": [
        {
            "afi": "ipv4",
            "safi": "unicast",
            "multipath": 10,
            "resolve-nexthop": {
                "safi": "labeled-unicast"
            }
        },
        {
            "afi": "ipv6",
            "safi": "labeled-unicast"
        },
        {
            "afi": "ipv6",
            "safi": "unicast",
            "multipath": 10,
            "resolve-nexthop": {
                "safi": "labeled-unicast"
            }
        }
    ],
    "peer": {
        "ipv4": [
            {

```

```
        "peer-address": "192.0.2.1",
        "update-source": "192.0.2.51",
        "peer-group": "cbng"
    },
    {
        "peer-address": "192.0.2.2",
        "update-source": "192.0.2.51",
        "peer-group": "cbng"
    }
]
},
"peer-group": [
{
    "pg-name": "cbng",
    "remote-as": 4200000001,
    "address-family": [
        {
            "afi": "ipv4",
            "safi": "unicast"
        },
        {
            "afi": "ipv6",
            "safi": "labeled-unicast"
        },
        {
            "afi": "ipv6",
            "safi": "unicast",
            "send-label": "true"
        }
    ]
}
],
"ldp": {
    "router-id": "192.0.2.51",
    "interface": [
        {
            "name": "hostif-0/0/0/10"
        },
        {
            "name": "hostif-0/0/1/10"
        },
        {
            "name": "hostif-0/0/2/10"
        },
        {
            "name": "lo-0/0/0/10"
        }
    ]
}
}
]
```

Appendix E: BNG Blaster Configuration

Show BNG Blaster Configuration

```
{
  "interfaces": {
    "tx-interval": 1,
    "rx-interval": 1,
    "lag": [
      {
        "interface": "lag1",
        "lacp": true,
        "lacp-timeout-short": true
      },
      {
        "interface": "lag11",
        "lacp": true,
        "lacp-timeout-short": true
      }
    ],
    "links": [
      {
        "interface": "SN-5-C1",
        "lag-interface": "lag1"
      },
      {
        "interface": "SN-6-C1",
        "lag-interface": "lag1"
      },
      {
        "interface": "SN-7-C1",
        "lag-interface": "lag1"
      },
      {
        "interface": "SN-11-C2",
        "lag-interface": "lag1"
      },
      {
        "interface": "SN-12-C2",
        "lag-interface": "lag1"
      },
      {
        "interface": "SN-13-C2",
        "lag-interface": "lag1"
      },
      {
        "interface": "SN-20-C1",
        "lag-interface": "lag11"
      },
      {
        "interface": "SN-21-C1",
        "lag-interface": "lag11"
      },
      {
        "interface": "SN-22-C1",
        "lag-interface": "lag11"
      },
      {
        "interface": "SN-23-C2",
        "lag-interface": "lag11"
      }
    ]
  }
}
```

```

    },
    {
        "interface": "SN-24-C2",
        "lag-interface": "lag11"
    },
    {
        "interface": "SN-25-C2",
        "lag-interface": "lag11"
    }
],
"network": [
    {
        "interface": "SN-19-RR",
        "address": "192.0.2.130/30",
        "gateway": "192.0.2.129",
        "address-ipv6": "2001:db8::130",
        "gateway-ipv6": "2001:db8::129",
        "isis-instance-id": 1,
        "isis-level": 1,
        "ldp-instance-id": 1
    }
],
"access": [
    {
        "interface": "lag1",
        "type": "ipoe",
        "agent-remote-id": "CBNG1.RTBRICK.{session-global}",
        "outer-vlan-min": 1001,
        "outer-vlan-max": 2000,
        "inner-vlan-min": 1001,
        "inner-vlan-max": 1100
    },
    {
        "interface": "lag11",
        "type": "ipoe",
        "agent-remote-id": "CBNG2.RTBRICK.{session-global}",
        "outer-vlan-min": 2001,
        "outer-vlan-max": 3000,
        "inner-vlan-min": 1001,
        "inner-vlan-max": 1100
    }
]
},
"sessions": {
    "count": 20000,
    "max-outstanding": 800,
    "start-rate": 400,
    "stop-rate": 400
},
"access-line": {
    "agent-remote-id": "DEU.RTBRICK.{session-global}",
    "agent-circuit-id": "0.0.0.0/0.0.0.0 eth 0:{session-global}",
    "rate-up": 2000,
    "rate-down": 16384,
    "dsl-type": 5
},
"dhcp": {
    "enable": true
},
"dhcpv6": {
    "ldra": true,
}

```

```

    "enable": true
},
"session-traffic": {
    "ipv4-pps": 1,
    "ipv6-pps": 1,
    "ipv6pd-pps": 1,
    "autostart": false
},
"ldp": [
{
    "instance-id": 1,
    "lsr-id": "192.0.2.6",
    "keepalive-time": 30,
    "raw-update-file": "/home/supervisor/ldp_1000.ldp"
}
],
"isis": [
{
    "instance-id": 1,
    "area": [
        "49.0002/24"
    ],
    "system-id": "0204.0000.0001",
    "router-id": "192.0.2.6",
    "hostname": "BBL-RR",
    "hello-padding": true,
    "teardown-time": 30,
    "external": {
        "mrt-file": "/home/supervisor/isis_1000.mrt",
        "connections": [
            {
                "system-id": "0300.1001.0001",
                "ll-metric": 10
            }
        ]
    }
}
],
"bgp": [
{
    "__comment__": "RR1-C1-IPv4",
    "network-interface": "SN-19-RR",
    "local-ipv4-address": "198.51.100.10",
    "peer-ipv4-address": "192.0.2.1",
    "raw-update-file": "/home/supervisor/ipv4_nlri_nh1.bgp",
    "local-as": 4200000001,
    "peer-as": 4200000001
},
{
    "__comment__": "RR1-C1-IPv6",
    "network-interface": "SN-19-RR",
    "local-ipv4-address": "198.51.100.20",
    "peer-ipv4-address": "192.0.2.1",
    "raw-update-file": "/home/supervisor/ipv6_nlri_nh1.bgp",
    "local-as": 4200000001,
    "peer-as": 4200000001
},
{
    "__comment__": "RR1-C2-IPv4",
    "network-interface": "SN-19-RR",
    "local-ipv4-address": "198.51.100.10",

```

```

    "peer-ipv4-address": "192.0.2.2",
    "raw-update-file": "/home/supervisor/ipv4_nlri_nh1.bgp",
    "local-as": 4200000001,
    "peer-as": 4200000001
},
{
    "__comment__": "RR1-C2-IPv6",
    "network-interface": "SN-19-RR",
    "local-ipv4-address": "198.51.100.20",
    "peer-ipv4-address": "192.0.2.2",
    "raw-update-file": "/home/supervisor/ipv6_nlri_nh1.bgp",
    "local-as": 4200000001,
    "peer-as": 4200000001
},
{
    "__comment__": "RR2-C1-IPv4",
    "network-interface": "SN-19-RR",
    "local-ipv4-address": "198.51.100.30",
    "peer-ipv4-address": "192.0.2.1",
    "raw-update-file": "/home/supervisor/ipv4_nlri_nh2.bgp",
    "local-as": 4200000001,
    "peer-as": 4200000001
},
{
    "__comment__": "RR2-C1-IPv6",
    "network-interface": "SN-19-RR",
    "local-ipv4-address": "198.51.100.40",
    "peer-ipv4-address": "192.0.2.1",
    "raw-update-file": "/home/supervisor/ipv6_nlri_nh2.bgp",
    "local-as": 4200000001,
    "peer-as": 4200000001
},
{
    "__comment__": "RR2-C2-IPv4",
    "network-interface": "SN-19-RR",
    "local-ipv4-address": "198.51.100.30",
    "peer-ipv4-address": "192.0.2.2",
    "raw-update-file": "/home/supervisor/ipv4_nlri_nh2.bgp",
    "local-as": 4200000001,
    "peer-as": 4200000001
},
{
    "__comment__": "RR2-C2-IPv6",
    "network-interface": "SN-19-RR",
    "local-ipv4-address": "198.51.100.40",
    "peer-ipv4-address": "192.0.2.2",
    "raw-update-file": "/home/supervisor/ipv6_nlri_nh2.bgp",
    "local-as": 4200000001,
    "peer-as": 4200000001
}
]

```

Registered Address	Support	Sales
40268, Dolerita Avenue Fremont CA 94539		
+1-650-351-2251		+91 80 4850 5445
http://www.rtbrick.com	support@rtbrick.com	sales@rtbrick.com

©Copyright 2024 RtBrick, Inc. All rights reserved. The information contained herein is subject to change without notice. The trademarks, logos and service marks ("Marks") displayed in this documentation are the property of RtBrick in the United States and other countries. Use of the Marks are subject to RtBrick's Term of Use Policy, available at <https://www.rtbrick.com/privacy>. Use of marks belonging to other parties is for informational purposes only.